

HP-5101Wn





COPYRIGHT

Copyright © Edimax Technology Co., Ltd. all rights reserved. No part of this publication may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language, in any form or by any means, electronic, mechanical, magnetic, optical, chemical, manual or otherwise, without the prior written permission from Edimax Technology Co., Ltd.

Edimax Technology Co., Ltd. makes no representations or warranties, either expressed or implied, with respect to the contents hereof and specifically disclaims any warranties, merchantability, or fitness for any particular purpose. Any software described in this manual is sold or licensed as is. Should the programs prove defective following their purchase, the buyer (and not this company, its distributor, or its dealer) assumes the entire cost of all necessary servicing, repair, and any incidental or consequential damages resulting from any defect in the software. Edimax Technology Co., Ltd. reserves the right to revise this publication and to make changes from time to time in the contents hereof without the obligation to notify any person of such revision or changes.

The product you have purchased and the setup screen may appear slightly different from those shown in this QIG. For more information about this product, please refer to the user manual on the CD-ROM. The software and specifications are subject to change without notice. Please visit our website www.edimax.com for updates. All brand and product names mentioned in this manual are trademarks and/or registered trademarks of their respective holders.

Edimax Technology Co., Ltd.

Add: No. 3, Wu-Chuan 3rd Rd., Wu-Ku Industrial Park, New Taipei City, Taiwan

Tel: +886-2-77396888

Email: sales@edimax.com.tw

Notice According to GNU General Public License Version 2

This product includes software that is subject to the GNU General Public License version 2. The program is free software and distributed without any warranty of the author. We offer, valid for at least three years, to give you, for a charge no more than the costs of physically performing source distribution, a complete machine-readable copy of the corresponding source code.

CONTENTS


I.	PRODUCT INFORMATION	5
	I-1. Package Contents	5
	I-2. Hardware	5
	I-3. LED Status	6
	I-4. Safety Information	7
	I-5. System Requirements For Powerline Utility Software	7
II.	CREATING A POWERLINE NETWORK	8
	II-1. Hardware Installation	8
	II-2. iQ Setup	10
	II-3. WPS Setup	15
	II-4. Connecting to your HP-5101Wn	16
	II-5. Leaving a Powerline Network	18
	II-6. Resetting the Wireless Extender	18
III.	BROWSER BASED CONFIGURATION INTERFACE	19
	III-1. Home	21
	III-2. iQ Setup	23
	III-3. Basic Setting	24
	III-3-1. Security	26
	III-3-1-1. Disable	27
	III-3-1-1-1. 802.1x Authentication	27
	III-3-1-2. WEP	28
	III-3-1-2. WPA Pre-shared Key	29
	III-3-1-3. WPA Radius	30
	III-4. WPS Setting	32
	III-5. Wireless Advanced	34
	III-5-1. MAC Filtering	36
	III-6. System Utility	
	III-6-1. Time Setting	41
	III-6-2. Scheduling Setting	42
	II-7. Configuration Tool	45
	III-7-1. Diagnosis	47
	III-7-2. Firmware Upgrade	48
	III-7-3. Reboot	49
IV.	POWERLINE UTILITY SOFTWARE	50
	IV-1. Installation	50
	IV-1.1 Win 8	50
	IV-1.2 Win XP/Vista / 7	59
	IV-2. Using the Utility Software	65
	IV-2-1. Main Tab	65
	IV-2-2. Diagnostics Tab	66
	IV-2-3. About Tab	67
V	ADDENDLY	68

V-1.	Configuring your IP address68
V-1-1.	How to Configure Your Computer to Use a Dynamic IP Address68
V-1-1-1.	Windows XP69
V-1-1-2.	Windows Vista70
V-1-1-3.	Windows 772
IV-1-1-4.	Windows 874
V-1-1-5.	Mac OS78
V-1-2.	How to Modify the IP Address of Your PC or Macintosh80
V-1-2-1.	Windows XP80
V-1-2-2.	Windows Vista81
V-1-2-3.	Windows 782
V-1-2-4.	Windows 884
V-1-2-5.	Mac OS88
V-1-3.	How to Find Your Network Security Key90
V-1-3-1.	Windows 7 & Windows Vista90
V-1-3-2.	Windows 892
V-1-3-3.	Mac95
V-1-4.	How to Find Your Router's IP Address98
V-1-4-1.	Windows XP, Vista & 798
V-1-4-2.	Windows 899
V-1-4-3.	Mac101
V-2.	Troubleshooting
V-3.	Glossary105


I. PRODUCT INFORMATION

Before you start using this product, please check if there is anything missing in the package, and contact your dealer to claim the missing items(s):

I-1. Package Contents



I-2. Hardware



Item	Description
Ethernet Port	Connects HP-5101Wn to a computer or other network device via Ethernet cable.
WPS/Reset Button	Resets the HP-5101Wn to factory default settings or starts the WPS function. Reset: Press for over 10 seconds. WPS: Press for 2–5 seconds.

Group Button	Groups the HP-5101Wn with other Powerline devices to establish an encrypted Powerline network. Press for less than 3 seconds to join/establish a network, and 5–8 seconds to leave a Powerline network.
--------------	---

I-3. LED Status

LED	Color	LED Status	Description
WLAN	Green	Flashing	Wireless activity (transmitting or receiving data).
*	Green	Off	No wireless activity.
WPS		On	WPS connection established (LED remains on for one minute after the connection is made).
WPS	Green	Flashing	WPS in progress (waiting for another WPS device's connection).
		Off	No WPS in progress.
LAN		On	LAN port connected.
. 	Green	Flashing	LAN activity (transferring or receiving data).
		Off	LAN port not connected.
	C	Green with slow yellow flashing	Detecting Powerline connection.
PLC	Green & Yellow Flashing	Green with rapid yellow flashing	Powerline activity (transferring or receiving data).
		Off	No Powerline connection detected.
_		On	HP-5101Wn is on.
Power	Green	Flashing every 15 seconds	The HP-5101Wn is in power-saving mode.
		Off	HP-5101Wn is off.

I-4. Safety Information

In order to ensure the safe operation of the device and its users, please read and act in accordance with the following safety instructions.

- 1. The wireless extender is designed for indoor use only; do not place the wireless extender outdoors.
- 2. Do not place the wireless extender in or near hot/humid places, such as a kitchen or bathroom.
- 3. Do not pull any connected cable with force; carefully disconnect it from the wireless extender.
- 5. The device contains small parts which are a danger to small children under 3 years old. Please keep the wireless extender out of reach of children.
- 6. Do not place the wireless extender on paper, cloth, or other flammable materials. The wireless extender will become hot during use.
- 7. There are no user-serviceable parts inside the wireless extender. If you experience problems with the wireless extender, please contact your dealer of purchase and ask for help.
- 8. The wireless extender is an electrical device and as such, if it becomes wet for any reason, do not attempt to touch it without switching the power supply off. Contact an experienced electrical technician for further help.
- 9. If you smell burning or see smoke coming from the wireless extender then unplug the extender immediately, as far as it is safely possible to do so. Call your dealer of purchase for help.

I-5. System Requirements For Powerline Utility Software

Operating System	Utility supports Windows XP/Vista/7/8
CPU	Intel Pentium III 1.0GHz (or above)
RAM	256MB (or above)
Free Disk Space	100MB (or above)
Network Interface	Ethernet port (100Mbps or above) and an Ethernet cable

II. CREATING A POWERLINE NETWORK



A minimum of two Powerline devices are required to establish a Powerline network.




For best performance, plug Powerline adapters directly into standard wall sockets. Avoid using multi-socket adapters.




It may be convenient to install and configure your Powerline adapters in the same room, and then relocate the HP-5101Wn to its preferred location after setup is complete.

II-1. Hardware Installation

1. Connect one Powerline adapter to your router via Ethernet cable and plug it into a power socket. The power and LAN LEDs should display on.



2. Plug another Powerline adapter (HP-5101Wn) into a power socket, and confirm the power LED is on.



3. The PLC LED on both Powerline adapters should indicate first that they are detecting a Powerline connection, and then that a Powerline connection is established. See **LED Status** for HP-5101Wn LEDs.


4. Press the "Group" button button on each Powerline adapter for less than 3 seconds, within 2 minutes of each other. The adapters will automatically group together and generate an encrypted network.



You can now setup the HP-5101Wn's Wi-Fi using either <u>II-2. iQ Setup</u> or <u>II-3.</u> <u>WPS Setup</u>.

II-2. iQ Setup

1. Use a Wi-Fi device (e.g. computer, tablet, smartphone) to search for a Wi-Fi network with the SSID "Edimax.Setup" and connect to it.



2. Open a web browser and if you do not automatically arrive at the "Get Started" screen shown below, enter the URL http://edimax.setup. Select your language from the drop down menu and click "Get Started" to begin the setup process.





If you cannot access http://edimax.setup, please make sure your computer is set to use a dynamic IP address. If you are unsure, see V-1. Configuring your IP address.


3. Select "Obtain an IP address automatically" and then click "NEXT".





Advanced users who need to specify an IP address for the HP-5101Wn, select "Use the following IP address".

4. Please wait a moment.



5. Please enter a "MAIN ESSID" – this is a name to identify the HP-5101Wn's Wi-Fi network, which you will connect to from your wireless device. Then select a channel number ("Auto" is recommended) and enter a "Wi-Fi Security Password" between 8–64 characters, which is the password used to connect to the HP-5101Wn's Wi-Fi network. Click "Next" to continue.



Please do not forget your Wi-Fi password. If you do not wish to use a Wi-Fi password, check the box labeled "I don't want to set up the Wi-Fi password".



6. A summary of your HP-5101Wn's Wi-Fi settings will be displayed, as shown below. Click "NEXT" to continue and restart your HP-5101Wn.



7. Please wait while the HP-5101Wn restarts.



8. When the HP-5101Wn has restarted, the following "Congratulations" screen will be displayed, indicating that wireless setup is complete. Your HP-5101Wn's Wi-Fi should now be active and ready for use. If you need, you can relocate the HP-5101Wn to any power socket within 300m without additional configuration.



Refer to <u>II-4. Connecting to your HP-5101Wn</u> for help with connecting a Wi-Fi device to the extender's Wi-Fi.

II-3. WPS Setup

If your wireless router/access point supports WPS (Wi-Fi Protected Setup) then you can use this method to set up your HP-5101Wn's Wi-Fi network. WPS is an *alternative* to II-2.iQ Setup. The HP-5101Wn's Wi-Fi settings (including SSID) will be the same as your existing router/access point.

1. Press the WPS button (often the WPS/Reset button) on your router/access point to activate WPS.



Please check the instructions for your wireless router/access point for how long you need to hold down its WPS button to activate WPS. Take care not to hold the WPS button for too long – this may result in inadvertently resetting the extender or router/access point.

2. Within two minutes, press and hold the WPS button for 2–5 seconds on the HP-5101Wn to activate its WPS. The HP-5101Wn's WPS LED should flash to indicate a WPS connection is in progress.



3. The devices will establish a connection. The HP-5101Wn's WPS LED should display on to indicate a successful connection. You can now connect to the HP-5101Wn's wireless network with a Wi-Fi device, as described in II-4.
Connecting to your HP-5101Wn.


II-4. Connecting to your HP-5101Wn




The following steps 9-11 are an example of how to connect to a Wi-Fi network using Windows Vista. If you are using a different version of Windows, the process may vary slightly – please connect to a Wi-Fi network in the usual manner for operating system.


1. Click the network icon (connect to a network".

Local to a network icon (connect to a network icon (conne




2. Search for the SSID of your Wi-Fi network, click it and then click "Connect". If you set a password for your network, you will then be prompted to enter it.





3. After correctly entering your password, you will be successfully connected to your Wi-Fi network.

4. You can also use the Ethernet port on the underside of the HP-5101Wn to connect a computer or other device via Ethernet cable.



II-5. Leaving a Powerline Network

Press the **Group/Reset** button on the wireless extender for 5–8 seconds to leave a Powerline network that the extender is connected to. The extender will be disconnected/ungrouped from its network and ready to reconnect to any Powerline network.

II-6. Resetting the Wireless Extender

If you experience a problem with your HP-5101Wn you can reset the device back to its factory default settings. This resets **all** settings back to default.

Press and hold the WPS/Reset button for at least 10 seconds. The HP-5101Wn will re-initialize and the power LED ($^{\circ}$) will display on when the extender is ready (see *LED Status*).

III. BROWSER BASED CONFIGURATION INTERFACE

Once you have setup the wireless extender as detailed in <u>II. CREATING A</u>

<u>POWERLINE NETWORK</u> or the included **QIG**, you can further configure the settings of the wireless extender or run iQ Setup again using the browser based configuration interface.

To access the browser based configuration interface, enter http://edimax.setup into the URL bar of a web browser on a computer which is connected to the extender's Wi-Fi network. You will be prompted for a username and password. The default username is "admin" and the default password is "1234".




You will arrive the at Home page, use the menu on the left side of the screen to navigate. You can also change the language using the drop down menu in the top right corner.




- III-1. Home
- III-2. iQ Setup
- III-3. Basic Setting
- III-4. WPS Setting
- III-5. Wireless Advanced
- III-6. System Utility
- III-7. Configuration Tool

III-1. Home



The Home page shows the basic status and information of the wireless extender.





The screenshots shown in this manual are examples. The information you see on your screen will be unique to your configuration.

System		
Uptime	Displays the total passed time since the device was turned	

	on.
Hardware Version	Displays the hardware version.
Runtime Code	Displays the current firmware version.
Version	
Wireless Configura	ation
Mode	Displays the current wireless operating mode.
ESSID	Displays the current ESSID (the name used to identify the
	wireless extender).
Channel	Displays the current wireless channel number.
Number	
Security	Displays the current wireless security/encryption type.
BSSID (MAC)	Displays the device's MAC address. A MAC address is a
	unique, fixed ID for this device which cannot be modified.
Associated	Displays the number of clients connected to the wireless
Clients	extender. Click the "Show Active Clients" button to display
	active clients in a new window (see below for full
	description):
	Active Wireless Client Table
	This table shows the MAC address, transmitted packets, and received packet of each connected wireless client.
	Connected whereas chem.
	MAC Address Mode Tx Packets Rx Packets Tx Rate Power Expire (Mbps) saving Time
	00:1c:bf:10:cb:68 11g 35542 24837 54 no 300
	Refresh Close
LAN Settings	
IP Address	Displays the IP address of this device.
Subnet Mask	Displays the subnet mask of the IP address.
Default Catavasy	Displays the ID address of the default gateway
Default Gateway	Displays the IP address of the default gateway.

Active Wireless Client Table		
MAC Address	Displays the MAC address of the wireless client.	
Mode	Displays the transmission mode (802.11b, 802.11n or	
	802.11g).	
Tx Packet	Tx (transmission) packet counter.	
Rx Packet	Rx (received) packet counter.	
Tx Rate (Mbps)	Transmission rate is displayed here in Mbps.	
Power Saving	"Yes" or "No" is displayed here according to whether	
	power saving feature is active.	
Expired Time (s)	If the wireless client is idle for longer than the expired	

time, the access point will disassociate with it. When the wireless client becomes active, it will have to re-associate with the access point.

III-2. iQ Setup



To perform iQ Setup again and configure the Wi-Fi networks which the extender will connect to, select "iQ Setup".


You will see the screen below. Please click "Get Started" to begin iQ Setup and refer back to II. iQ
Setup onwards for further guidance.



III-3. Basic Setting



The "Basic Setting" page enables you to configure the ESSID, channel number and other basic parameters of the wireless extender.



Mode	The extender's mode cannot be configured – the
	default mode is "Access Point". The device acts as a
	wireless access point to a wired Ethernet network.
	Wireless clients can connect to the extender and
	exchange data with devices connected to the network.
Band	Select the wireless band you wish to use for the access
	point. The extender uses the 2.4GHz frequency band –
	select which wireless standard or combination of
	standards to use. Only wireless clients of the same

	band(s) will be able to connect.
MAIN ESSID	Specify an ESSID (the name used to identify the access
	point) of up to up to 32 alphanumerical characters.
	Please note that the ESSID is case sensitive.
AP Isolation	When this is set to "Enabled", wireless clients
	connected to this device will be able to access the
	Internet, but will not be able to communicate with each
	other. This applies to clients connected to the MAIN
	ESSID only.
SSID Isolation	When the access point uses multiple SSIDs and this is
	set to "Enabled", then wireless clients connected to the
	same SSID will be able to communicate with each
	other, but will not be able to communicate with other
	wireless clients connected to another of this access
	point's SSIDs. You can input a numeric VLAD ID value
	between 1 – 4094 for the MAIN ESSID.
Channel Number	Select a channel number for the wireless extender.
Associated Clients	Click the "Show Active Clients" button and a new
	window will appear which displays information about
	wireless clients connected to this access point. Click the
	"Refresh" button in the new window to refresh the list.

Click "APPLY" to save the changes. The following message will appear:



Click "CONTINUE" to save the changes and continue configuring other settings, or click "APPLY" to restart the system and make the changes take effect.

III-3-1. Security



The wireless extender provides a variety of wireless security options (data encryption) which can be configured on this page.

It is important to configure security to prevent intruders from accessing your local network and causing damage to computers and servers. Use complicated, hard-to-guess security keys which include combinations of letters and numbers and change your security key regularly.



SSID choice	Select which SSID's security settings to configure.
Encryption	Select an encryption type from the drop down menu
	and refer to the appropriate section (following) for
	more details.



WPA pre-shared key offers the highest level of security and is the recommended encryption type.

III-3-1-1. Disable

Select "Disable" to disable wireless encryption for the network. This is not recommended - anyone within range can connect to the device's SSID.

Enable 802.1x	Check this box to enable 802.1x user authentication.
Authentication	See below.


III-3-1-1. 802.1x Authentication

If you select "Disable" or "WEP" as your encryption type, you can check the "Enable 802.1x Authentication" box to enable 802.1x authentication based on a RADIUS user authentication server.



RADIUS Server IP	Enter the IP address of the RADIUS authentication
Address	server here.
RADIUS Server Port	Enter the port number of the RADIUS authentication
	server here. Default value is 1812.
RADIUS Server	Enter the password of the RADIUS authentication
Password	server here.

Click "APPLY" to save the changes. The following message will appear:




Click "CONTINUE" to save the changes and continue configuring other settings, or click "APPLY" to restart the system and make the changes take effect.

III-3-1-2. WEP


Wired Equivalent Privacy (WEP) is a basic encryption type.



WPA encryption is recommended — though some legacy wireless devices may only support WEP. WEP supports data rates up to a maximum 54Mbps.




Key Length	Select "64-bit" or "128-bit" key length. "128-bit" is safer than "64-bit" but will reduce some data transfer
	performance.
Key Format	Select "ASCII" or "Hex" key format. The key length will
	also be displayed here - ASCII and Hex keys vary in
	length depending on "Key Length" (above)".
Default Key	The value for "Default Key" is "Key 1" and cannot be
-	modified.
Encryption Key 1 to	Enter WEP key here, the number of characters must be
4	the same as the number displayed in the "Key Format"
	field. For "ASCII" key format, you can use any
	alphanumerical characters (0-9, a-z, and A-Z). For "Hex"
	format, you can use the characters 0-9, a-f, and A-F.
Enable 802.1x	Check this box to enable 802.1x user authentication.
Authentication	See III-1-1. Enable 802.1x Authentication.



Click "CONTINUE" to save the changes and continue configuring other settings, or click "APPLY" to restart the system and make the changes take effect.

III-3-1-2. WPA Pre-shared Key


WPA pre-shared key is the recommended and most secure encryption type.



WPA Unicast Cipher	Select from WPA (TKIP), WPA2 (AES) or WPA2 Mixed.
Suite	AES is safer than TKIP, but not supported by all wireless
	clients. WPA2(AES) or WPA2 is recommended if
	supported by your wireless client. Mixed is
	recommended if your client does not support AES.
Pre-shared Key	Select the pre-shared key format from "Passphrase" (8
Format	to 63 alphanumerical characters) or "Hex (64 characters
	0 to 9 and a to f.)
Pre-shared Key	Please enter the key according to the key format you
	selected above. For security reasons, it's best to use a
	complex, hard-to-guess key.



TKIP supports a maximum data rate of 54Mbps.



Click "CONTINUE" to save the changes and continue configuring other settings, or click "APPLY" to restart the system and make the changes take effect.

III-3-1-3. WPA Radius

WPA RADIUS is a combination of WPA encryption and RADIUS user authentication. If you have a RADIUS authentication server, you can authenticate the identity of every wireless client against a user database.



WPA Unicast Cipher Suite	Select from WPA (TKIP), WPA2 (AES) or WPA2 Mixed. AES is safer than TKIP, but not supported by all wireless clients. WPA2(AES) or WPA2 is recommended if supported by your wireless client. Mixed is recommended if your client does not support AES.
RADIUS Server IP address	Enter the IP address of the RADIUS authentication server here.
RADIUS Server Port	Enter the port number of the RADIUS authentication server here. Default value is 1812.
RADIUS Server Password	Enter the password of the RADIUS authentication server here.

Settings saved successfully! Click CONTINUE to continue other configuring settings, or click APPLY to restart the system and make the changes take effect. CONTINUE APPLY

Click "CONTINUE" to save the changes and continue configuring other settings, or click "APPLY" to restart the system and make the changes take effect.


III-4. WPS Setting



WPS (Wi-Fi Protected Setup) is a simple way to establish connections between WPS compatible devices. WPS devices feature a WPS function which can be activated by pushing a WPS button on the device or from within the device's firmware/configuration interface. When WPS is activated in the correct manner and at the correct time for two compatible devices, they will automatically connect.

By default, the WPS Settings page displays settings for WPS between your extender and a wireless client. For

WPS Setup between your extender and **router/access point**, please refer back to (II-3. WPS Setup).



The wireless extender supports two types of WPS for wireless clients: PBC (Push Button Configuration) and PIN code. For PBC you can activate WPS on the wireless extender by clicking the "Start PBC" button on the screen.



Click the "Start PBC" button to activate WPS - do not push the WPS/Reset button on the extender.

PIN code setup varies slightly in that it requires you to manually enter a PIN code into each device via the WPS Settings before activating WPS.

WPS Status	Displays "Configured" or "unConfigured" depending on whether WPS Settings for the extender have been configured or not, either manually or using the WPS button.
Device PIN Code	This is the WPS PIN code of the wireless extender for use with other WPS-enabled wireless devices.
SSID	Displays the current SSID (the name used to identify the wireless extender).
Authentication Mode	Displays the current wireless security/encryption type.
Passphrase Key	Shows the WPA passphrase here, though all characters will be replaced by asterisks for security reasons. If encryption is not set on the access point, this field will be blank.
Config Mode	The configuration mode of the extender's WPS setting is displayed here. "Registrar" means the device acts as an access point for a wireless client to connect to and the wireless client(s) will follow the extender's wireless settings. "Enrollee" means the device acts a wireless client and will follow the settings of the wireless router/access point.
Configure via Push Button	Click "Start PBC" to activate WPS on the extender.
Input Client PIN Code	Input the wireless client's PIN code here and click "Start PIN" to activate PIN code WPS. Refer to your wireless client's documentation if you are unsure of its PIN code.

The WPS LED () will flash slowly to indicate WPS is active. WPS will remain active for two minutes. Within two minutes, activate WPS on your client device (refer to client device's user manual for guidance on how to do so) in order to establish a connection. The WPS LED () will display ON to indicate a successful connection, and will remain ON for 5 minutes (see I-3. LED Status).


III-5. Wireless Advanced




In "Advanced Setting" you can configure the advanced features of the wireless extender. Please do not modify these settings unless you know what effect the changes will have on your access point; advanced settings are for experienced users only.



Changing these settings can adversely affect the performance of your wireless extender.



Fragment Threshold	Set the fragment threshold of the wireless radio. The default value is "2346".
RTS Threshold	Set the RTS threshold of the wireless radio. The default value is "2347".
Beacon Interval	Set the beacon interval of the wireless radio. The default value is "100".
DTIM Period	Set the DTIM period of wireless radio. The default value is "3".
Data Rate	Set the wireless data transfer rate. The default value is "Auto".
N Data Rate	Set the data rate of 802.11n. The default value is "Auto".
Channel Width	Select wireless channel width.
Preamble Type	Set the wireless radio preamble type.
Broadcast ESSID	Set if the access point will broadcast its own ESSID. To hide the ESSID of your extender select "Disable" - only users who know the ESSID of your access point will be able to connect.
WMM	WMM (Wi-Fi Multimedia) technology can improve the performance of certain network applications, such as audio/video streaming, network telephony (VoIP), and others. When WMM is enabled, the extender will prioritize different kinds of data and give higher priority to applications which require instant responses. This improves the performance of such network applications.
CTS Protect	Enabling this setting will reduce the chance of radio signal collisions between 802.11b and 802.11g wireless access points. It's recommended to set this option to "Auto".
TX Power	Set the power output of the wireless radio. Setting a lower power output, provided it is still sufficient for your range requirements, can potentially improve security since malicious/unknown users in distant areas will not be able to access your signal.



Click "CONTINUE" to save the changes and continue configuring other settings, or click "APPLY" to restart the system and make the changes take effect.

III-5-1. MAC Filtering



The MAC filtering feature allows you to define a list of wireless devices permitted to connect to this access point, identified by their unique MAC address. When a device which is not listed as a permitted MAC address attempts to connect to the extender, it will be denied.



Check the box "Enable Wireless Access Control" box to enables MAC address filtering.




Select SSID	Select which SSID to configure.
-------------	---------------------------------

MAC Address Filtering Table:


Select	Check this box to select MAC address(es).
Delete Selected	Click this button to delete selected MAC address(es).
Delete All	Delete all MAC addresses in the table.
Reset	Uncheck all selected MAC address entries.
Enable Wireless	Check this box to enable MAC address filtering.
Access Control	
MAC address	Enter a MAC address permitted to connect to the
	extender. Only enter characters 0 to 9 or a to f.
Comment	Enter an optional comment associated with the
	specified MAC address for reference/identification,
	consisting of up to 16 alphanumerical characters.
Add	Add the MAC address entry to the list.
Clear	Remove all characters in the "MAC address" and
	"Comments" fields.

Click "APPLY" to save the changes. The following message will appear:



Click "CONTINUE" to save the changes and continue configuring other settings, or click "APPLY" to restart the system and make the changes take effect.

III-6. System Utility



In "System Utility" you can configure the extender's administrative password and manage the extender's IP and DHCP settings.

Admii	strator	
	If you wish to customize the login information for your Access Point, please enter the new user name and password in the following columns. If you want to set up a DHCP server, you need to assign this device an unique IP address.	
	Password Settings:	
	Current Password :	
	New Password :	
	Re-Enter Password :	

You can change the password used to login to the browser-based configuration interface here. It is advised to do so for security purposes.

Current Password	Enter your current password. The default password is 1234 .
New Password	Enter your desired new password here. You can use any combination of letters, numbers and symbols up to 20 characters.
Re-Enter Password	Confirm your new password.

Management IP:	
	Obtain an IP address automatically
	 Use the following IP address
IP Address :	192.168.10.1
Subnet Mask :	255.255.255.0
Gateway Address :	192.168.2.1
DHCP Server :	
DHCP Server :	Disabled 🔻
Default Gateway :	192.168.10.1
Domain Name Server IP:	168.95.1.1
Start IP:	192.168.10.100
End IP:	192.168.10.200
Domain Name :	
Lease Time :	Forever +
A	APPLY Cancel

You can modify the IP address of the extender, enabling it to become a part of your local area network. To do so, input the IP address, subnet mask and gateway address into the corresponding fields.

IP Address	Specify an IP address here. This IP address will be assigned to your extender, and will replace the default IP address 192.168.10.1.
Subnet Mask	Input the subnet mask of the new IP address.
Gateway Address	Input the network's gateway IP address.
DHCP Server	Select "Enabled" if you wish to use the DHCP function
	of the extender, as detailed below.



Please write down and remember the new IP address you assigned to the wireless extender. If you forget this IP address

you may not be able to connect to the browser-based configuration interface in the future.



For static IP users, the wireless extender needs to have an IP address in the same subnet as your network, in order that you can access the browser based configuration interface. For example, if your static IP is 192.168.9.2 then you need to assign the wireless extender an IP address in the range 192.168.9.x where x = 3-254. Each network device has a unique IP address.



To ensure that you assign a correct IP address to the wireless extender, you can also check the IP address of your router. Please refer to V-1-4. How to Find your Router's IP Address. Your ISP can also provide you with such information as IP address, subnet mask and gateway address.




If you are unable to connect to the browser based **c**onfiguration interface using http://edimax.setup, it is possible that you assigned an incorrect IP address to the extender. In this case you can reset the wireless extender back to its default IP address. See <u>II-4. Resetting The Wireless</u> Extender.

The extender can be configured to act as a DHCP server for your network. By default DHCP is disabled. Enable DHCP by selecting "Enable" in the field "DHCP Server".


Default Gateway	Specify the IP address of the default gateway of your network here.
Domain Name	Input the IP address of the domain name server (DNS).
Server IP	
Start IP	Input the start address of the IP range.
End IP	Input the end address of the IP range.
Domain Name	Input the domain name for your network (optional).
Lease Time	Choose a lease time (the duration that every computer
	can keep a specific IP address) of every IP address
	assigned by the extender.

Click "APPLY" to save the changes. The following message will appear:




Click "CONTINUE" to save the changes and continue configuring other settings, or click "APPLY" to restart the system and make the changes take effect.

III-6-1. Time Setting




You can configure the time settings of your wireless extender here. The date and time of the device can be configured manually or can be synchronized with a time server.



Time Zone	Select the time zone of your country/region. If your country/region is not listed, please select another country/region whose time zone is the same as yours.
Time Server Address	The extender supports NTP (Network Time Protocol) for automatic time and date setup. Input the host name or IP address of the IP server manually.
Daylight Savings	If your country/region uses daylight saving time, please check the "Enable Function" box and select the start and end date.

Click "APPLY" to save the changes. The following message will appear:



Click "CONTINUE" to save the changes and continue configuring other settings, or click "APPLY" to restart the system and make the changes take effect.

III-6-2. Scheduling Setting




The wireless extender includes a scheduling function, where power saving functions and an automatic reboot can be automated for specific times. By default, scheduling setting is disabled. Please select "Enable" if you wish to continue.




Click "Add" to open a new window and create a new scheduled event.




Ensure that you have correctly configured the time settings of your wireless extender before enabling the scheduling function.






Service	Select the type of event to be scheduled. "Wireless off" will switch off wireless and "Auto reboot" will restart the device.
Schedule Description	Assign the event an optional name or description for reference.
Start Time	Specify a start time (hh.mm) for the event on one or more specified days.
End Time	Specify an end time (hh.mm) for the event, for a specific day or to recur every day.
Select	Check the box to select and confirm your event.

Click "Save" to save your scheduled event and then click "OK".




The scheduled event should now be listed. Up to 10 events can be scheduled.




Edit	Select the type of event to be scheduled. "Wireless off" will switch off wireless and "Auto reboot" will restart the device.
Delete	Assign the event an optional name or description for reference.

Click "APPLY" to save the changes. The following message will appear:




Click "CONTINUE" to save the changes and continue configuring other settings, or click "APPLY" to restart the system and make the changes take effect.

II-7. Configuration Tool



On the configuration tool page you can backup the extender's current settings, restore the settings to a previously saved version or reset the extender back to it's original, factory default state.






Restoring settings to the factory default will restore <u>all</u> settings, configurations and passwords back to the factory default.




You can also reset the device to factory defaults by pressing and holding the Reset/WPS button for at least 10 seconds. See <u>II-3. Resetting The Wireless Extender.</u>

Backup Settings	Click "Save" to save the current settings of the extender
	as a config.bin file to your specified location.
Restore Settings	Click the browse button to locate a previously saved
	config.bin file and then click "Upload" to upload the file
	and replace your current settings.
Restore to Factory	Click "Reset" to restore settings to the factory default.
Defaults	A pop-up window will appear and ask you to confirm,
	please click "Ok" and the extender will restart. A status
	bar will indicate the progress of the restart.

III-7-1. Diagnosis




Using the diagnosis tool, you can ping a specific IP address and automatically reboot the device if there is no response.



Watchdog and	Select "Enable" or "Disable" for the automatic reboot
reboot device	function.
Ping address	Specify the IP address to ping.
Time interval	Specify the frequency of the ping as a time interval, in
	minutes. Enter a value from 1-60.

III-7-2. Firmware Upgrade



The wireless extender's firmware upgrade feature allows you to upgrade the system firmware to a more recent version. You can download the latest firmware from the Edimax website.

Do not switch off or disconnect the access point during a firmware upgrade, as this could damage the device.




It is recommended that you use a wired Ethernet connection to upload the firmware file.





Browse	Click "Browse" to open a window and locate the
	firmware file.
CANCEL	Click "CANCEL" to cancel and clear the selected file
	from the "Browse" box.
APPLY	Click "APPLY" to upgrade to the selected firmware file.
	A pop up window will ask you to confirm, and inform
	you that the device may not respond for up to a minute
	after the upgrade. Please click "OK". A status bar will
	show the progress of the upgrade.

III-7-3. Reboot



If the wireless extender malfunctions or is not responding, then it is recommended that you reset the device. This feature is useful if the location of the access point is not convenient to physically use the hardware reset button.

A system reboot will restart the device without affecting existing settings.

If the wireless extender is still not responding after a reset, then switch off the device by disconnecting the power supply and wait for 10 seconds before reconnecting the power.



Reboot

In the event that the system stops responding correctly or stops functioning, you can perform a reset. Your settings will not be changed. Click the APPLY button below to reset the device. You will be asked to confirm the reset.

APPLY

APPLY

Click "APPLY" to reboot the system. You will be asked to confirm, and informed that the reboot may take a while. A status bar will indicate the progress..

IV. POWERLINE UTILITY SOFTWARE


The included CD-ROM contains Powerline utility software, which enables you to manage and configure your Powerline network in more detail. The utility enables you to manage all connected Powerline adapters.

IV-1. Installation



Before installating the utility software, please uninstall any existing Powerline utility software you may already have.

To install the utility software, insert the CD into your CD-ROM drive and the setup wizard should begin automatically. If not, please manually locate and open the "AutoRun.exe" file in the CD.



IV-1.1 Win 8


- **Step 1** Before installing the utility software, make sure that no other powerline utility is installed on your computer. If any other utility software is installed, uninstall it and reboot the computer.
- **Step 2** Insert the CD into your CD-ROM drive. When the following EZmax Wizard appears, select your model.




Step 3 Then click "Setup Utility".









Step 5 Click Compatibility tab and check "Run this program in compatibility mode for:", then select Windows 7, then click "Apply".




Step 6 Then click "WinPcap_4_1_2". The wizard will guide you through the setup process.



Step 7 When the following WinPcap Compatibility Assistant appears, select Run the program without getting help.











Step 8 After the installation is complete, click "Finish".




Step 9 Click the "Edimax PowerLine Utility", the "PLC 500Mbps Utility" appears, click "Next" to continue.






Step 10 Select where you want to install the utility software, and then click "Next".



Step 11 After the installation is complete, click "Close".



Step 12 An icon will appear on your desktop. Click the icon to open the utility software.



Note: You can manage all the connected powerline adapters with the utility software. However, installing the utility software is optional.

IV-1.2 Win XP/Vista / 7

- **Step 1** Before installing the utility software, make sure that no other powerline utility is installed on your computer. If any other utility software is installed, uninstall it and reboot the computer.
- **Step 2** Insert the CD into your CD-ROM drive. When the following EZmax Wizard appears, select your model.




Step 3 Then click "Setup Utility".




Step 4 If you have not installed WinPcap version 4.1.2 (or higher) on your computer before. The wizard will guide you through the setup process.












Step 5 When the "Edimax PowerLine Utility" setup wizard appears, click "Next" to continue.




Step 6 In the "License Agreement" screen, please select "I Agree" and then click "Next" to continue.




Step 7 Select where you want to install the utility software, and then click "Next".



Step 8 If you confirm to install the utility, click "Next".



Step 9 After the installation is complete, click "Close".



Step 10 An icon will appear on your desktop. Click the icon to open the utility software.




Note: You can manage all the connected powerline adapters with the utility software. However, installing the utility software is optional.

IV-2. Using the Utility Software


IV-2-1. Main Tab

The "Main" tab provides a list of powerline adapters connected to the network. The upper panel displays local powerline adapters. The lower panel displays remote powerline adapters in the network.



Set Name	Select a device and click "Set Name" to rename the
	device.
Enter Password	By default, this column is blank. Select a device and click
	"Enter Password" to set up a password for the device.
Scan	Click "Scan" and the utility software will perform an
	immediate scan of other remote powerline adapters. By
	default, the utility automatically scans every few seconds.

IV-2-2. Diagnostics Tab




The "Diagnostics" tab displays the system information and history of all remote devices.

The upper panel displays technical data concerning the software and hardware on the host computer and the lower panel displays the history of all remote devices.

IV-2-3. About Tab

The "About" tab contains some basic information about the software. You can also enable or disable the autoscan function under "Preferences".



V. APPENDIX

Configuring your IP address V-1.

Before you use the wireless extender, please make sure your computer is set to use a dynamic IP address. This means your computer can obtain an IP address automatically from a DHCP server. This is a simple procedure, which is explained step by step in V-1-1. How to configure your computer to use a dvnamic IP address.



Static IP users, please make a note of your static IP before you change it or switch to a dynamic IP address.

Unfortunately, not all networks support DHCP capability. In this case, you need to use a static IP address for the wireless extender and your PC or Macintosh. The wireless extender uses the default IP address 192.168.10.1, which may not be in the same IP address subnet of your network; meaning you are unable to access the browser based configuration interface. So, you need to modify the IP address of your PC or Macintosh to 192.168.10.x (x = 2 - 254) in order to access the browser-based configuration interface.

The procedure for doing so varies across different operating systems; please follow the guide appropriate for your operating system in <a>IV-1-2. How to modify the IP address of your PC or Macintosh.




Note: For guidance on how to assign a new IP address to the wireless extender, so that it is within the same IP address subnet of your network, please refer to III-6. System Utility. In cases where you need to modify the IP of your PC or Macintosh in order to access the browser based configuration interface, if the default IP of the wireless extender remains unchanged, you may need to repeat this process and modify the IP of your PC or Macintosh every time you wish to configure the wireless extender.

V-1-1. How to Configure Your Computer to Use a Dynamic IP Address


Please follow the instructions appropriate for your operating system.

V-1-1-1. Windows XP

1. Click the "Start" button (it should be located in the lower-left corner of your computer), then click "Control Panel". Double-click the "Network and Internet Connections" icon, click "Network Connections", and then double-click "Local Area Connection". The "Local Area Connection Status" window will then appear, click "Properties".




2. Select "Obtain an IP address automatically" and "Obtain DNS server address automatically", then click "OK".




V-1-1-2. Windows Vista

1. Click the "Start" button (it should be located in the lower-left corner of your computer), then click "Control Panel". Click "View Network Status and Tasks", then click "Manage Network Connections". Right-click "Local Area Network", then select "Properties". The "Local Area Connection Properties" window will then appear, select "Internet Protocol Version 4 (TCP / IPv4)", and then click "Properties".




2. Select "Obtain an IP address automatically" and "Obtain DNS server address automatically", then click "OK".



V-1-1-3. Windows 7

1. Click the "Start" button (it should be located in the lower-left corner of your computer), then click "Control Panel".




2. Under "Network and Internet" click "View network status and tasks".




3. Click "Local Area Connection".


View your basic network information and set up connections




4. Click "Properties".



5. Select "Internet Protocol Version 4 (TCP/IPv6) and then click "Properties".



3. Select "Obtain an IP address automatically" and "Obtain DNS server address automatically", then click "OK".




IV-1-1-4. Windows 8


1. From the Windows 8 Start screen, you need to switch to desktop mode. Move your curser to the bottom left of the screen and click.




2. In desktop mode, click the File Explorer icon in the bottom left of the screen, as shown below.




3. Right click "Network" and then select "Properties".




4. In the window that opens, select "Change adapter settings" from the left side.




5. Choose your connection and right click, then select "Properties".



6. Select "Internet Protocol Version 4 (TCP/IPv6) and then click "Properties".



4. Select "Obtain an IP address automatically" and "Obtain DNS server address automatically", then click "OK".



V-1-1-5. Mac OS



Note: Please ensure that your wireless extender is switched on and connected to your Macintosh via Ethernet cable before you begin.


1. Have your Macintosh computer operate as usual, and click on "System Preferences".




2. In System Preferences, click on "Network".



3. Here you will see all of your network connections. Network Preferences will now display an Ethernet adapter, as shown below. The status of "Ethernet" should be "Connected".



4. Click on "Ethernet" in the left panel and then click the drop down arrow for the menu labeled "Configure IPv4" in the right panel. From the drop down menu, select "Using DHCP" and then click "Apply".



V-1-2. How to Modify the IP Address of Your PC or Macintosh


Please follow the instructions appropriate for your operating system. In the following examples we use the IP address **192.168.10.20** though you can use any IP address in the range **192.168.9.x** (x = 3 - 254) in order to access the browser based configuration interface.



Note: Please make a note of your static IP before you change it. This is for your convenience if you wish to modify the IP address of the wireless extender in future. To modify the IP address of the wireless extender, please refer to III-6. System Utility.

V-1-2-1. Windows XP

1. Click the "Start" button (it should be located in the lower-left corner of your computer), then click "Control Panel". Double-click the "Network and Internet Connections" icon, click "Network Connections", and then double-click "Local Area Connection". The "Local Area Connection Status" window will then appear, click "Properties".



2. Select "Use the following IP address", then input the following values:




Note: Your existing static IP address will be displayed in the "IP address" field before you replace it. Please make a note of this IP address, subnet mask, default gateway and DNS server addresses.

IP address: 192.168.10.20 Subnet Mask: 255.255.255.0

Click 'OK' when finished.

V-1-2-2. Windows Vista

1. Click the "Start" button (it should be located in the lower-left corner of your computer), then click "Control Panel". Click "View Network Status and Tasks", then click "Manage Network Connections". Right-click "Local Area Network", then select "Properties". The "Local Area Connection Properties" window will then appear, select "Internet Protocol Version 4 (TCP / IPv4)", and then click "Properties".



2. Select "Use the following IP address", then input the following values:




Note: Your existing static IP address will be displayed in the "IP address" field before you replace it. Please make a note of this IP address, subnet mask, default gateway and DNS server addresses.

IP address: 192.168.10.20 Subnet Mask: 255.255.255.0

Click 'OK' when finished.

V-1-2-3. Windows 7

1. Click the "Start" button (it should be located in the lower-left corner of your computer), then click "Control Panel".




2. Under "Network and Internet" click "View network status and tasks".




3. Click "Local Area Connection".


View your basic network information and set up connections



4. Click "Properties".



5. Select "Internet Protocol Version 4 (TCP/IPv6) and then click "Properties".



6. Select "Use the following IP address", then input the following values:




Note: Your existing static IP address will be displayed in the "IP address" field before you replace it. Please make a note of this IP address, subnet mask, default gateway and DNS server addresses.

IP address: 192.168.10.20 Subnet Mask: 255.255.255.0


Click 'OK' when finished.

V-1-2-4. Windows 8


1. From the Windows 8 Start screen, you need to switch to desktop mode. Move your curser to the bottom left of the screen and click.




2. In desktop mode, click the File Explorer icon in the bottom left of the screen, as shown below.




3. Right click "Network" and then select "Properties".




4. In the window that opens, select "Change adapter settings" from the left side.



5. Choose your connection and right click, then select "Properties".



6. Select "Internet Protocol Version 4 (TCP/IPv4) and then click "Properties".



7. Select "Use the following IP address", then input the following values:



Note: Your existing static IP address will be displayed in the "IP address" field before you replace it. Please make a note of this IP address, subnet mask, default gateway and DNS server addresses.

IP address: 192.168.10.20 Subnet Mask: 255.255.255.0

Click 'OK' when finished.

V-1-2-5. Mac OS



Note: Please ensure that your wireless extender is switched on and connected to your Macintosh via Ethernet cable before you begin.


1. Have your Macintosh computer operate as usual, and click on "System Preferences"




2. In System Preferences, click on "Network".



3. Here you will see all of your network connections. Network Preferences will now display an Ethernet adapter, as shown below. The status of "Ethernet" should be "Connected".



4. Click on "Ethernet" in the left panel and then click the drop down arrow for the menu labeled "Configure IPv4" in the right panel. From the drop down menu, select "Manually".



5. In the panel on the right side, enter IP address 192.168.10.20 and subnet mask 255.255.255.0. Click on "Apply".



Note: Your existing static IP address will be displayed in the "IP address" field before you replace it. Please make a note of this IP address, subnet mask, router IP and DNS server address.

6. In the left sidebar, "Ethernet" should now display "Connected" as shown below. In the right panel, you should see the IP address 192.168.10.20 and subnet mask 255.255.255.0.

V-1-3. How to Find Your Network Security Key


To find your network security key, please follow the instructions appropriate for your operating system.




Note: If you are using Windows XP or earlier, please contact your ISP or router manufacturer to find your network security key.

V-1-3-1. Windows 7 & Windows Vista

1. Open "Control Panel" and click on "Network and Internet" in the top menu.




2. Click on "View network status and tasks" which is under the heading "Network and Sharing Center".




3. Click on "Manage wireless networks" in the left menu.



4. You should see the profile of your Wi-Fi network in the list. Right click on your Wi-Fi network and then click on "Properties".




5. Click on the "Security" tab, and then check the box labeled "Show characters". This will show your network security key. Click the "Cancel" button to close the window.




V-1-3-2. Windows 8


8. From the Windows 8 Start screen, you need to switch to desktop mode. Move your curser to the bottom left of the screen and click.




9. In desktop mode, click the network icon in the bottom right corner.



10. Select your Wi-Fi connection from the list and right click. Select "View connection properties".




11. In the window that opens, click the "Security" tab and check the box labeled "Show characters". Your network security key will be displayed in the field "Network security key".




V-1-3-3. Mac

1. Open a new Finder window, and select "Applications" from the menu on the left side. Open the folder labeled "Utilities" and then open the application "Keychain Access".




2. Select "Passwords" from the sub-menu labeled "Category" on the left side, as shown below. Then search the list in the main panel for the SSID of your network. In this example, the SSID is "EdimaxWireless" – though your SSID will be unique to your network.



3. Double click the SSID of your network and you will see the following window.



4. Check the box labeled "Show password" and you will be asked to enter your administrative password, which you use to log into your Mac. Enter your password and click "Allow".



Your network security password will now be displayed in the field next to the box labeled "Show password". In the example below, the network security password is "edimax1234". Please make a note of your network security password.




V-1-4. How to Find Your Router's IP Address


To find your router's IP address, please follow the instructions appropriate for your operating system.

V-1-4-1. Windows XP, Vista & 7

1. Go to "Start", select "Run" and type "cmd", then press Enter or click "OK".



2. A new window will open, type "ipconfig" and press Enter.



3. Your router's IP address will be displayed next to "Default Gateway".


```
_ D X
Administrator: C:\Windows\system32\cmd.exe
Ethernet adapter 區域連線:
   Connection-specific DNS Suffix .:
  Link-local IPv6 Address . . . . : fe80::4cdc:3e90:ba56:1722%9
  IPv4 Address. . . . . . . . . : 192.168.10.14
 192.168.10.254
Wireless LAN adapter 無線網路連線:
                               . . . : Media disconnected
  Media State . . . . . . . . : Media disconnection-specific DNS Suffix . : edimax.com
Tunnel adapter 區域連線* 6:
  Media State . . . . . . . . . : Media disconnected Connection—specific DNS Suffix . :
Tunnel adapter 區域連線* 7:
  Media State . . . . . . . . . : Media disconnected Connection-specific DNS Suffix . :
C:\Users\AlanChiu>_
```

V-1-4-2. Windows 8


1. From the Windows 8 Start screen, move your curser to the top right corner of the screen to display the Charms bar.




12. Click "Search" and enter "cmd" into the search bar. Click the "Command Prompt" app which be displayed on the left side.



13. A new window will open, type "ipconfig" and press Enter.




14. Your router's IP address will be displayed next to "Default Gateway".




V-1-4-3. Mac


- 1. Launch "System Preferences" and click on "Network".
- **2.** If you are using an Ethernet cable to connect to your network, your router's IP address will be displayed next to "Router".



3. If you are using Wi-Fi, click "Wi-Fi" in the left panel, and then "Advanced" in the bottom right corner.



4. Click the "TCP/IP" tab and your router's IP address will be displayed next to "Router".



V-2. Troubleshooting

If you are experiencing problems with your wireless extender, please refer to this troubleshooting guide before contacting your dealer of purchase for help.



Note: If you are experiencing problems immediately after a firmware upgrade, please contact your dealer of purchase for help.

Scenario	Solution
I can't log onto the browser-based configuration interface.	 a. Please check that the extender is correctly inserted into a power socket and check the LEDs on the front panel. If the extender is initializing after being switched off or restarted, wait for a 2 minutes and try again. b. Make sure you are using the full, correct URL: http://edimax.setup c. If you are using a MAC or IP address filter, try to connect the wireless extender using a different computer. d. Set your computer to obtain an IP address automatically (DHCP), and see if your computer can

	alatain an ID addus : :		
	obtain an IP address.		
	e. Ensure that all other Wi-Fi/Ethernet adapters are		
	disabled or disconnected.		
I can't log onto the browser-based	a. Password is case-sensitive. Make sure the "Caps		
	Lock" light is not illuminated.		
configuration	b. If you do not know your password, restore the		
interface: incorrect	device to factory settings.		
password.	16		
I can't establish a	a. If encryption is enabled, please re-check WEP or		
connection to my	WPA passphrase settings on your wireless client.		
wireless extender.	The password is case-sensitive. Make sure the		
	"Caps Lock" light is not illuminated.		
	b. Try moving closer to the wireless extender.		
	c. Switch off the extender and switch it back on after		
	10 seconds.		
	f. Please check that the extender is correctly inserted		
	into a power socket and check the LEDs on the front		
	panel.		
File downloads are	a. Reset the wireless extender		
very slow or	b. Try again later. Your local network may be		
frequently	experiencing technical difficulties or very high		
interrupted.	usage.		
	c. Change channel number.		
The wireless extender	a. It is normal for the wireless extender to heat up		
is extremely hot.	during frequent use. If you can safely place your		
	hand on the wireless extender, the temperature of		
	the device is at a normal level.		
	b. If you smell burning or see smoke coming from		
	wireless extender then disconnect the extender		
	immediately, as far as it is safely possible to do so.		
	Call your dealer of purchase for help.		
My network device	a. Ensure that your broadband router is fully		
can't access the	functional.		
Internet.	b. Switch off both your network device and wireless		
	extender and switch back on again.		
	c. Ensure that the wireless extender is powered on		
	(check the PWR LED).		
My network is using a	You can modify the IP address of the wireless bridge		
static IP address, how	using the browser based configuration interface.		
do I assign an IP	Please refer to III-6. System Utility.		
address to my			

V-3. Glossary

Default Gateway (Wireless bridge): Every non-access point IP device needs to configure a default gateway's IP address. When the device sends out an IP packet, if the destination is not on the same network, the device has to send the packet to its default gateway, which will then send it out towards the destination.

DHCP: Dynamic Host Configuration Protocol. This protocol automatically gives every computer on your home network an IP address.

DNS Server IP Address: DNS stands for Domain Name System, which allows Internet servers to have a domain name (such as www.Broadbandaccess point.com) and one or more IP addresses (such as 192.34.45.8). A DNS server keeps a database of Internet servers and their respective domain names and IP addresses, so that when a domain name is requested (as in typing "Broadbandaccess point.com" into your Internet browser), the user is sent to the proper IP address. The DNS server IP address used by the computers on your home network is the location of the DNS server your ISP has assigned to you.

DSL Modem: DSL stands for Digital Subscriber Line. A DSL modem uses your existing phone lines to transmit data at high speeds.

Ethernet: A standard for computer networks. Ethernet networks are connected by special cables and hubs, and move data around at up to 10/100 million bits per second (Mbps).

IP Address and Network (Subnet) Mask: IP stands for Internet Protocol. An IP address consists of a series of four numbers separated by periods, that identifies a single, unique Internet computer host in an IP network. Example: 192.168.2.1. It consists of 2 portions: the IP network address, and the host identifier.

ISP Gateway Address: (see ISP for definition). The ISP Gateway Address is an IP address for the Internet access point located at the ISP's office.

ISP: Internet Service Provider. An ISP is a business that provides connectivity to the Internet for individuals and other businesses or organizations.

LAN: Local Area Network. A LAN is a group of computers and devices connected together in a relatively small area (such as a house or an office). Your home network is considered a LAN.

MAC Address: MAC stands for Media Access Control. A MAC address is the hardware address of a device connected to a network. The MAC address is a unique identifier for a device with an Ethernet interface. It is comprised of two parts: 3 bytes of data that corresponds to the Manufacturer ID (unique for each manufacturer), plus 3 bytes that are often used as the product's serial number.

NAT: Network Address Translation. This process allows all of the computers on your home network to use one IP address. Using the broadband access point's NAT capability, you can access the Internet from any computer on your home network without having to purchase more IP addresses from your ISP.

Port: Network Clients (LAN PC) uses port numbers to distinguish one network application/protocol over another. Below is a list of common applications and protocol/port numbers:

Application	Protocol	Port Number
Telnet	ТСР	23
FTP	ТСР	21
SMTP	TCP	25
POP3	TCP	110
H.323	TCP	1720
SNMP	UCP	161
SNMP Trap	UDP	162
HTTP	TCP	80
PPTP	TCP	1723
PC Anywhere	ТСР	5631
PC Anywhere	UDP	5632

Access point: A access point is an intelligent network device that forwards packets between different networks based on network layer address information such as IP addresses.

Subnet Mask: A subnet mask, which may be a part of the TCP/IP information provided by your ISP, is a set of four numbers (e.g. 255.255.255.0) configured like an IP address. It is used to create IP address numbers used only within a particular network (as opposed to valid IP address numbers recognized by the Internet, which must be assigned by InterNIC).

TCP/IP, UDP: Transmission Control Protocol/Internet Protocol (TCP/IP) and Unreliable Datagram Protocol (UDP). TCP/IP is the standard protocol for data transmission over the Internet. Both TCP and UDP are transport layer protocol. TCP performs proper error detection and error recovery, and thus is reliable. UDP on the other hand is not reliable. They both run on top of the IP (Internet Protocol), a network layer protocol.

WAN: Wide Area Network. A network that connects computers located in geographically separate areas (e.g. different buildings, cities, countries). The Internet is a wide area network.

Web-based management Graphical User Interface (GUI): Many devices support a graphical user interface that is based on the web browser. This means the user can use the familiar Netscape or Microsoft Internet Explorer to Control/configure or monitor the device being managed.

Federal Communication Commission Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- 1. Reorient or relocate the receiving antenna.
- 2. Increase the separation between the equipment and receiver.
- 3. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- 4. Consult the dealer or an experienced radio technician for help.

FCC Caution

This device and its antenna must not be co-located or operating in conjunction with any other antenna or transmitter. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any changes or modifications not expressly approved by the party responsible for compliance could void the authority to operate equipment.

For product available in the USA/Canada market, only channel 1~11 can be operated. Selection of other channels is not possible.

This device is restricted to *indoor* use when operated in the 5.15 to 5.25 GHz frequency range.

- FCC requires this product to be used indoors for the frequency range 5.15 to 5.25 GHz to reduce the potential for harmful interference to co-channel Mobile Satellite systems.
- This device will not permit operations on channels 116-128 for 11na and 120-128 for 11a which overlap the 5600 -5650MHz band.

For a product that has the potential to be used in a body worn configuration and has not been certified with a specific accessory device(s):

"For body worn operation, this EUT name has been tested and meets FCC RF exposure guidelines when used with an accessory that contains no metal and that positions the handset a minimum of (specified distance) from the body. Use of other accessories may not ensure compliance with FCC RF exposure guidelines."

Federal Communications Commission (FCC) Radiation Exposure Statement

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.

R&TTE Compliance Statement

This equipment complies with all the requirements of DIRECTIVE 1999/5/EC OF THE EUROPEAN PARLIAMENT AND THE COUNCIL of March 9, 1999 on radio equipment and telecommunication terminal equipment and the mutual recognition of their conformity (R&TTE). The R&TTE Directive repeals and replaces in the directive 98/13/EEC (Telecommunications Terminal Equipment and Satellite Earth Station Equipment) As of April 8, 2000.

Safety

This equipment is designed with the utmost care for the safety of those who install and use it. However, special attention must be paid to the dangers of electric shock and static electricity when working with electrical equipment. All guidelines of this and of the computer manufacture must therefore be allowed at all times to ensure the safe use of the equipment.

EU Countries Intended for Use

The ETSI version of this device is intended for home and office use in Austria, Belgium, Bulgaria, Cyprus, Czech, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Turkey, and United Kingdom. The ETSI version of this device is also authorized for use in EFTA member states: Iceland, Liechtenstein, Norway, and Switzerland.

EU Countries Not Intended for Use

None



Edimax Technology co., Ltd 6F., No.3, Wu-Chuan 3rd Road, Wu-Gu, New Taipei **Edimax Technology Europe B.V.** Nijverheidsweg 25 5683 CJ Best The Netherlands **Edimax Computer Company** 3350 Scott Blvd., Bldg.15 Santa Clara, CA 95054, USA Free Manuals Download Website

http://myh66.com

http://usermanuals.us

http://www.somanuals.com

http://www.4manuals.cc

http://www.manual-lib.com

http://www.404manual.com

http://www.luxmanual.com

http://aubethermostatmanual.com

Golf course search by state

http://golfingnear.com

Email search by domain

http://emailbydomain.com

Auto manuals search

http://auto.somanuals.com

TV manuals search

http://tv.somanuals.com