

# Digital Cinema Series

Theater Optimized Plasma

FPP-61HD20

FPP-50HD20

FPP-42HD20

## Operation Manual

For the specifications of your plasma monitor  
refer to the Model Information manual





# Important Information


## Precautions


Please read this manual carefully before using your plasma monitor and keep the manual handy for future reference.

**CAUTION**

RISK OF ELECTRIC SHOCK  
DO NOT OPEN

CAUTION: TO REDUCE THE RISK OF ELECTRIC SHOCK, DO NOT REMOVE COVER. NO USER-SERVICEABLE PARTS INSIDE. REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.

 This symbol warns the user that uninsulated voltage within the unit may have sufficient magnitude to cause electric shock. Therefore, it is dangerous to make any kind of contact with any part inside of this unit.

 This symbol alerts the user that important literature concerning the operation and maintenance of this unit has been included. Therefore, it should be read carefully in order to avoid any problems.

**WARNING**

TO PREVENT FIRE OR SHOCK HAZARDS, DO NOT EXPOSE THIS UNIT TO RAIN OR MOISTURE. ALSO DO NOT USE THIS UNIT'S POLARIZED PLUG WITH AN EXTENSION CORD RECEPTACLE OR OTHER OUTLETS, UNLESS THE PRONGS CAN BE FULLY INSERTED. REFRAIN FROM OPENING THE CABINET AS THERE ARE HIGH-VOLTAGE COMPONENTS INSIDE. REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.

## Warnings and Safety Precaution

This plasma monitor is designed and manufactured to provide long, trouble-free service. No maintenance other than cleaning is required. Please see the section "Plasma monitor cleaning procedure" on the next page.

The plasma display panel consists of fine picture elements (cells) with more than 99.99 percent active cells. There may be some cells that do not produce light or remain lit.

For operating safety and to avoid damage to the unit, read carefully and observe the following instructions. To avoid shock and fire hazards:

1. Provide adequate space for ventilation to avoid internal heat build-up. Do not cover rear vents or install the unit in a closed cabinet or shelves.  
If you install the unit in an enclosure, make sure there is adequate space at the top of the unit to allow hot air to rise and escape. If the monitor becomes too hot, the overheat protector will be activated and the monitor will be turned off. If this happens, turn off the power to the monitor and unplug the power cord. If the room where the monitor is installed is particularly hot, move the monitor to a cooler location, and wait for 60 minutes to cool the monitor. If the problem persists, contact your dealer for service.
2. Do not use this unit's polarized plug with extension cords or outlets unless the prongs can be completely inserted.
3. Do not expose the unit to water or moisture.
4. Avoid damage to the power cord, and do not attempt to modify the power cord.
5. Unplug the power cord during electrical storms or if the unit will not be used over a long period.
6. Do not open the cabinet which has potentially dangerous high voltage components inside. If the unit is damaged in this way the warranty will be void. Moreover, there is a serious risk of electric shock.
7. Do not attempt to service or repair the unit. The manufacturer is not liable for any bodily harm or damage caused if unqualified persons attempt service or open the back cover. Refer all service to authorized Service Centers.

---

To avoid damage and prolong operating life:

1. **Use only with 120V50/60Hz AC power.**  
Continued operation at line voltages greater than 120 Volts AC will shorten the life of the unit, and might even cause a fire hazard.
2. Handle the unit carefully when installing it and do not drop.
3. Set the unit away from heat, excessive dust, and direct sunlight.
4. Protect the inside of the unit from liquids and small metal objects. In case of accident, unplug the power cord and have it serviced by an authorized Service Center.
5. Do not hit or scratch the panel surface as this causes flaws on the surface of the screen.
6. For correct installation and mounting it is strongly recommended to use a trained, authorized dealer.
7. As is the case with any phosphor-based display (like a CRT monitor, for example) light output will gradually decrease over the life of a Plasma Display Panel.
8. To avoid sulfurization it is strongly recommended not to place the unit in a dressing room in a public bath or hot spring bath.

Plasma monitor cleaning procedure:

1. Use a soft dry cloth to clean the front panel and bezel area. Never use solvents such as alcohol or thinner to clean these surfaces.
2. Clean plasma ventilation areas with a vacuum cleaner with a soft brush nozzle attachment.
3. To ensure proper ventilation, cleaning of the ventilation areas must be carried out monthly. More frequent cleaning may be necessary depending on the environment in which the plasma monitor is installed.

Recommendations to avoid or minimize phosphor burn-in: Like all phosphor-based display devices and all other gas plasma displays, plasma monitors can be susceptible to phosphor burn under certain circumstances. Certain operating conditions, such as the continuous display of a static image over a prolonged period of time, can result in phosphor burn if proper precautions are not taken. To protect your investment in this plasma monitor, please adhere to the following guidelines and recommendations for minimizing the occurrence of image burn:

- \* Always enable and use your computer's screen saver function during use with a computer input source.
- \* Display a moving image whenever possible.
- \* Change the position of the menu display from time to time.
- \* Always power down the monitor when you are finished using it.

If the plasma monitor is in long term use or continuous operation take the following measures to reduce the likelihood of phosphor burn:

- \* Lower the Brightness and Contrast levels as much as possible without impairing image readability.
- \* Display an image with many colors and color gradations (i.e. photographic or photo-realistic images).
- \* Create image content with minimal contrast between light and dark areas, for example white characters on black backgrounds. Use complementary or pastel color whenever possible.
- \* Avoid displaying images with few colors and distinct, sharply defined borders between colors.

**\* Note:** Burn-in is not covered by the warranty.


Contact your dealer for other recommended procedures that will best suit your particular application needs.

# Recommandations importantes


## Précautions

Veillez lire avec attention ce manuel avant d'utiliser le moniteur à plasma et le conserver accessible pour s'y référer ultérieurement.


**ATTENTION**




**RISQUE D'ELECTROCUTION  
NE PAS OUVRIR**



MISE EN GARDE: AFIN DE REDUIRE LES RISQUES D'ELECTROCUTION, NE PAS DEPOSER LE COUVERCLE, IL N'Y A AUCUNE PIECE UTILISABLE A L'INTERIEUR DE CET APPAREIL. NE CONFIER LES TRAVAUX D'ENTRETIEN QU'A UN PERSONNEL QUALIFIE.

 Ce symbole a pour but de prévenir l'utilisateur de la présence d'une tension dangereuse, non isolée se trouvant à l'intérieur de l'appareil. Elle est d'une intensité suffisante pour constituer un risque d'électrocution. Eviter le contact avec les pièces à l'intérieur de cet appareil.

 Ce symbole a pour but de prévenir l'utilisateur de la présence d'importantes instructions concernant l'entretien et le fonctionnement de cet appareil. Par conséquent, elles doivent être lues attentivement afin d'éviter des problèmes.

**AVERTISSEMENT**

AFIN DE REDUIRE LES RISQUES D'INCENDIE OU D'ELECTROCUTION, NE PAS EXPOSER CET APPAREIL A LA PLUIE OU A L'HUMIDITE. AUSSI, NE PAS UTILISER LA FICHE POLARISEE AVEC UN PROLONGATEUR OU UNE AUTRE PRISE DE COURANT SAUF SI CES LAMES PEUVENT ETRE INSEREES A FOND. NE PAS OUVRIR LE COFFRET, DES COMPOSANTS HAUTE TENSION SE TROUVENT A L'INTERIEUR. LAISSER A UN PERSONNEL QUALIFIE LE SOIN DE REPARER CET APPAREIL.

## Mises en garde et précautions de sécurité

Ce moniteur à plasma a été conçu et fabriqué pour une utilisation fiable et durable. Il ne nécessite aucun entretien en dehors du nettoyage. Voir la section "Méthode de nettoyage du moniteur à plasma" plus loin. Le panneau à affichage plasma est constitué de fines particules d'images (cellules) dont plus de 99,99% sont actives. Certaines d'entre elles ne produisent pas de lumière ou restent allumées.

Pour des raisons de sécurité et pour éviter d'endommager l'appareil, lire attentivement les instructions suivantes.

Pour éviter les risques d'électrocution et d'incendie:

1. Laisser suffisamment d'espace autour de l'appareil pour la ventilation et éviter toute augmentation excessive de la température interne. Ne pas couvrir les événements ou l'installer dans un endroit trop exigü.  
Si vous installez l'appareil dans un espace clos, assurez-vous qu'il y ait suffisamment d'espace au dessus pour permettre à l'air chaud de s'élever et de s'évacuer. Si la température du moniteur devient excessive, la protection contre les surchauffes entrera en action et coupera l'alimentation. Dans ce cas, éteindre l'appareil et débrancher le câble d'alimentation. Si la température de la pièce dans laquelle se trouve le moniteur est particulièrement élevée, déplacer celui-ci dans un endroit plus frais et attendre environ 60 minutes qu'il refroidisse. Si le problème persiste, prendre contact avec votre revendeur.
2. Ne pas raccorder la prise d'alimentation polarisée de ce périphérique à une rallonge ou une prise murale si les fiches ne peuvent pas être complètement insérées.
3. Ne pas exposer à l'eau ou à l'humidité.
4. Eviter d'endommager le cordon d'alimentation, et ne pas modifier le cordon d'alimentation.
5. Débrancher le câble d'alimentation électrique pendant les orages ou les longues périodes d'inactivité.
6. Ne pas ouvrir le coffret. Des composants de haute tension se trouvent à l'intérieur. Si l'appareil est endommagé de cette manière, la garantie devient caduque. De plus, il y a un risque d'électrocution.
7. Ne pas essayer d'intervenir ou de réparer l'appareil. Le fabricant décline toute responsabilité en cas de blessure corporelle ou de dégâts matériels résultant d'une opération d'entretien quelconque effectuée par des personnes non qualifiées ou résultant de l'ouverture du couvercle arrière. S'adresser aux services après-vente autorisés.

---

Pour éviter des dommages et prolonger la durée de service de l'appareil:

1. N'utiliser qu'une source d'alimentation de 120 V 50/60 Hz CA. Le fait d'utiliser l'appareil en continu à des tensions de ligne supérieures à 120 Volts CA réduit sa durée de vie et risque de provoquer un incendie.
2. Manipuler l'appareil avec soin pendant son déplacement et ne pas le faire tomber.
3. Eloigner l'appareil des endroits chauds, très poussiéreux et exposés en plein soleil.
4. Eviter que des liquides et des petits objets métalliques pénètrent à l'intérieur de l'appareil. En cas d'incident de ce genre, débrancher le câble d'alimentation électrique et confier le moniteur à un service après-vente agréé.
5. Ne pas frapper ou rayer la surface de la écran plasma, car des défauts risquent de se produire sur la surface de la écran plasma.
6. Pour un montage et une installation correcte, il est fortement recommandé de faire appel à un revendeur agréé et qualifié.
7. Comme c'est le cas pour tout affichage à base de phosphore (comme un moniteur CRT, par exemple), la puissance de lumière baisse graduellement au cours de la vie du Panneau d'Affichage à Plasma.
8. Pour éviter tout risque de sulfuration, il est fortement conseillé de ne pas installer l'appareil dans un vestiaire, un bain public ou un bain de source thermale.

Méthode de nettoyage du moniteur à plasma:

1. Nettoyer le panneau avant et le cadre en procédant à l'aide d'un chiffon doux et sec. Ne jamais utiliser de solvants du type alcool ou diluant pour le nettoyage de ces surfaces.
2. Nettoyer les prises d'aération du plasma en procédant à l'aide d'une brosse à poils doux fixée à un aspirateur.
3. Pour garantir la bonne ventilation du moniteur, nettoyer les prises d'air tous les mois. Un nettoyage plus fréquent peut s'avérer nécessaire selon les conditions environnantes dans lesquelles le moniteur à plasma est utilisé.

Pour éviter les risques de brûlage du luminophore, les mesures suivantes sont recommandées:

Comme tous les périphériques d'affichage à base luminophore et tous les autres affichages gaz plasma, les moniteurs plasma peuvent être sujets au brûlage du luminophore dans certaines circonstances. Certaines conditions d'utilisation, telles que l'affichage continu d'une image statique pour une durée prolongée, peuvent causer le brûlage du luminophore si aucune précaution n'est prise. Pour protéger votre investissement dans ce moniteur à plasma, veuillez suivre les directives et les conseils suivantes pour minimiser l'occurrence le marquage de l'écran:

- Assurez-vous de mettre en marche et d'utiliser l'économisateur d'écran chaque fois que c'est possible lorsque vous l'utilisez avec une source d'entrée d'ordinateur.
- Affichez une image en mouvement aussi souvent que possible.
- Changez la position de l'affichage de menu de temps à autre.
- Coupez toujours l'alimentation lorsque vous avez terminé d'utiliser la moniteur.

Si le moniteur est en usage continu ou longue durée, prenez les mesures suivantes afin d'éviter l'occurrence le brûlage du luminophore:

- Abaissez le niveau de l'image (contraste, luminosité) autant que possible, sans faire perdre la lisibilité de l'image.
- Affichez une image avec de nombreuses couleurs et graduations de couleur (par ex. des images photographiques ou photo-réalistes).
- Créez un contenu d'image avec un contraste minimal entre les zones sombres et les zones claires, par exemple, des caractères blancs sur un fond noir. Utilisez des couleurs complémentaires ou pastels le plus souvent possible.
- Évitez d'afficher des images avec peu de couleurs et des limites nettes et clairement définies entre les couleurs.

\* **Remarque:** Le brûlage de l'écran n'est pas couvert par la garantie.

Contactez un revendeur agréé ou un revendeur de marque pour d'autres procédures qui conviendront le mieux à vos besoins particuliers.

# Contents

<b>How to Attach Options to the Plasma Monitor .... 1</b>	
Ventilation Requirements for enclosure mounting ..... 1	
How to use the safety metal fittings and the screws for safety metal fittings ..... 1	
<b>Part Names and Function ..... 2</b>	
Front View ..... 2	
Rear View / Terminal Board ..... 3	
Remote Control ..... 4	
Battery Installation and Replacement ..... 5	
Using the wired remote control mode ..... 6	
Operating Range ..... 6	
Handling the remote control ..... 6	
<b>Installation ..... 7</b>	
Connecting the video processor ..... 7	
Connecting video sources ..... 8	
Pin Assignments and Signal Levels for 15 pin RGB (Analog) ..... 9	
Pin Configuration and Signal Levels of the RGB 3 Connector (DVI Connector) ..... 9	
<b>Basic Operations ..... 11</b>	
POWER ..... 10	
VOLUME ..... 10	
MUTE ..... 10	
DISPLAY ..... 10	
DIGITAL ZOOM ..... 10	
AUTO ADJUST ..... 10	
OFF TIMER ..... 11	
<b>WIDE Operations ..... 12</b>	
Wide Screen Operation (manual) ..... 12	
Wide Screen Operation with Computer Signals ..... 13	
When "PICTURE SIZE" is set to "OFF" ..... 13	
<b>OSM Controls ..... 14</b>	
Menu Operations ..... 14	
Menu Tree ..... 15	
Picture Settings Menu ..... 17	
Reducing noise in the picture ..... 18	
Setting the color temperature ..... 18	
Adjusting the color to the desired level ..... 18	
Changing the Gamma Curve ..... 19	
Making the Low Tone adjustments ..... 19	
Adjusting the colors ..... 20	
Audio Settings Menu ..... 20	
Setting the allocation of the audio connectors ..... 22	
Image Adjust Settings Menu ..... 21	
Option1 Settings Menu ..... 22	
Setting the on-screen menu ..... 22	
Setting the BNC connectors ..... 23	
Checking the signal being transmitted to RGB1 terminal ..... 23	
Setting a computer image to the correct RGB select screen ..... 23	
Setting high definition images to the suitable screen size ..... 24	
Setting the Input Skip ..... 24	
Option2 Settings Menu ..... 25	
Setting the power management for computer images ..... 25	
POWER/STANDBY indicator ..... 26	
Reducing burn-in of the screen ..... 26	
Setting the gray level for the sides of the screen ..... 29	
Option3 Settings Menu ..... 31	
Using the timer ..... 31	
Setting the power on mode ..... 32	
Enabling/disabling the front panel controls ..... 33	
Enabling/disabling remote control wireless transmission ..... 33	
Loop Out setting ..... 34	
ID number setting ..... 34	
Video Wall setting ..... 35	
Advanced OSM Settings Menu ..... 38	
Language Settings Menu ..... 39	
Color System Settings Menu ..... 39	
Source Information Menu ..... 39	
<b>External Control ..... 40</b>	
<b>Troubleshooting ..... 41</b>	

# How to Attach Options to the Plasma Monitor

You can attach your optional mounts or stand to the plasma monitor in one of the following two ways:

- \* While it is upright. (See Drawing A)
- \* As it is laid down with the screen face down (See Drawing B). Lay the protective sheet, which was wrapped around the monitor when it was packaged, beneath the screen surface so as not to scratch the screen face.
- \* Do not touch or hold the screen face when carrying the unit.

• This device cannot be installed on its own. Be sure to use a stand or original mounting unit. (Wall mount unit, Stand, etc.)


\* See the inside of the cover page.

• For correct installation and mounting it is strongly recommended to use a trained, authorized dealer.

Failure to follow correct mounting procedures could result in damage to the equipment or injury to the installer.


Product warranty does not cover damage caused by improper installation.

\* Use only the mounting kit or stand provided by manufacturer and listed under Options.



## Ventilation Requirements for enclosure mounting


To allow heat to disperse, leave space between surrounding objects as shown on the diagram below when installing.



## How to use the safety metal fittings and the screws for safety metal fittings


These are fittings for fastening the unit to a wall to prevent tipping due to external shock when using the stand (optional). Fasten the safety fittings to the holes in the back of the monitor using the safety fitting mount screws.

\* Safety metal fittings will differ according to the model.



# Part Names and Function

## Front View




- ① **Power**  
Turns the monitor's power on and off.
- ② **Remote sensor window**  
Receives the signals from the remote control.
- ③ **POWER/STANDBY indicator**  
When the power is on ..... Lights green.  
When the power is in the standby mode ... Lights red.
- ④ **INPUT SELECT / EXIT**  
Switches the input, in the following order.  
The available inputs depend on the setting of "BNC INPUT".  
RGB:  VIDEO1  VIDEO2  VIDEO3  HD/DVD/DTV   
 RGB/PC3  RGB/PC2  RGB/PC1
- ⑤ **LEFT/- and RIGHT/+**  
Enlarges or reduces the image. Functions as the CURSOR (◀/▶) buttons in the On-Screen Menu (OSM) mode.
- ⑥ **VOLUME DOWN and UP**  
Adjusts the volume. Functions as the CURSOR (▲/▼) buttons in the On-Screen Menu (OSM) mode.
- ⑦ **MENU/ENTER**  
Sets the On-Screen Menu (OSM) mode and displays the main menu.

Functions as the EXIT buttons in the On-Screen Menu (OSM) mode.



## Rear View/ Terminal Board



### A AC IN

Connect the included power cord here.

### B EXT SPEAKER L and R

Connect speakers (optional) here. Maintain the correct polarity. Connect the  $\oplus$  (positive) speaker wire to the  $\oplus$  EXT SPEAKER terminal and the  $\ominus$  (negative) speaker wire to the  $\ominus$  EXT SPEAKER terminal on both LEFT and RIGHT channels. Please refer to your speaker's owner's manual.

### C VIDEO1, 2, 3 (BNC, RCA, S-Video)

Connect VCR's, DVD's or Video Cameras, to the video processor.

### D AUDIO1, AUDIO2, AUDIO3

These are audio input terminals. The input is selectable. Set which video image to allot them from the audio menu screen.

### E DVD1 / HD1

Connect DVDs to the video processor.

### F RGB2/ DVD2/ HD2

RGB2: You can connect an analog RGB signal and the synchronization signal.

DVD2/ HD2: You can connect DVDs, High Definition sources, Laser Discs, etc. here.

This input can be set for use with an RGB or component source. (see page 24)

### G RGB1 (mini D-Sub 15pin)

Connect an analog RGB signal from a computer, etc. here. This input can be used for Input or Output. (see page 10)

### H RGB3 (DVI 24pin)

Connect the video processor here

### I EXTERNAL CONTROL

This terminal is used when operating and controlling the monitor externally (by external control).

### J REMOTE IN


Connect the remote cable\* to the remote control's remote jack to obtain wired remote control.

### K REMOTE OUT

Connect the remote cable\* to the REMOTE IN jack of the other display monitor to obtain wired remote control.

\* The 1/8 Stereo Mini cable must be purchased separately.

## Remote Control



### 1 POWER ON/STANDBY

Switches the power on/standby.  
(This does not operate when POWER/STANDBY indicator of the main unit is off.)

### 2 RGB/PC

Press this button to select RGB/PC as the source.  
The available sources depend on the setting of "BNC INPUT".

RGB:  RGB/PC1  RGB/PC2  RGB/PC3

COMP.:  RGB/PC1  RGB/PC3

RGB/PC can also be selected using the INPUT SELECT button on the monitor.

### 3 DVD / HD

Press this button to select DVD/HD as the source.  
The available sources depend on the setting of "BNC INPUT".

RGB: HD/DVD/DTV

COMP.:  HD1/DVD1/DTV1  HD2/DVD2/DTV2

DVD/HD can also be selected using the INPUT SELECT button on the monitor.

### 4 VIDEO

Press this button to select VIDEO as the source.

VIDEO1  VIDEO2  VIDEO3

VIDEO can also be selected using the INPUT SELECT button on the monitor.

### 5 MENU/ENTER

Press this button to access the OSM controls.  
Press this button during the display of the main menu to go to the sub menu.

### 6 CURSOR (▲ / ▼ / ◀ / ▶)

Use these buttons to select items or settings and to adjust settings or switch the display patterns.

### 7 EXIT

Press this button to exit the OSM controls in the main menu. Press this button during the display of the sub menu to return to the previous menu.

### 8 POINTER

Press this button to display the pointer.

### 9 ZOOM (+/-)

Enlarges or reduces the image.

### 10 VOLUME (+/-)

Adjusts the audio volume.

### 11 MUTE

Mutes the sound.

### 12 WIDE

Automatically detects the signal and sets the aspect ratio.  
Wide button is not active for all signals.

### 13 DISPLAY

Displays the source settings on the screen.

### 14 OFF TIMER

Activates the off timer for the unit.

**15 MULTI**

Not functional for the models covered in this manual.

**16 SELECT**

Not functional for the models covered in this manual.

**17 AUTO ADJUST**

Press this button to adjust Fine Picture, Picture ADJ, Position, and Contrast automatically, or to switch the screen size to ZOOM mode automatically with the superimposed caption displayed fully only when the picture contains dark areas above and below the picture.

**18 ID SELECT**

Set the ID number in the remote control. The remote control can then be used only for a display with the same ID number. When several displays are used together they can be controlled individually.

**19 CLEAR**

Clears the number set by the ID SELECT button.

**20 Remote control signal transmitter**

Transmits the remote control signals.


**21 Remote Jack**

Insert the plug of the remote cable (The 1/8 Stereo Mini cable) here when using the supplied remote control in the wired condition.


**Battery Installation and Replacement**

Insert the 2 “AAA” batteries, making sure to set them in with the proper polarity.


1. Press and open the cover.



2. Align the batteries according to the (+) and (-) indication inside the case.




3. Replace the cover.



### Using the wired remote control mode


Connect the remote cable\* to the remote control's remote jack and the "REMOTE IN" terminal on the monitor. When the cable is connected, the mode automatically switches to wired remote control. When the wired remote control mode is used, the remote control can be operated even if no batteries are loaded.



\* The 1/8 Stereo Mini cable must be purchased separately.

### Operating Range


- \* Use the remote control within a distance of about 7 m / 23ft. from the front of the monitor's remote control sensor and at horizontal and vertical angles of up to approximately 30°.
- \* The remote control operation may not function if the monitor's remote control sensor is exposed to direct sunlight or strong artificial light, or if there is an obstacle between the sensor and the remote control.



### Handling the remote control

- Do not drop or mishandle the remote control.
- Do not get the remote control wet. If the remote control gets wet, wipe it dry immediately.
- Avoid heat and humidity.
- When not using the remote control for a long period, remove the batteries.
- Do not use new and old batteries together, or use different types together.
- Do not take apart the batteries, heat them, or throw them into a fire.
- When using the remote control in the wireless condition, be sure to unplug the remote cable from the REMOTE IN terminal on the monitor.

# Installation



Notes: All standard sources (480i) connect to the Faroudja processor. High scan rate sources such as HDTV or PC can either be sent as a pass-through via the processor or connected directly to the plasma with the alternate inputs.

Notes on HDCP with DVI: This plasma is not compatible with HDCP encryption for DVI HDTV from satellite receivers. When a HDTV channel is to be viewed that has HDCP, view the channel via the analog outputs to the processor as pass-through to the analog outputs of the processor.

# Connections

---

## VIDEO PROCESSOR

The primary connection from the video processor to the display is the DVI cable. If an analog signal will be used through the pass-through on the processor (HDTV or PC, for example), the analog RGBHV cables should also be connected.

## SOURCES

**DVD** – Connect the S-video or component signals to the processor. Interlaced signals are preferred over progressive.

**VHS** – Connect the composite signal to the processor.

**Video Game** – Connect the composite or S-video signal to the processor.

### Standard Satellite Receiver

(Non-HDTV) – Connect the S-video signal to the processor.

**HDTV Satellite Receiver** – Connect the S-video signal to the processor. For the HDTV signals there are three options:

1. Connect the YPrPb or RGB signals directly to the alternate inputs of the plasma
2. Connect the YPrPb signal to the BNC inputs on the processor.
3. Connect the YPrPb or RGB signals to the D15 connector on the processor.


When viewing non-HDTV channels use the S-video connector for best results.

**HDTV Satellite Receiver with DVI** – Connect both the DVI cable and the analog YPrPb cables to either the video processor (pass-through) or directly to the plasma.

When viewing HDTV channels with HDCP (copy protection encoding), use the analog signals from the satellite receiver to view the image. Also use the Analog RGBHV signals from the processor.

**Computer Signals** – Connect the RGB to either the D15 on the processor or connect directly to the plasma.

## Pin Assignments and Signal Levels for 15 pin RGB (Analog)




Pin No.	Signal (Analog)
1	Red
2	Green or sync-on-green
3	Blue
4	No connection
5	Ground
6	Red ground
7	Green ground
8	Blue ground
9	No connection
10	Sync signal ground
11	No connection
12	Bi-directional DATA (SDA)
13	Horizontal sync or Composite sync
14	Vertical sync
15	Data clock

## Pin Configuration and Signal of the RGB 3 Connector (DVI Connector)

The unit is equipped with a type of connector commonly used for digital.

(This cannot be used for an analog input.)  
(TMDS can be used for one link only.)

### RGB 3



Pin No.	Signal (Digital)
1	T.M.D.S Data 2 -
2	T.M.D.S Data 2 +
3	T.M.D.S Data 2 Shield
4	No connection
5	No connection
6	DDC Clock
7	DDC Data
8	No connection
9	T.M.D.S Data 1 -
10	T.M.D.S Data 1 +
11	T.M.D.S Data 1 Shield
12	No connection
13	No connection
14	+5V Power
15	Ground
16	Hot Plug Detect
17	T.M.D.S Data 0 -
18	T.M.D.S Data 0 +
19	T.M.D.S Data 0 Shield
20	No connection
21	No connection
22	T.M.D.S Clock Shield
23	T.M.D.S Clock +
24	T.M.D.S Clock -

# Basic Operations

## POWER

### To turn the unit ON and OFF:

1. Plug the power cord into an active AC power outlet.
2. Press the Power button (on the unit).  
The monitor's POWER/STANDBY indicator turns red and the standby mode is set.
3. Press the POWER ON button (on the remote control) to turn on the unit.  
The monitor's POWER/STANDBY indicator will light up (green) when the unit is on.
4. Press the POWER STANDBY button (on the remote control) or the Power button (on the unit) to turn off the unit.  
The monitor's POWER/STANDBY indicator turns red and the standby mode is set (only when turning off the unit with the remote control).

## VOLUME

### To adjust the sound volume:

1. Press and hold the VOLUME ⊕ button (on the remote control or the unit) to increase to the desired level.
2. Press and hold the VOLUME ⊖ button (on the remote control or the unit) to decrease to the desired level.

## MUTE

### To cancel the sound:

Press the MUTE button on the remote control to cancel the sound; press again to restore.

## DISPLAY

### To check the settings:


1. The screen changes each time the DISPLAY button is pressed.
2. If the button is not pressed for approximately three seconds, the menu turns off.

## DIGITAL ZOOM

Digital zoom specifies the picture position and enlarges the picture.

1. Press the POINTER button to display the pointer. (  )

### To change the size of the picture:

Press the ZOOM+ button and enlarge the picture.  
The pointer will change to resemble a magnifying glass. (  )  
A press of the ZOOM- button will reduce the picture and return it to its original size.

### To change the picture position:

Select the position with the ▲▼◀▶ buttons.

2. Press the POINTER button to delete the pointer.

## AUTO ADJUST

### To adjust the size or quality of the picture automatically:

Press the AUTO ADJUST button.

### Information

#### ■ AUTO ADJUST ON setting

When RGB (still picture) input is selected ..... Fine Picture, Picture ADJ, Position, and Contrast will be adjusted automatically.

When RGB (motion picture), VIDEO, or Y/Pb/Pr (component) input is selected ..... The screen size switches to ZOOM mode automatically with the superimposed caption displayed fully only when the picture contains dark areas above and below the picture.



---


## OFF TIMER

### To set the off timer:

The off timer can be set to turn the power off after 30, 60, 90 or 120 minutes.

1. Press the OFF TIMER button to start the timer at 30 minutes.
2. Press the OFF TIMER button to the desired time.
3. The timer starts when the menu turns off.

← 30 γ 60 γ 90 γ 120 γ 0 →



### To check the remaining time:

1. Once the off timer has been set, press the OFF TIMER button once.
2. The remaining time is displayed, then turns off after a few seconds.
3. When five minutes remain the remaining time appears until it reaches zero.



### To cancel the off timer:

1. Press the OFF TIMER button twice in a row.
2. The off timer is canceled.



### Note:

*After the power is turned off with the off timer ...  
A slight current is still supplied to the monitor. When you are leaving the room or do not plan to use the system for a long period of time, turn off the power of the monitor.*

# WIDE Operations

## Wide Screen Operation (manual)

With this function, you can select one of six screen sizes.

### When viewing videos or digital video discs

1. Press the WIDE button on the remote control.
2. *Within 3 seconds ...*

Press the WIDE button again.


The screen size switches as follows:

γ NORMAL γ FULL γ STADIUM γ ZOOM γ 2.35:1 γ 14:9

When a 720P or 1080I signal is input:

FULL ε 2.35:1


### NORMAL size screen (4:3)



The normal size screen is displayed.

- \* The picture has the same size as video pictures with a 4 : 3 aspect ratio.


### FULL size screen



The image is expanded in the horizontal direction.

- \* Images compressed in the horizontal direction (“squeezed images”) are expanded in the horizontal direction and displayed on the entire screen with correct linearity. (Normal images are expanded in the horizontal direction.)


### STADIUM size screen



The picture is expanded in the horizontal and vertical directions at different ratios.

- \* Use this for watching normal video programs (4:3) with a wide screen.


### ZOOM size screen




The picture is expanded in the horizontal and vertical direction, maintaining the original proportions.

- \* Use this for theater size (wide) movies, etc.

### 2.35:1 size screen



Original image




Information is lost on both sides.

The squeezed film image is expanded to fulfill the entire screen at a ratio of 2.35:1. Black bands do not appear at the top and bottom but information is lost on the left and right margins.

- \* This feature is available when the input signal is video, component (480I, 480P, 576I, 576P, 720P, 1080I) or RGB (525P or 625P signal from a scan converter).
- \* If black bands appear on the top and bottom in the full size screen, select the 2.35:1 size screen to avoid phosphor burn-in.

### 14:9 size screen



The image is displayed at a 14:9 aspect ratio.

- \* This feature is available when the input signal is video, component (480I, 480P, 576I, 576P) or RGB (525P or 625P signal from a scan converter).

### Note:

*Do not allow the displayed in 4:3 mode for an extended period. This can cause a phosphor burn-in.*

## Wide Screen Operation with Computer Signals

Switch to the wide screen mode to expand the 4 : 3 image to fill the entire screen.

1. Press the WIDE button on the remote control.


2. Within 3 seconds ...

Press the WIDE button again.

The screen size switches as follows:


⌈ **NORMAL** ⌋ **FULL** **ZOOM**

NORMAL size screen (4:3 or SXGA 5:4)




The picture has the same size as the normal computer image.

FULL size screen




The image is expanded in the horizontal direction.

ZOOM size screen



When wide signals are input.

FULL size screen




### When "PICTURE SIZE" is set to "OFF"

\* This cannot be set in some models. "TRUE size" will not be displayed in such cases.

The screen size switches as follows:


⌈ **TRUE** ⌋ **FULL** **ZOOM**

TRUE size screen (VGA, SVGA 4:3)




The image is true resolution.

FULL size screen




The image is expanded in the horizontal and vertical direction.

ZOOM size screen




When wide signals are input.

TRUE



The image is true resolution.

FULL



### Information

#### ■ Supported resolution

See page 7 of Model Information for details on the display output of the various VESA signal standards supported by the monitor.

#### ■ "PICTURE SIZE" setting

When the setting of "PICTURE SIZE" is OFF, the size of RGB-input pictures will be TRUE in place of NORMAL.

#### ■ When 852 (848) dot × 480 line wide VGA\* signals with a vertical frequency of 60 Hz and horizontal frequency of 31.7 (31.0) kHz are input

Select an appropriate setting for RGB SELECT mode referring to the "Table of Signals Supported" on page 7 of Model Information.

\* "VGA", "SVGA" and "SXGA" are registered trademarks of IBM, Inc. of the United States.

### Note:

Do not allow the displayed in 4:3 mode for an extended period. This can cause a phosphor burn-in.


# OSM(On Screen Menu) Controls

## Menu Operations

The OSM window is displayed with respect to the screen as shown on the diagram.



\* Depending on the screen's mode, the OSM may be displayed differently.

In the explanation, the OSM section is shown close up.




The following describes how to use the menus and the selected items.

1. Press the MENU/ENTER button on the remote control to display the MAIN MENU.



2. Press the cursor buttons ▲ ▼ on the remote control to highlight the menu you wish to enter.

3. Press the MENU/ENTER button on the remote control to select a sub menu or item.



4. Adjust the level or change the setting of the selected item by using the cursor buttons ◀ ▶ on the remote control.

5. The adjustments or the settings that are stored in memory.

The change is stored until you change it again.


6. Repeat steps 2 – 5 to adjust an additional item, or press the EXIT button on the remote control to return to the main menu.

**Note:** The main menu disappears by pressing the EXIT button.

## Information

### Advanced menu mode

When “ADVANCED OSM” is set to “ON” in the main menu (1/2), full menu items will be shown.



## Menu Tree

■ : Shaded areas indicate the default value.

-β γ + : Press the ◀ or ▶ button to adjust. The default value is at the center.

▭ : Menu items in a ruled box are available when the ADVANCED OSM is set to ON.

Main menu	Sub menu	Sub menu 2	Sub menu 3	Sub menu 4	RESET	REFERENCE	
PICTURE	CONTRAST	-β γ +			YES	18	
	BRIGHTNESS	-β γ +			YES	18	
	SHARPNESS	-β γ +			YES	18	
	COLOR	-β γ +			YES	18	
	TINT	-β γ +			YES	18	
	PICTURE MODE	BRIGHT/NORMAL/THEAT.1/THEAT.2/DEFAULT			YES	18	
	NR	OFF/NR-1/NR-2/NR-3			YES	19	
	COLOR TEMP	LOW/MID LOW/MID/HIGH			YES	19	
	WHITE BALANCE	GAIN RED	-β γ +			YES	19
		GAIN GREEN	-β γ +			YES	19
		GAIN BLUE	-β γ +			YES	19
		BIAS RED	-β γ +			YES	19
		BIAS GREEN	-β γ +			YES	19
		BIAS BLUE	-β γ +			YES	19
		RESET	OFFβ γ ON			YES	19
		GAMMA	1β γ 2β ...γ 4				YES
	AUTOβ γ 1β ...γ 3				YES	20	
	LOW TONE	RED	Yβ γ M			YES	21
		GREEN	Cβ γ Y			YES	21
		BLUE	Mβ γ C			YES	21
		YELLOW	Gβ γ R			YES	21
MAGENTA		Rβ γ B			YES	21	
CYAN		Bβ γ G			YES	21	
RESET		OFFβ γ ON			YES	21	
COLOR TUNE							

Main menu	Sub menu	Sub menu 2	Sub menu 3	Sub menu 4	RESET	REFERENCE
AUDIO	BASS	-β γ +			YES	21
	TREBLE	-β γ +			YES	21
	BALANCE	Lβ γ R			YES	21
	AUDIO INPUT1	VIDEO 1-3 / HD/DVD 1-2 / RGB 1-3			YES	22
	AUDIO INPUT2	VIDEO 1-3 / HD/DVD 1-2 / RGB 1-3			YES	22
	AUDIO INPUT3	VIDEO 1-3 / HD/DVD 1-2 / RGB 1-3			YES	22

Main menu	Sub menu	Sub menu 2	Sub menu 3	Sub menu 4	RESET	REFERENCE
IMAGE ADJUST	ASPECT MODE	NORMAL/FULL/STADIUM/ZOOM/2.35:1/14:9			—	22
	V-POSITION	-β γ +			YES	22
	H-POSITION	-β γ +			YES	22
	V-HEIGHT	-β γ +			YES	22
	H-WIDTH	-β γ +			YES	22
	AUTO PICTURE	OFFβ γ ON*2			NO	22
	FINE PICTURE*1	-β γ + *2			YES	22
	PICTURE ADJ.*1	-β γ + *2			YES	22

Main menu	Sub menu	Sub menu 2	Sub menu 3	Sub menu 4	RESET	REFERENCE
OPTION1	OSM	DISPLAY OSM	OFFβ γ ON		YES	23
		OSM ADJ.	1β ...γ 6		YES	23
		OSM ANGLE	Hβ γ V		YES	23
		OSM ORBITER	OFFβ γ ON		YES	23
	BNC INPUT	RGBβ γ COMP.			YES	24
	D-SUB INPUT	RGB			—	24
	RGB SELECT	AUTO/STILL/MOTION/WIDE1/WIDE2/DTV			YES	24
	HD SELECT	1080B/1035I/1080A			NO	25
	INPUT SKIP	OFFβ γ ON			YES	25
	ALL RESET	OFFβ γ ON			—	26

Main menu	Sub menu	Sub menu 2	Sub menu 3	Sub menu 4	RESET	REFERENCE	
OPTION2	PWR. MGT.	OFFβ γ ON			YES	26	
	CINEMA MODE	OFFβ γ ON			YES	27	
	LONG LIFE	PLE		AUTO/LOCK 1/LOCK 2/LOCK 3		YES	27
		ORBITER		AUTO 1		YES	28
				AUTO 2		YES	28
				MANUAL	H-DOT/V-LINE/TIME	YES	28
				OFF		YES	28
		INVERSE	OFF			YES	28
			ON		WORKING TIME/WAITING TIME	YES	28
			WHITE			YES	28
		SCREEN WIPER	OFF			YES	29
			ON		WORKING TIME/WAITING TIME/SPEED	YES	29
		SOFT FOCUS	OFF/1/2/3/4			YES	30
	GRAY LEVEL	0β ...γ 3β ...γ 15				YES	30
	S1/S2	AUTOβ γ OFF				YES	30
	PICTURE SIZE*3	OFFβ γ ON				YES	31
DVI SET UP*4	PLUG/PLAY		PCβ γ STB/DVD		NO	31	
	BLACK LEVEL		LOWβ γ HIGH		NO	31	

Main menu	Sub menu	Sub menu 2	Sub menu 3	Sub menu 4	RESET	REFERENCE		
OPTION3	TIMER	PRESENT TIME	DAYLIGHT SAVING TIME	OFFβ γ ON	NO	31		
			DAY/HOUR/MINUTES		NO	31		
		PROGRAM	OFF		YES	32		
			ON	DATE/ON/OFF(HOUR, MINUTE)/INPUT/FUNCTION	YES	32		
	PWR. ON MODE	LAST / VIDEO 1-3 / HD/DVD 1-2 / RGB 1-3			YES	33		
	CONTROL LOCK	OFFβ γ ON			YES	34		
	IR REMOTE	OFFβ γ ON			YES	34		
	LOOP OUT	OFFβ γ ON			YES	35		
	ID NUMBER	ALLβ γ 1β ...γ 256			YES	35		
	VIDEO WALL	DIVIDER	OFF/1/4/9			YES	36	
		POSITION	No.1β ...γ No.4/No.7β ...γ No.15			—	36	
		DISP. MODE	SPLITβ γ BLANK			YES	37	
		AUTO ID	OFFβ γ ON			YES	37	
		IMAGE ADJUST	ASPECT MODE	NORMAL/FULL/STADIUM/ZOOM/2.35:1/14:9			—	37
			V-POSITION	-β γ +			YES	37
			H-POSITION	-β γ +			YES	37
			V-HEIGHT	-β γ +			YES	37
			H-WIDTH	-β γ +			YES	37
			AUTO PICTURE	OFFβ γ ON*2			NO	37
			FINE PICTURE*1	-β γ +*2			YES	37
			PICTURE ADJ.*1	-β γ +*2			YES	37
	P. ON DELAY	OFFβ γ ON			YES	38		
	PLE LINK	OFFβ γ ON			YES	38		
	REPEAT TIMER	OFF				YES	39	
		ON		DIVIDER/SOURCE/WORK TIME		YES	39	

Main menu	Sub menu	Sub menu 2	Sub menu 3	Sub menu 4	RESET	REFERENCE
ADVANCED OSM	OFFβ γ ON				YES	39
LANGUAGE	ENGLISH/DEUTSCH/FRANÇAIS/ESPAÑOL/ITALIANO/SVENSKA/中文				NO	40
COLOR SYSTEM	AUTO/3.58NTSC/4.43 NTSC/PAL/PAL 60/PAL-N/PAL-M/SECAM				NO	40
SOURCE INFORMATION	—				—	40

\*1 Only when AUTO PICTURE is OFF

\*2 RGB/PC only

\*3 Cannot be set in some models.

\*4 The setting is possible only in the HDCP compatible (silver bezel) model.


## Picture Settings Menu

### Adjusting the picture

THESE SETTINGS HAVE BEEN PRESET BY FAROUDJA!

Example: Adjusting the contrast

1. On the MAIN MENU, select "PICTURE", then press the MENU/ENTER button.  
The "PICTURE" screen appears.
2. Use the ▲ and ▼ buttons to select "CONTRAST".



3. Use the ◀ and ▶ buttons to adjust the contrast.



\* If neither the ◀ or ▶ button is pressed within 5 seconds, the current setting is set and the previous screen reappears.

**Note:** If "CAN NOT ADJUST" appears ...  
When trying to enter the PICTURE submenu, make sure PICTURE MODE is not set to DEFAULT.

### Information

#### Picture adjustment screen

**CONTRAST** .... Changes the picture's white level.  
**BRIGHTNESS** .. Changes the picture's black level.  
**SHARPNESS** .. Changes the picture's sharpness.  
 Adjusts picture detail of VIDEO display.  
**COLOR** ..... Changes the color density.  
**TINT** ..... Changes the picture's tint. Adjust for natural colored skin, background, etc.

#### Adjusting for the video processor


Only the contrast and brightness can be adjusted when the video processor is connected.

## Setting the picture mode according to the brightness of the room

There are four picture modes that can be used effectively according to the environment in which you are viewing the display.

Example: Setting the "THEAT. 1" mode

1. On the MAIN MENU, select "PICTURE", then press the MENU/ENTER button.  
The "PICTURE" screen appears.
2. Use the ▲ and ▼ buttons to select "PICTURE MODE".



3. To set to "THEAT. 1" ...

Use the ◀ and ▶ buttons to select "THEAT. 1".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

γ BRIGHT ε NORMAL ε THEAT. 1 ε THEAT. 2 ε DEFAULT β



\* If neither the ◀ or ▶ button is pressed within 5 seconds, the current selection is set and the previous screen reappears.

### Information

#### Types of picture modes

**THEAT. 1, 2** ..... Set this mode when watching video in a dark room.  
 This mode provides darker, finer pictures, like the screen in movie theaters.  
 For a darker image, select THEAT. 2.

**NORMAL** ..... Set this mode when watching video in a bright room.  
 This mode provides dynamic pictures with distinct differences between light and dark sections.

**BRIGHT** ..... This mode provides brighter pictures than NORMAL.


**DEFAULT** ..... Use this to reset the picture to the factory default settings.

## Reducing noise in the picture

Use these settings if the picture has noise due to poor reception or when playing video tapes on which the picture quality is poor.

Example: Setting "NR-3"

1. On the MAIN MENU, select "PICTURE", then press the MENU/ENTER button.  
The "PICTURE" screen appears.
2. Use the ▲ and ▼ buttons to select "NR".



3. Use the ◀ and ▶ buttons to select "NR-3".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

OFF ε NR-1 ε NR-2 ε NR-3 β



\* If neither the ◀ or ▶ button is pressed within 5 seconds, the current selection is set and the previous screen reappears.

### Information

#### ■ NR

- \* "NR" stands for Noise Reduction.
- \* This function reduces noise in the picture.

#### ■ Types of noise reduction

There are three types of noise reduction. Each has a different level of noise reduction. The effect becomes stronger as the number increases (in the order NR-1 γ NR-2 γ NR-3).  
OFF ..... Turns the noise reduction function off.

## Setting the color temperature


Use this procedure to set color tone produced by the plasma display.

Example: Setting "HIGH"

1. On the MAIN MENU, select "PICTURE", then press the MENU/ENTER button.  
The "PICTURE" screen appears.
2. Use the ▲ and ▼ buttons to select "COLOR TEMP".
3. Use the ◀ and ▶ buttons to select "HIGH".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

γ LOW ε MID LOW ε MID ε HIGH β

\* See below to set "WHITE BALANCE".



\* If neither the ◀ or ▶ button is pressed within 5 seconds, the current selection is set and the previous screen reappears.

### Information

#### ■ Setting the color temperature

LOW ..... Redder  
MID LOW ..... Slightly redder  
MID ..... Standard (slightly bluer)  
HIGH ..... Bluer

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

## Adjusting the color to the desired level


THIS HAS BEEN OPTIMIZED BY FAROUDJA  
DO NOT CHANGE

Example: Adjusting the "GAIN RED" of "HIGH" color temperature

Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

Perform Steps 1-3 of COLOR TEMP., then...

4. Press the MENU/ENTER button.  
The "WHITE BALANCE" screen appears.
5. Use the ▲ and ▼ buttons to select "GAIN RED".





6. Adjust the white balance using the ◀ and ▶ buttons.



\* If neither the ◀ or ▶ button is pressed within 5 seconds, the current setting is set and the previous screen reappears.

**Information**

■ **Adjusting the white balance**

**GAIN R/G/B** ..... White balance adjustment for signal level  
**BIAS R/G/B** ..... White balance adjustment for black level  
**RESET** ..... Resets settings to the factory default values. Use ◀ and ▶ buttons to select "ON", then press the MENU/ENTER button.

**Changing the Gamma Curve**


This feature adjusts the brightness of the midtone areas while keeping shadows and highlights unchanged.

Example: Setting "3"

Set "ADVANCED OSM" to "ON" in the MAIN MENU (1/2), then perform the following operations.

1. On the MAIN MENU, select "PICTURE", then press the MENU/ENTER button. The "PICTURE" screen appears.
2. Use the ▲ and ▼ buttons to select "GAMMA".
3. Use the ◀ and ▶ buttons to select "3". The mode switches as follows each time the ◀ or ▶ button is pressed:

γ 1 ε 2 ε 3 ε 4 β



**Information**

■ **GAMMA settings**

The picture becomes darker as the number increases (in the sequence of 1, 2, 3, 4).

■ **Restoring the factory default settings**

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

**Making the Low Tone adjustments**


This feature allows more detailed tone to be reproduced especially in the dark area.

Example: Setting "2"

Set "ADVANCED OSM" to "ON" in the MAIN MENU (1/2), then perform the following operations.

1. On the MAIN MENU, select "PICTURE", then press the MENU/ENTER button. The "PICTURE" screen appears.
2. Use the ▲ and ▼ buttons to select "LOW TONE".
3. Use the ◀ and ▶ buttons to select "2". The mode switches as follows each time the ◀ or ▶ button is pressed:

γ AUTO ε 1 ε 2 ε 3 β



**Information**

■ **LOW TONE settings**

**AUTO** ..... Will automatically appraise the picture and make adjustments.  
**1** ..... Will apply the dither method suitable for still pictures.  
**2** ..... Will apply the dither method suitable for motion pictures.  
**3** ..... Will apply the error diffusion method.

■ **Restoring the factory default settings**

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

## Adjusting the colors


Use this procedure to adjust hue and color density for red, green, blue, yellow, magenta and cyan.

You can accentuate the green color of trees, the blue of the sky, etc.

Example: Adjusting the color tune for blue

Set "ADVANCED OSM" to "ON" in the MAIN MENU (1/2), then perform the following operations.

1. On the MAIN MENU, select "PICTURE", then press the MENU/ENTER button.  
The "PICTURE" screen appears.
2. Use the ▲ and ▼ buttons to select "COLOR TUNE", then press the MENU/ENTER button.  
The "COLOR TUNE" screen appears.
3. Use the ▲ and ▼ buttons to select "BLUE".
4. Adjust using the ◀ and ▶ buttons.



\* If neither the ◀ or ▶ button is pressed within 5 seconds, the current selection is set and the previous screen reappears.

To continue making other adjustments...

Repeat from step 3.

### Information

#### ■ COLOR TUNE settings

RED ..... Makes red's adjustment  
GREEN ..... Makes green's adjustment  
BLUE ..... Makes blue's adjustment  
YELLOW ..... Makes yellow's adjustment  
MAGENTA ..... Makes magenta's adjustment  
CYAN ..... Makes cyan's adjustment  
RESET ..... Resets settings to the factory default value. Use ◀ and ▶ buttons to select "ON", then press the MENU/ENTER button.

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.


## Audio Settings Menu

### Adjusting the treble, bass and left/right balance and audio input select

The treble, bass and left/right balance can be adjusted to suit your tastes.

Example: Adjusting the bass

1. On the MAIN MENU, select "AUDIO", then press the MENU/ENTER button.  
The "AUDIO" screen appears.
2. To adjust the bass ...  
Use the ▲ and ▼ buttons to select "BASS".
3. Adjust the bass using the ◀ and ▶ buttons.



To continue adjusting the audio ...

Repeat from step 2.

**Note :** If "CAN NOT ADJUST" appears...

Set "AUDIO INPUT" on the AUDIO menu correctly.

### Information

#### ■ Audio settings menu

BASS ..... Controls the level of low frequency sound.  
TREBLE ..... Controls the level of high frequency sound.  
BALANCE ..... Controls the balance of the left and right channels.

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

## Setting the allocation of the audio connectors


Setting the AUDIO 1, 2, and 3 connectors to the desired input.

Example: Setting "AUDIO INPUT1" to "VIDEO 2"

1. On the MAIN MENU, select "AUDIO", then press the MENU/ENTER button.  
The "AUDIO" screen appears.
2. Use the ▲ and ▼ buttons to select "AUDIO INPUT1".
3. To set the AUDIO INPUT1 to "VIDEO2"...  
Use the ◀ and ▶ buttons to select "VIDEO2".  
The mode switches as follows each time the ◀ or ▶ button is pressed:  
The available sources depend on the setting of "BNC INPUT".

RGB:  $\left\{ \begin{array}{l} \gamma \text{ VIDEO1} \varepsilon \text{ VIDEO2} \varepsilon \text{ VIDEO3} \varepsilon \text{ HD/DVD1} \beta \\ \gamma \text{ RGB3} \varepsilon \text{ RGB2} \varepsilon \text{ RGB1} \beta \end{array} \right\}$

COMP.:  $\left\{ \begin{array}{l} \gamma \text{ VIDEO1} \varepsilon \text{ VIDEO2} \varepsilon \text{ VIDEO3} \varepsilon \text{ HD/DVD1} \beta \\ \gamma \text{ RGB3} \varepsilon \text{ RGB1} \varepsilon \text{ HD/DVD2} \beta \end{array} \right\}$



### Information

#### ■ AUDIO INPUT

A single audio input cannot be selected as the audio channel for more than one input terminal.

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

## Image Adjust Settings Menu


### Adjusting the Position, Size, Fine Picture, Picture Adj

The position of the image can be adjusted and flickering of the image can be corrected.

Example: Adjusting the vertical position in the normal mode

1. On the MAIN MENU, select "IMAGE ADJUST", then press the MENU/ENTER button.  
The "IMAGE ADJUST" menu appears.

Default settings (when RGB/PC is selected)



- \* The settings on the IMAGE ADJUST menu are not preset at the factory.

To select a mode ...

Use the ◀ and ▶ buttons to select a mode.


The mode switches as follows each time the ◀ or ▶ button is pressed:

**NORMAL**  $\varepsilon$  **FULL**

- \* The mode can also be switched by pressing the "WIDE" button on the remote control.

2. To adjust the vertical position ...

Use the ▲ and ▼ buttons to select "V-POSITION".



3. Adjust using the ◀ and ▶ buttons.




- \* If neither the ◀ or ▶ button is pressed within 5 seconds, the current setting is set and the previous screen reappears.

To continue making other computer image adjustments ...

Repeat from step 2.

## Information

### ■ When “AUTO PICTURE” is “OFF”



When Auto Picture is off, the Fine Picture and the Picture ADJ. items are displayed so that you can adjust them.

### ■ Adjusting the Auto Picture

ON ..... The Picture ADJ., Fine Picture and Position adjustments are made automatically.

Not available for digital ZOOM.

OFF ..... The Picture ADJ., Fine Picture and Position adjustments are made manually.

\* If FINE PICTURE won't be adjusted, set Auto Picture to OFF and adjust manually.

### ■ Adjusting the position of the image

V-POSITION ... Adjusts the vertical position of the image.

H-POSITION ... Adjusts the horizontal position of the image.

V-HEIGHT ..... Adjusts the vertical size of the image. (Except for STADIUM mode)

H-WIDTH ..... Adjusts the horizontal size of the image. (Except for STADIUM mode)

FINE PICTURE\* .. Adjusts for flickering.

PICTURE ADJ.\*... Adjusts for striped patterns on the image.

\* The Picture ADJ. and Fine Picture features are available only when the “Auto Picture” is off.

\* The AUTO PICTURE, FINE PICTURE and PICTURE ADJ. are available only for RGB signals.

But, these features are not available for moving pictures on VIDEO, HD/DVD or RGB.

### ■ Restoring the factory default settings

Select “ALL RESET” under the OPTION1 menu. Note that this also restores other settings to the factory defaults except for Auto Picture.

## Option 1 Settings Menu


### Setting the on-screen menu

This sets the position of the menu, the display format (horizontal or vertical) etc.

Example: Turning the DISPLAY OSM off

1. On the MAIN MENU, select “OPTION1”, then press the MENU/ENTER button.  
The “OPTION1” menu appears.
2. Use the ▲ and ▼ buttons to select “OSM”, then press the MENU/ENTER button.  
The “OSM” menu appears.
3. Use the ▲ and ▼ buttons to select “DISPLAY OSM”.
4. To set the DISPLAY OSM to “OFF”...  
Use the ◀ and ▶ buttons to select “OFF”.  
The mode switches as follows each time the ◀ or ▶ button is pressed:

ON ε OFF



## Information

### ■ DISPLAY OSM settings

ON ..... The on-screen menu appears.

OFF ..... The on-screen menu does not appear.

If you press the DISPLAY button on the remote control for more than 3 seconds the main menu will appear and can be set (although it is not ON).

### ■ OSM ADJUST settings

Adjusts the position of the menu when it appears on the screen.


The position can be set between 1 to 6.




### ■ OSM ANGLE settings

Sets the display format (landscape “H” or portrait “V”). When the unit is installed vertically set the OSM ANGLE at “V”.

“H”



“V”



### ■ OSM ORBITER settings

ON ..... The position of the menu will be shifted by eight dots each time OSM is displayed.

OFF ..... OSM will be displayed at the same position.

### ■ Restoring the factory default settings

Select “ALL RESET” under the OPTION1 menu. Note that this also restores other settings to the factory defaults except for Auto Picture.


### Setting the BNC connectors

Select whether to set the input of the 5 BNC connectors to RGB and component.

Example: Set the BNC INPUT mode to “COMP.”

1. On the MAIN MENU, select “OPTION1”, then press the MENU/ENTER button.  
The “OPTION1” screen appears.
2. Use the ▲ and ▼ buttons to select “BNC INPUT”.
3. To set the BNC INPUT mode to “COMP.”...  
Use the ◀ and ▶ buttons to select “COMP.”.  
The mode switches as follows each time the ◀ or ▶ button is pressed:

RGB ε COMP.



### Information

#### ■ BNC INPUT Settings

RGB .....Use the 5BNC terminals for RGB input.

COMP. ....Use the 3BNC terminals for component input.


#### ■ Restoring the factory default settings

Select “ALL RESET” under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

### Checking the signal being transmitted to RGB1 terminal

Use this to confirm the signal being transmitted to the RGB1 terminal.

It is set to RGB and can not be adjusted.




### Setting a computer image to the correct RGB select screen

With the computer image, select the RGB Select mode for a moving image such as (video) mode, wide mode or digital broadcast.

Example: Setting the “RGB SELECT” mode to “MOTION”

1. On the MAIN MENU, select “OPTION1”, then press the MENU/ENTER button.  
The “OPTION1” screen appears.
2. Use the ▲ and ▼ buttons to select “RGB SELECT”.
3. To set the RGB select mode to “MOTION” ...  
Use the ◀ and ▶ buttons to select “MOTION”.  
The mode switches as follows each time the ◀ or ▶ button is pressed:

γ AUTO ε STILL ε MOTION ε WIDE1 ε WIDE2 ε DTV β



## Information

### ■ RGB SELECT modes

One of these 6 modes must be selected in order to display the following signals correctly.

**AUTO** ..... Select the suitable mode for the specifications of input signals as listed in the table "Computer input signals supported by this system" on page 7 of Model Information.

**STILL** ..... To display VESA standard signals. (Use this mode for a still image from a computer.)

**MOTION** ..... The video signal (from a scan converter) will be converted to RGB signals to make the picture more easily viewable. (Use this mode for a motion image from a computer.)

**WIDE1** ..... When an 852 dot × 480 line signal with a horizontal frequency of 31.7kHz is input, the image may be compressed horizontally. To prevent this, set RGB SELECT to WIDE1.

**WIDE2** ..... When an 848 dot × 480 line signal with a horizontal frequency of 31.0 kHz is input, the image may be compressed horizontally. To prevent this, set RGB SELECT to WIDE2.

**DTV** ..... Set this mode when watching digital broadcasting (480P).

See page 7 of Model Information for the details of the above settings.

### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

## Setting high definition images to the suitable screen size

Use this procedure to set whether the number of vertical lines of the input high definition image is 1035 or 1080.

Example: Setting the "1080B" mode to "1035I"

1. On the MAIN MENU, select "OPTION1", then press the MENU/ENTER button.  
The "OPTION1" screen appears.


2. Use the ▲ and ▼ buttons to select "HD SELECT".

3. To set the HD SELECT mode to "1035I" ...

Use the ◀ and ▶ buttons to select "1035I".

The mode switches as follows each time the ◀ or ▶ button is pressed:

γ 1080B ε 1035I ε 1080A β



## Information

### ■ HD SELECT modes

These 3 modes are not displayed in correct image automatically.

1080B ..... Standard digital broadcasts

1035I ..... Japanese "High Vision" signal format

1080A ..... Special Digital broadcasts (for example : DTC100)

## Setting the Input Skip

When this is ON, signals which are not present will be skipped over and only pictures whose signals are being transmitted will be displayed.

This setting is valid only for the INPUT SELECT button on the unit.

Example: Set to "ON"

1. On the MAIN MENU, select "OPTION1", then press the MENU/ENTER button.  
The "OPTION1" screen appears.


2. Use the ▲ and ▼ buttons to select "INPUT SKIP".

3. To set the INPUT SKIP mode to "ON"...

Use the ◀ and ▶ buttons to select "ON".

The mode switches as follows each time the ◀ or ▶ button is pressed:

OFF ε ON



## Information

### ■ INPUT SKIP settings

OFF ..... Regardless of the presence of the signal, scan and display all signals.

ON ..... If no input signal is present, skip that signal.

\* "SETTING NOW" will appear during the input search.

### ■ Restoring the factory default settings


Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

## Resetting to the default values


Use these operations to restore all the settings (PICTURE, AUDIO, IMAGE ADJUST, OPTION1~3, etc) to the factory default values.

Refer to page 16 for items to be reset.

1. On the MAIN MENU, select “OPTION1”, then press the MENU/ENTER button.  
The “OPTION1” screen appears.
2. Use the ▲ and ▼ buttons to select “ALL RESET”.



3. Use the ◀ and ▶ buttons to select “ON”, then press the MENU/ENTER button.



When the “SETTING NOW” screen disappears, then all the settings are restored to the default values.

## Option2 Settings Menu

### Setting the power management for computer images

This energy-saving (power management) function automatically reduces the monitor’s power consumption if no operation is performed for a certain amount of time.

Example: Turning the power management function on


Set “ADVANCED OSM” to “ON” in the main menu (1/2), then perform the following operations.

1. On the MAIN MENU, select “OPTION2”, then press the MENU/ENTER button.  
The “OPTION2” screen appears.
2. Use the ▲ and ▼ buttons to select “PWR. MGT.”.
3. To turn the power management function on ...

Use the ◀ and ▶ buttons to select “ON”.

The mode switches as follows each time the ◀ or ▶ button is pressed:

ON ε OFF



### Information

#### ■ Power management function

- \* The power management function automatically reduces the monitor’s power consumption if the computer’s keyboard or mouse is not operated for a certain amount of time. This function can be used when using the monitor with a computer.
- \* If the computer’s power is not turned on or if the computer and selector tuner are not properly connected, the system is set to the off state.
- \* For instructions on using the computer’s power management function, refer to the computer’s operating instructions.

#### ■ Power management settings

ON ..... In this mode the power management function is turned on.

OFF ..... In this mode the power management function is turned off.

#### ■ Power management function and POWER/STANDBY indicator

The POWER/STANDBY indicator indicates the status of the power management function. See page 27 for indicator status and description.

#### ■ Restoring the factory default settings

Select “ALL RESET” under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

## POWER/STANDBY indicator

Power management mode	POWER/STANDBY indicator	Power management operating status	Description	Turning the picture back on
On	Green	Not activated.	Horizontal and vertical synchronizing signals are present from the computer.	Picture already on.
Off	Red	Activated.	Horizontal and/or vertical synchronizing signals are not sent from the computer.	Operate the keyboard or mouse. The picture reappears.

### Setting the picture to suit the movie

The film image is automatically discriminated and projected in an image mode suited to the picture.


[NTSC, PAL, PAL60, 480I (60Hz), 525I (60Hz), 576I (50Hz), 625I (50Hz), 1035I (60Hz), 1080I (60Hz) only]

Example: Setting the "CINEMA MODE" to "OFF"

Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

- On the MAIN MENU, select "OPTION2", then press the MENU/ENTER button.  
The "OPTION2" screen appears.
- Use the ▲ and ▼ buttons to select "CINEMA MODE".
- To set the CINEMA MODE to "OFF" ...  
Use the ◀ and ▶ buttons to select "OFF".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

ON ε OFF



### Information

#### ■ CINEMA MODE

ON ..... Automatic discrimination of the image and projection in cinema mode.

OFF ..... Cinema mode does not function.

#### ■ Restoring the factory default settings


Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

## Reducing burn-in of the screen

The brightness of the screen, the position of the picture, positive/negative mode and screen wiper are adjusted to reduce burn-in of the screen.

Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

- On the MAIN MENU, select "OPTION2", then press the MENU/ENTER button.  
The "OPTION2" screen appears.
- Use the ▲ and ▼ buttons to select "LONG LIFE", then press the MENU/ENTER button.  
The "LONG LIFE" screen appears.



- Set the LONG LIFE mode using ▲▼◀ and ▶ buttons.  
See page 27 to set PLE.  
See page 28 to set ORBITER.  
See page 28 to set INVERSE.  
See page 29 to set SCREEN WIPER.  
See page 30 to set SOFT FOCUS.

### Information

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

### PLE (Peak Luminance Enhancement)


Use this to activate the brightness limiter.

Example: Setting "PLE" to "LOCK1"

Perform Steps 1-2 of LONG LIFE, then...

- Use the ▲ and ▼ buttons to select "PLE".
- Use the ◀ and ▶ buttons to select "LOCK1".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

☺ AUTO ε LOCK1 ε LOCK2 ε LOCK3β



### Information

#### ■ PLE settings

AUTO ..... The brightness of the screen is adjusted automatically to suit the picture quality.



LOCK1, 2, 3 .... Sets maximum brightness.  
The brightness level decreases in the order of LOCK 1, 2, 3. LOCK 3 provides minimum brightness.

## ORBITER


Use this to set the picture shift.

Example: Setting "ORBITER" to "AUTO1"

Perform Steps 1-2 of LONG LIFE, then...

- Use the ▲ and ▼ buttons to select "ORBITER".
- Use the ◀ and ▶ buttons to select "AUTO1".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

γ OFF ε AUTO1 ε AUTO2 ε MANUALβ



### Information

#### ■ ORBITER settings

- OFF ..... Orbiter mode does not function.  
This is the default setting when RGB is input.
- AUTO1 ..... The picture moves around the screen intermittently, making the picture smaller. This is the default setting when a Video or a DVD/HD/DTV signal is input. Set to "OFF" when these signals are not used.
- AUTO2 ..... The picture moves around the screen intermittently, making the picture bigger.
- MANUAL ..... User can adjust the orbiter function (Horizontal Dot, Vertical Line and Time) manually.  
See the following explanation.

\* When a Video or a DVD/HD/DTV signal is input, the AUTO1 and 2 functions will affect only the moving picture and will not make the screen smaller or bigger.

### Adjust the ORBITER function manually

Set the amount of shift and the time between movement.

Example: Setting so that the picture moves 2 dots horizontally and 3 lines vertically every 3 minutes.

Perform Steps 1-3 of ORBITER, then...

- Use the ◀ and ▶ buttons to select "MANUAL", then press the MENU/ENTER button.  
THE "ORBITER" screen appears.
- Adjust the items using the ▲▼◀ and ▶ buttons.  
The mode switches as follows each time the ◀ or ▶ button is pressed:

#### • H-DOT


γ 1 DOT ε 2 DOT ε ..... ε 19 DOT ε 20 DOTβ

#### • V-LINE

γ 1 LINE ε 2 LINE ε ..... ε 19 LINE ε 20 LINEβ

#### • TIME

γ 1 M ε 2 M ε 3 M ε 4 M ε 5 Mβ



### Information

#### ■ ORBITER Function settings

- H-DOT ..... Moves from 1 to 20 dots in the horizontal direction.
- V-LINE ..... Moves from 1 to 20 lines in the vertical direction.
- TIME ..... Interval of 1~5 minutes (1 horizontal dot or 1 vertical line per interval).

## INVERSE


Use this to set the inverse mode or to display a white screen.

Example: Setting "INVERSE" to "WHITE"

Perform Steps 1-2 of LONG LIFE, then...

- Use the ▲ and ▼ buttons to select "INVERSE".
- Use the ◀ and ▶ buttons to select "WHITE".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

γ OFF ε ON ε WHITEβ



### Information

#### ■ INVERSE Settings

- ON ..... The picture is displayed alternately between positive image and negative image.  
You can set the time by pressing the MENU/ENTER button while "ON" is set.
- OFF ..... Inverse mode does not function.
- WHITE ... The entire screen turns white.  
You can set the time by pressing the MENU/ENTER button while "ON" is set.

## Setting the time for INVERSE/WHITE

Set a time duration.

Example: Setting to that the INVERSE mode starts in 2 hours and proceeds for one hour and a half.

Perform Steps 1-3 of INVERSE, then...

- Use the ◀ and ▶ buttons to select "ON", then press the MENU/ENTER button.  
THE "INVERSE/WHITE" screen appears.


- Adjust the time using the ▲▼◀ and ▶ buttons.  
The mode switches as follows each time the ◀ or ▶ button is pressed:

- WORKING TIME

γ ON ε 00H03M ε 00H06M ε ..... ε 12H42M ε 12H45Mβ

- WAITING TIME

γ 00H03M ε 00H06M ε 00H09M ε ...ε 12H42M ε 12H45Mβ



### Information

#### ■ Setting the time

WORKING TIME ..... Set the time duration for "INVERSE/WHITE".

When the WORKING TIME is set to "ON" the mode will stay on.

WAITING TIME ..... Set the standby time until the "INVERSE/WHITE" mode starts.

\* The "WAITING TIME" can not be set when the "WORKING TIME" is ON.

\* THE "WORKING TIME" and "WAITING TIME" can be set for up to 12 hours and 45 minutes in units of 3 minutes.

\* Ending a WORKING TIME function, the monitor will be STAND BY.

[Example]

WORKING TIME: 01H30M

WAITING TIME: 02H00M

β ΦΦΦΦ 2H ΦΦΦΦ β ΦΦ 1.5H ΦΦ β ΦΦΦΦ  
Start INVERSE/WHITE Start STAND BY

#### ■ To select "ON" for the "WORKING TIME"...

Set the hours of the working time to 0H and the minutes to 0M. "ON" will be displayed.

## SCREEN WIPER

When this is set to ON, a white vertical bar moves repeatedly from the left and of the screen to the right end at a constant speed.


Example: Setting "SCREEN WIPER" to "ON"

Perform Steps 1-2 of LONG LIFE, then...

- Use the ▲ and ▼ buttons to select "SCREEN WIPER".

- Use the ◀ and ▶ buttons to select "ON".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

OFF ε ON



### Information

#### ■ SCREEN WIPER

ON ..... The white vertical bar appears.

You can set the time by pressing the MENU/ENTER button while "ON" is set.

OFF ..... Screen wiper mode does not function.

## Setting the time for SCREEN WIPER

Set a time duration and the speed.

Example: Setting to that the SCREEN WIPER mode starts in 30 minutes and proceeds for one hour and a half.

Perform Steps 1-3 of SCREEN WIPER, then...

- Use the ◀ and ▶ buttons to select "ON", then press the MENU/ENTER button.  
THE "SCREEN WIPER" screen appears.

- Adjust the time and speed using the ▲▼◀ and ▶ buttons.  
The mode switches as follows each time the ◀ or ▶ button is pressed:

- WORKING TIME


γ ON ε 00H03M ε 00H06M ε ..... ε 12H42M ε 12H45Mβ

- WAITING TIME

γ 00H03M ε 00H06M ε 00H09M ε ...ε 12H42M ε 12H45Mβ

- SPEED

γ 1 ε 2 ε 3 ε 4 ε 5β



### Information

#### ■ Setting the time

WORKING TIME ..... Set the time duration for "SCREEN WIPER".

When the WORKING TIME is set to "ON" the mode will stay on.

WAITING TIME ..... Set the standby time until the "SCREEN WIPER" mode starts.

SPEED ..... Set the moving speed for the "SCREEN WIPER". The speed decreases as the number increases.

\* The "WAITING TIME" can not be set when the "WORKING TIME" is ON.

\* THE "WORKING TIME" and "WAITING TIME" can be set for up to 12 hours and 45 minutes in units of 3 minutes.

### SOFT FOCUS

Reduces edges and softens the image.


Example: Setting "SOFT FOCUS" to "2"

Perform Steps 1-2 of LONG LIFE, then...

3. Use the ▲ and ▼ buttons to select "SOFT FOCUS".

4. Use the ◀ and ▶ buttons to select "2".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

OFF ε 1 ε 2 ε 3 ε 4



### Information

#### ■ SOFT FOCUS settings

OFF ..... Turns the SOFT FOCUS function off.

1, 2, 3, 4 ..... Activates the SOFT FOCUS setting. The higher numbers create a softer image.  
"SHARPNESS" can not be adjusted on the "PICTURE" menu.

### Setting the gray level for the sides of the screen

Use this procedure to set the gray level for the parts on the screen on which nothing is displayed when the screen is set to the 4:3 size.


Example: Adjusting the "GRAY LEVEL"

Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

1. On the MAIN MENU, select "OPTION2", then press the MENU/ENTER button.  
The "OPTION2" screen appears.

2. Use the ▲ and ▼ buttons to select "GRAY LEVEL".

3. To adjust the "GRAY LEVEL" ...  
Use the ◀ and ▶ buttons to adjust the GRAY LEVEL.



### Information

#### ■ GRAY LEVEL settings

This adjusts the brightness of the black (the gray level) for the sides of the screen.

The standard is 0 (black). The level can be adjusted from 0 to 15. The factory setting is 3 (dark gray).

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

### Setting the screen size for S1/S2 video input

If the S-video signal contains screen size information, the image will be automatically adjusted to fit the screen when this S1/S2 is set to AUTO.

This feature is available only when an S-video signal is input via the VIDEO3 terminal.

Example: Setting the "S1/S2" to "AUTO"


Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

1. On the MAIN MENU, select "OPTION2", then press the MENU/ENTER button.  
The "OPTION2" screen appears.

2. Use the ▲ and ▼ buttons to select "S1/S2".

3. Use the ◀ and ▶ buttons to select "AUTO".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

OFF ε AUTO



### Information

#### ■ S1/S2 settings

AUTO ..... Adjusts the screen size automatically according to the S1/S2 video signal.

OFF ..... Turns the S1/S2 function off.

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

### Setting the picture size for RGB input signals

Use this procedure to switch the setting to "ON" or "OFF".

\* Cannot be set in some models.

Example: Setting the "PICTURE SIZE" mode to "OFF"

Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

1. On the MAIN MENU, select "OPTION2", then press the MENU/ENTER button.

The "OPTION2" screen appears.


2. Use the ▲ and ▼ buttons to select "PICTURE SIZE".

3. To set PICTURE SIZE mode to "OFF"...

Use the ◀ and ▶ buttons to select "OFF".

The mode switches as follows each time the ◀ or ▶ button is pressed:

ON ε OFF



### Information

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults. DO NOT USE WITH VIDEO PROCESSOR

### Setting the signal and black level for DVI signal

Choose the signal for the DVI connector (PC or STB/DVD) and set the black level.

This setting is possible only in the HDCP compatible (silver bezel) model.

Example: Setting the "PLUG/PLAY" mode to "STB/DVD"

Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

1. On the MAIN MENU, select "OPTION2", then press the MENU/ENTER button.

The "OPTION2" screen appears.

2. Use the ▲ and ▼ buttons to select "DVI SET UP", then press the MENU/ENTER button.

The "DVI SET UP" screen appears.


3. To set PLUG/PLAY mode to "STB/DVD"...

Use the ◀ and ▶ buttons to select "STB/DVD".

The mode switches as follows each time the ◀ or ▶ button is pressed:

PLUG/PLAY: PC ε STB/DVD

BLACK LEVEL: LOW ε HIGH



### Information

#### ■ PLUG/PLAY settings

PC ..... When connected to the PC signal.

BLACK LEVEL is set to "LOW" automatically.

STB/DVD ... When connected to the SET TOP BOX, DVD etc.

BLACK LEVEL is set to "HIGH" automatically.

#### ■ BLACK LEVEL settings

LOW ..... When connected to the PC signal.

HIGH ..... When connected to the SET TOP BOX, DVD etc. Change "HIGH" into "OFF" if the black level appears gray.


## Option3 Settings Menu

### Using the timer

This function sets the monitor to turn ON/OFF automatically at a set time.

Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

1. On the MAIN MENU, select "OPTION3", then press the MENU/ENTER button.  
The "OPTION3" screen appears.
2. Use the ▲ and ▼ buttons to select "TIMER", then press the MENU/ENTER button.  
The "TIMER" screen appears.



3. Set the TIMER using ▲▼◀▶ and ▶ buttons.  
See page 32 to set PRESENT TIME.  
See page 33 to set PROGRAM.

#### Information

##### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu.  
DO NOT USE WITH FAROUDJA PACKAGE

#### PRESENT TIME

This sets the day of the week and present time.

Example: Setting "WEDNESDAY", "22:05"

Perform Steps 1-2 of TIMER, then...

3. Use the ▲ and ▼ buttons to select "PRESENT TIME", then press the MENU/ENTER button.  
The "PRESENT TIME" screen appears.



4. Use the ▲ and ▼ buttons to select the item, then adjust using the ◀ and ▶ buttons.



The mode switches as follows each time the ◀ or ▶ button is pressed:

- DAYLIGHT SAVING TIME

ON ε OFF

- Day

γ SUNDAY ε MONDAY ε ..... ε FRIDAY ε SATURDAYβ

- Hour/Minutes

γ 00:00 ε 00:01 ε 00:02 ε ..... ε 23:58 ε 23:59β

5. Once the setting is completed...

Use the ▲ and ▼ buttons to select "SET", then press the MENU/ENTER button.

The adjustments are stored and return to the TIMER menu.



#### Information

##### ■ PRESENT TIME settings

##### DAYLIGHT SAVING TIME

..... Use to set DAYLIGHT SAVING TIME.

ON: The present time + 1 hour.

OFF: Cancelled

Day ..... Set the day of the week (e.g. Sunday).

Hour ..... Set the hour in the 24-hour format (range 00 to 23).

Minutes ..... Set the minutes (range 00 to 59).

\* If you press the EXIT button instead of the MENU/ENTER button in step 5, the settings can not be mode.


## PROGRAM TIMER

This sets the day and time at which the power will be switched ON/OFF as well as the input mode.

Example: Setting so that the power will be switched on at 8:30 A.M., Monday, displaying RGB2 source, and switched off at 10:30 A.M.

Perform Steps 1-2 of **TIMER**, then...


- Use the ▲ and ▼ buttons to select "PROGRAM".



- Use the ◀ and ▶ buttons to select "ON", then press the MENU/ENTER button.

The "PROGRAM TIMER" screen appears.

- Adjust using the ▲▼◀ and ▶ buttons and ZOOM + / - button.



The mode switches as follows each time the ZOOM + / - button is pressed:

- Date

γ — ε SUN ε MON ε ... ε SAT ε \*ε \*SUN ε \*MON ε ... ε \*SATβ

- ON/OFF Hour

γ 00 ε 01 ε 02 ε ..... ε 21 ε 22 ε 23β

- Minute

γ 00 ε 01 ε 02 ε ..... ε 57 ε 58 ε 59β

- INPUT

γ — ε LAST ε VIDEO1 ε VIDEO2 ε VIDEO3 ε HD/DVD1 β  
γ RGB3 ε RGB2 ε RGB1 ε HD/DVD2 β

- FUNCTION

γ — ε ORBITER ε INVERSE ε WHITE ε WIPERβ

### Information

#### PROGRAM TIMER settings

DATE ..... Set the day of the week (e.g. Sunday).

ON (hour, minutes) .... Set the time at which the power will be turned on in the 24-hour format.

OFF (hour, minutes) ... Set the time at which the power will be turned off in the 24-hour format.

INPUT ..... Set the input mode that will be displayed when the timer is on.

FUNCTION ..... Set the LONG LIFE function.

#### To reset the program

Align the cursor with the DATE field that you wish to reset, then press the CLEAR button.

#### To reset the data

Align the cursor with the field (ON/OFF/INPUT/FUNCTION) that you wish to reset, then press the CLEAR button.

#### Special characters in the PROGRAM TIMER screen

DATE	ON	OFF	INPUT	FUNCTION
MON	08:30	10:30	RGB2	INVERSE
TUE	-:-:-	18:15	—	—
SAT	08:30	12:15	VIDEO1	WHITE
*FRI	08:30	10:00	HD/DVD1	—
—	-:-:-	-:-:-	—	—
SAT	08:30	12:15	VIDEO1	WHITE
*	15:30	16:00	RGB1	—

- An asterisk "\*" in the DATE field

An asterisk "\*" means "every". For example, "\*FRI" means every Friday and "\*" means everyday.

- A hyphen "-" in the ON field or OFF field

If any hyphen remains in the ON field or OFF field, the FUNCTION can not be set.

- A hyphen "-" in the FUNCTION field

A hyphen "-" means last mode (the mode that was last selected at the time the power was switched off).

## Setting the power on mode

This function sets the input mode at the time the power is switched on.

Example: Setting "VIDEO2"

Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

- On the MAIN MENU, select "OPTION3", then press the MENU/ENTER button.

The "OPTION3" screen appears.

- Use the ▲ and ▼ buttons to select "PWR. ON MODE".

- To set the PWR. ON MODE to "VIDEO2"...


Use the ◀ and ▶ buttons to select "VIDEO2".

The mode switches as follows each time the ◀ or ▶ button is pressed:

The available inputs depend on the setting of "BNC INPUT".

RGB: γ LAST ε VIDEO1 ε VIDEO2 ε VIDEO3 β  
γ RGB3 ε RGB2 ε RGB1 ε HD/DVD1 β

COMP: γ LAST ε VIDEO1 ε VIDEO2 ε VIDEO3 β  
γ RGB3 ε RGB1 ε HD/DVD2 ε HD/DVD1 β



### Information

#### ■ PWR. ON MODE settings

LAST ..... Last mode (the mode that was last selected at the time the power was switched off).

VIDEO1, 2, 3 .... VIDEO input mode.

RGB1, 2, 3 ..... RGB input mode.

HD/DVD1, 2 ..... HD/DVD input mode.

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

### Enabling/disabling the front panel controls

This function enables/disables the front panel controls.

Example: Setting "ON"

Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

1. On the MAIN MENU, select "OPTION3", then press the MENU/ENTER button.

The "OPTION3" screen appears.


2. Use the ▲ and ▼ buttons to select "CONTROL LOCK".

3. To set the CONTROL LOCK to "ON"...

Use the ◀ and ▶ buttons to select "ON", then press the MENU/ENTER button.

The mode switches as follows each time the ◀ or ▶ button is pressed:

OFF ε ON



### Information

#### ■ CONTROL LOCK settings

ON ..... Disables the buttons on the front panel.

OFF .... Enables the buttons on the front panel.

\* Even when the CONTROL LOCK is set, the POWER switch will not be locked.

\* This becomes effective when the on-screen menu goes out.

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

### Enabling/disabling remote control wireless transmission

This function enables/disables remote control wireless transmission.

Example: Setting "OFF"

Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

1. On the MAIN MENU, select "OPTION3", then press the MENU/ENTER button.

The "OPTION3" screen appears.


2. Use the ▲ and ▼ buttons to select "IR REMOTE".

3. To set the IR REMOTE to "OFF"...

Use the ◀ and ▶ buttons to select "OFF", then press the MENU/ENTER button.

The mode switches as follows each time the ◀ or ▶ button is pressed:

OFF ε ON



### Information

#### ■ IR REMOTE settings

ON ..... Enables remote control wireless transmission.

OFF .... Disables remote control wireless transmission.

Set "OFF" to avoid unwanted control from other remote controls.

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

## Loop Out setting

When this feature is set to ON, the received signal will be looped out.

Example: Setting "ON"

Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

1. On the MAIN MENU, select "OPTION3", then press the MENU/ENTER button.

The "OPTION3" screen appears.


2. Use the ▲ and ▼ buttons to select "LOOP OUT".

3. To set the LOOP OUT to "ON"...

Use the ◀ and ▶ buttons to select "ON".

The mode switches as follows each time the ◀ or ▶ button is pressed:

OFF ε ON



### Information

#### ■ LOOP OUT settings

ON ..... The received signal will be looped out via PC1 terminal or VIDEO1 terminal.

OFF .... The received signal will not loop out.

\* Even if LOOP OUT is ON, signals won't be sent out if POWER is being turned off.

#### ■ To connect another display...

See page 10.

#### ■ If the RGB/PC1 signal is present at the time the power switched on...

The RGB/PC1 input will be displayed regardless of the setting of LOOP OUT.

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

## ID number setting

When using more than one of these displays, this function sets ID numbers so that operation of the remote control does not cause multiple monitors to operate at the same time.

Example: Setting "2"

Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

1. On the MAIN MENU, select "OPTION3", then press the MENU/ENTER button.

The "OPTION3" screen appears.

2. Use the ▲ and ▼ buttons to select "ID NUMBER".


3. To set the ID NUMBER to "2"...

Use the ◀ and ▶ buttons to select "2".

The mode switches as follows each time the ◀ or ▶ 34

button is pressed:

γ ALL ε 1 ε 2 ε ..... ε 255 ε 256β



#### \* To reset back to ALL

Press the CLEAR button.

### Information

#### ■ ID NUMBER settings

ALL .....ID NUMBER will not be set.

1 to 256 ....ID NUMBER will be set.

#### ■ When the ID NUMBER have been set

You can also set ID NUMBER for each remote control to operate the plasma display individually. To do so, see below.

#### ■ Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

### To set the ID number for the remote control

Example: Setting "2"

1. Press the ID SELECT button on the remote control. The "ID SELECT" screen appears.


2. Use the ▲ and ▼ buttons to select "ID NUMBER".

3. To set the ID NUMBER to "2"...

Use the ◀ and ▶ buttons to select "2".

The mode switches as follows each time the ◀ or ▶ button is pressed:

γ ALL ε 1 ε 2 ε ..... ε 255 ε 256β



#### \* To reset back to ALL

Press the CLEAR button.

4. Once the setting is completed...


Press the EXIT button to delete the ID SELECT screen.



## Video Wall setting

Use this feature to configure a 2x2 or 3x3 video wall.  
Set "ADVANCED OSM" to "ON" in the main menu (1/2), then perform the following operations.

- On the MAIN MENU, select "OPTION3", then press the MENU/ENTER button.  
The "OPTION3" screen appears.
- Use the ▲ and ▼ buttons to select "VIDEO WALL", then press the MENU/ENTER button.  
The "VIDEO WALL" screen appears.



- Set the VIDEO WALL using ▲▼◀▶ buttons.  
See page 36 to set DIVIDER.  
See page 36 to set POSITION.  
See page 37 to set DISP. MODE.  
See page 37 to set AUTO ID.  
See page 37 to set IMAGE ADJUST.  
See page 38 to set P. ON DELAY.  
See page 38 to set PLE LINK.  
See page 39 to set REPEAT TIMER.
- Once the setting is completed...  
Press the EXIT button to return to the OPTION3 menu.

**Note:** A contingency method of shutting off the electric power should be used in cases of emergency during video wall setup.

### Information

#### Restoring the factory default settings

Select "ALL RESET" under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

### DIVIDER

Set the 2x2 or 3x3 video wall.

Example: Setting "4"

Perform Steps 1-2 of VIDEO WALL, then...

- Use the ▲ and ▼ buttons to select "DIVIDER".
- Use the ◀ and ▶ buttons to select "4".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

γ OFF ε 1 ε 4 ε 9 β



### Information

#### DIVIDER settings

OFF, 1 ..... 1 Screen (Matrix display function does not work)  
4 ..... 4 Screens (2x2 video wall)  
9 ..... 9 Screens (3x3 video wall)  
\* When you select "4" or "9", set the VIDEO WALL POSITION.

### VIDEO WALL POSITION

Set the position of each display.

Example: Setting "4"

Perform Steps 1-2 of VIDEO WALL, then...


- Use the ▲ and ▼ buttons to select "POSITION", then press the MENU/ENTER button.  
The "VIDEO WALL POSITION" screen appears.
- Use the ◀ and ▶ buttons to select "NO. 4".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

• 4 Screens

γ NO. 1 ε NO. 2 ε NO. 3 ε NO. 4 β

• 9 Screens

γ NO. 7 ε NO. 8 ε ..... ε NO. 14 ε NO. 15 β



### Information

#### VIDEO WALL POSITION settings

1 Screen ..... There is no need to set POSITION.

4 Screens

NO. 1	NO. 2
NO. 4	NO. 3

9 Screens

NO. 7	NO. 8	NO. 9
NO. 10	NO. 11	NO. 12
NO. 13	NO. 14	NO. 15

## DISP. MODE


Select the screen mode from between two options (Splitting, Blanking).

Example: Setting "BLANK"

Perform Steps 1-2 of VIDEO WALL, then...

- Use the ▲ and ▼ buttons to select "DISP. MODE".
- Use the ◀ and ▶ buttons to select "BLANK".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

SPLIT ε BLANK



### Information

#### DISP. MODE settings

SPLIT ..... Combines enlarged screens and creates multiple screens.

BLANK ..... Corrects misalignment of combined screen portions and creates multiple screens

## AUTO ID

This feature automatically sets the ID numbers of multiple displays connected to each other.


Example: Setting "ON"

Set the ID number for the No. 1 display on ID NUMBER menu.

Perform Steps 1-2 of VIDEO WALL, then...

- Use the ▲ and ▼ buttons to select "AUTO ID".
- Use the ◀ and ▶ buttons to select "ON", then press the MENU/ENTER button.  
The mode switches as follows each time the ◀ or ▶ button is pressed:


OFF ε ON



### Information

#### AUTO ID settings

ON ..... Enables Auto ID function. In the case shown below, display 1 will be set as ID 1, display 2 as ID2, etc.



OFF ... Disables Auto ID function.


## IMAGE ADJUST

The position of the image can be adjusted and flickering of the image can be corrected.

Example: Adjusting the vertical position

Perform Steps 1-2 of VIDEO WALL, then...

- Use the ▲ and ▼ buttons to select "IMAGE ADJUST", then press the MENU/ENTER button.  
The "IMAGE ADJUST" screen appears.
- Use the ▲ and ▼ buttons to select "V-POSITION".



- Adjust using the ◀ and ▶ buttons.



\* If neither the ◀ or ▶ button is pressed within 5 seconds, the current setting is set and the previous screen reappears.

### Information

#### IMAGE ADJUST settings

These are the same functions as the IMAGE ADJUST menu on page 22.

### P. ON DELAY (Power on delay)

Use this function to activate power-on delay.  
Turn on the AUTO ID before the following operations.  
Example: Setting "ON"

Perform Steps 1-2 of VIDEO WALL, then...

- Use the ▲ and ▼ buttons to select "P. ON DELAY".
- Use the ◀ and ▶ buttons to select "ON".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

OFF  $\epsilon$  ON

VIDEO WALL	
DIVIDER	: 1
POSITION	
DISP. MODE	: SPLIT
AUTO ID	: OFF
IMAGE ADJUST	
P. ON DELAY	: ◀ ON ▶
PLE LINK	: OFF
REPEAT TIMER	: OFF
◆ SEL.	◀▶ ADJ. EXIT RETURN

#### Information

##### ■ P. ON DELAY settings

ON ..... Turns on the main power of each display after a delay time.

OFF .... Turns on the main power of all displays at the same time.

\* Once this function has been set to "ON", POWER ON/OFF button on the remote control does not function except for the No.1 monitor.

By pressing the POWER ON button on the remote control the No.1 monitor will turn on and the others will be turned on one by one automatically.

\* From the second monitor onward, neither the POWER button on the unit nor the POWER ON button on the remote control does function. However, by pressing and holding the POWER ON button for more than 3 seconds, the monitor will be turned on.

### PLE LINK

Use this function to set a uniform brightness for each display.

Turn on the AUTO ID and set the DIVIDER (at 1, 4 or 9) before the following operations.

Example: Setting "ON"

Perform Steps 1-2 of VIDEO WALL, then...

- Use the ▲ and ▼ buttons to select "PLE LINK".
- Use the ◀ and ▶ buttons to select "ON", then press the MENU/ENTER button.  
The mode switches as follows each time the ◀ or ▶ button is pressed:

OFF  $\epsilon$  ON

VIDEO WALL	
DIVIDER	: 1
POSITION	
DISP. MODE	: SPLIT
AUTO ID	: OFF
IMAGE ADJUST	
P. ON DELAY	: OFF
PLE LINK	: ◀ ON ▶
REPEAT TIMER	: OFF
◆ SEL.	◀▶ ADJ. EXIT RETURN

#### Information


##### ■ PLE LINK settings

ON ..... Sets a uniform brightness for each screen in a video wall.

OFF .... Sets the individual screen brightness for each screen in a video wall.

\* When this function is set "ON", connect your plasma displays with the remote cable (optional) in the order of the position numbers for the 2x2 video wall. See the drawing below.

\* If there are changes in the DIVIDER or POSITION, the PLE LINK will automatically turn OFF.



\* With the 3x3 video wall, connect the final display to the first display the same way as with 2x2 video wall.

**Note:** The remote control can be operated unless the IR REMOTE is set to "OFF".

## REPEAT TIMER

Use this to set two timers. Each timer can use the DIVIDER, SOURCE and WORK TIME functions.


Turn on the AUTO ID and set the DIVIDER (at 1, 4 or 9) before the following operations.

Example:

TIMER1...VIDEO1 will be displayed for 3 minutes.  
TIMER2...RGB1 will be displayed for 6 minutes in a 2x2 video wall.

Perform Steps 1-2 of VIDEO WALL, then...

3. Use the ▲ and ▼ buttons to select “REPEAT TIMER”.



4. Use the ◀ and ▶ buttons to select “ON”, then press the MENU/ENTER button.

The “REPEAT TIMER” screen appears.

5. Adjust using the ▲▼◀ and ▶ buttons.

The mode switches as follows each time the ◀ or ▶ button is pressed:



• DIVIDER

⌈ 1 ε 4 ε 9 β ⌋

• SOURCE

The available sources depend on the setting of “BNC INPUT”.

⌈ VIDEO1 ε VIDEO2 ε VIDEO3 ε HD/DVD1 β ⌋

⌈ RGB3 ε RGB2 ε RGB1 ε HD/DVD2 β ⌋

• WORK TIME

⌈ 00H01M ε 00H02M ε 00H03M ε ..... ε 04H14M ε 04H15M β ⌋

### Information

#### ■ REPEAT TIMER settings

If you set both timers, Timer 1 and Timer 2 run consecutively.

In the case of the Video wall, timer No.1 can be used to control all the displays simultaneously.

\* This becomes effective when the on-screen menu goes out.

## Advanced OSM Settings Menu


### Setting the menu mode

This allows you to access full menu items.

When P. ON DELAY or PLE LINK is ON, this won't be turned OFF.

Example: Setting “ON”

1. On the MAIN MENU, select “ADVANCED OSM”.




2. To set the ADVANCED OSM to “ON”...

Use the ◀ and ▶ buttons to select “ON”.

The mode switches as follows each time the ◀ or ▶ button is pressed:

OFF ε ON



### Information

#### ■ ADVANCED OSM settings

ON ..... All of the main menu items are available for advanced users.

OFF .... Some of the main menu items are not available (e.g. OPTION2, OPTION3).

#### ■ Restoring the factory default settings

Select “ALL RESET” under the OPTION1 menu. Note that this also restores other settings to the factory defaults.

## Language Settings Menu

### Setting the language for the menus

The menu display can be set to one of seven languages: English, German, French, Swedish, Italian, Spanish or Chinese.

Example: Setting the menu display to "DEUTSCH"

1. On the MAIN MENU, select "LANGUAGE", then press the MENU/ENTER button.  
The "LANGUAGE" screen appears.

2. To select "DEUTSCH" ...

Use the ◀ and ▶ buttons to select "DEUTSCH".  
The mode switches as follows each time the ◀ or ▶ buttons is pressed:

γ ENGLISH ε DEUTSCH ε FRANÇAIS β  
γ 中文 ε SVENSKA ε ITALIANO ε ESPAÑOL β



### Information

#### ■ Language settings

ENGLISH ..... English  
DEUTSCH ..... German  
FRANÇAIS ..... French  
ESPAÑOL ..... Spanish  
ITALIANO ..... Italian  
SVENSKA ..... Swedish  
中文 ..... Chinese

## Color System Settings Menu

### Setting the video signal format

Use these operations to set the color systems of composite video signals or Y/C input signals.


Example: Setting the color system to "3.58 NTSC"

1. On the MAIN MENU, select "COLOR SYSTEM", then press the MENU/ENTER button.  
The "COLOR SYSTEM" screen appears.

2. To select "3.58NTSC" ...

Use the ◀ and ▶ buttons to select "3.58NTSC".  
The mode switches as follows each time the ◀ or ▶ button is pressed:

γ AUTO ε 3.58NTSC ε 4.43NTSC β  
γ SECAM ε PAL-M ε PAL-N ε PAL60 ε PAL β



### Information

#### ■ Video signal formats

Different countries use different formats for video signals. Connect to the video processor country.

AUTO ..... The color systems are automatically identified and the format is set accordingly.

PAL ..... This is the standard format used mainly in the United Kingdom and Germany.

SECAM ..... This is the standard format used mainly in France and Russia.

4.43 NTSC,

PAL60 ..... This format is used for videos in countries using PAL and SECAM video signals.

3.58 NTSC ..... This is the standard format used mainly in the United States and Japan.

PAL-M ..... This is the standard format used mainly in Brazil.

PAL-N ..... This is the standard format used mainly in Argentina.

## Source Information Menu


### Checking the frequencies, polarities of input signals, and resolution

Use this function to check the frequencies and polarities of the signals currently being input from a computer, etc.

Press the MENU/ENTER button on the remote control to display the MAIN MENU on the screen, then...

1. On the MAIN MENU, select "SOURCE INFORMATION", then press the MENU/ENTER button.

2. The "SOURCE INFORMATION" is displayed.



PC: MEMORY will be displayed.  
Others: MODE will be displayed.


# External Control

## Application

These specifications cover the communications control of the plasma monitor by external equipment.

## Connections

Connections are made as described below.



Connector on the plasma monitor side: **EXTERNAL CONTROL** connector.

Use a crossed (reverse) cable.

### Type of connector: D-Sub 9-pin male

Pin No.	Pin Name
1	No Connection
2	RXD (Receive data)
3	TXD (Transmit data)
4	DTR (DTE side ready)
5	GND
6	DSR (DCE side ready)
7	RTS (Ready to send)
8	CTS (Clear to send)
9	No connection



## Communication Parameters

- |                          |              |
|--------------------------|--------------|
| (1) Communication system | Asynchronous |
| (2) Interface            | RS-232C      |
| (3) Baud rate            | 9600 bps     |
| (4) Data length          | 8 bits       |
| (5) Parity               | Odd          |
| (6) Stop bit             | 1 bit        |
| (7) Communication code   | Hex          |

## External Control Codes (Reference)

FUNCTION		CODE DATA							
		9FH	80H	60H	4EH	00H	CDH		
Power ON	ON	9FH	80H	60H	4EH	00H	CDH		
	OFF	9FH	80H	60H	4FH	00H	CEH		
Input Switch	Video1 (BNC)	DFH	80H	60H	47H	01H	01H	08H	
	Video2 (RCA)	DFH	80H	60H	47H	01H	02H	09H	
	Video3 (S-Video)	DFH	80H	60H	47H	01H	03H	0AH	
	DVD1/HD1 (RCA)	DFH	80H	60H	47H	01H	05H	0CH	
	DVD2/HD2 (BNC)	DFH	80H	60H	47H	01H	06H	0DH	
	RGB1 (mini D-sub 15-pin)	DFH	80H	60H	47H	01H	07H	0EH	
	RGB2 (5BNC)	DFH	80H	60H	47H	01H	08H	0FH	
RGB3 (DVI)	DFH	80H	60H	47H	01H	0CH	13H		
Audio Mute	ON	9FH	80H	60H	3EH	00H	BDH		
	OFF	9FH	80H	60H	3FH	00H	BEH		
Picture Mode	NORMAL	DFH	80H	60H	0AH	01H	01H	CBH	
	THEAT. 1	DFH	80H	60H	0AH	01H	02H	CCH	
	THEAT. 2	DFH	80H	60H	0AH	01H	03H	CDH	
	DEFAULT	DFH	80H	60H	0AH	01H	04H	CEH	
Screen Mode	STADIUM	DFH	80H	60H	51H	01H	02H	13H	
	ZOOM	DFH	80H	60H	51H	01H	03H	14H	
	NORMAL	DFH	80H	60H	51H	01H	04H	15H	
	FULL	DFH	80H	60H	51H	01H	05H	16H	
	14 : 9	DFH	80H	60H	51H	01H	09H	1AH	
	2.35 : 1	DFH	80H	60H	51H	01H	0AH	1BH	
Auto Picture	ON	DFH	80H	60H	7FH	03H	03H	09H	00H 4DH
	OFF	DFH	80H	60H	7FH	03H	03H	09H	01H 4EH
Cinema Mode	ON	DFH	80H	60H	C1H	01H	01H	82H	
	OFF	DFH	80H	60H	C1H	01H	02H	83H	

**Note:** Contact your local dealer for a full list of the External Control Codes if needed.

# Troubleshooting

If the picture quality is poor or there is some other problem, check the adjustments, operations, etc., before requesting service.

Symptom	Checks	Remedy
Mechanical sound is heard.	<ul style="list-style-type: none"> <li>• Maybe the sound from the cooling fans used to prevent over heating.</li> </ul>	
The unit emits a crackling sound.	<ul style="list-style-type: none"> <li>• Are the image and sound normal?</li> </ul>	<ul style="list-style-type: none"> <li>• If there are no abnormalities in the image and sound, the noise is caused by the cabinet reacting to changes in humidity. This will not affect performance.</li> </ul>
Picture is disturbed. Sound is noisy. Remote control operates erroneously.	<ul style="list-style-type: none"> <li>• Is a connected component set directly in front or at the side of the display?</li> </ul>	<ul style="list-style-type: none"> <li>• Leave some space between the display and the connected components.</li> </ul>
The remote control does not work.	<ul style="list-style-type: none"> <li>• Are the remote control's batteries worn out?</li> <li>• Is IR REMOTE set to ON?</li> <li>• Has an ID number been set for the main unit?</li> </ul>	<ul style="list-style-type: none"> <li>• Replace both batteries with new ones.</li> <li>• Set IR REMOTE OFF on OPTION3 menu.</li> <li>• Set an ID number with the ID SELECT button, or set the ID number to ALL.</li> </ul>
Monitor's power does not turn on when the remote control's power button is pressed.	<ul style="list-style-type: none"> <li>• Is the monitor's power cord plugged into a power outlet?</li> <li>• Are all the monitor's indicators off?</li> <li>• Are the remote control's batteries worn out?</li> <li>• Is IR REMOTE set to ON?</li> <li>• Has an ID number been set for the main unit?</li> </ul>	<ul style="list-style-type: none"> <li>• Plug the monitor's power cord into a power outlet.</li> <li>• Press the power button on the monitor to turn on the power.</li> <li>• Replace both batteries with new ones.</li> <li>• Set IR REMOTE OFF.</li> <li>• Set an ID number with the ID SELECT button, or set the ID number to ALL.</li> </ul>
Monitor does not operate when the remote control's buttons are pressed.	<ul style="list-style-type: none"> <li>• Is the remote control pointed at the monitor, or is there an obstacle between the remote control and the monitor?</li> <li>• Is direct sunlight or strong artificial light shining on the monitor's remote control sensor?</li> <li>• Are the remote control's batteries worn out?</li> <li>• The remote cable is plugged into the REMOTE IN terminal (Wired).</li> </ul>	<ul style="list-style-type: none"> <li>• Point the remote control at the monitor's remote control sensor when pressing buttons, or remove the obstacle.</li> <li>• Eliminate the light by closing curtains, pointing the light in a different direction, etc.</li> <li>• Replace both batteries with new ones.</li> <li>• Unplug the remote cable from the monitor.</li> </ul>
The front panel buttons of the main unit do not function.	<ul style="list-style-type: none"> <li>• The front panel buttons do not function during Control Lock.</li> </ul>	<ul style="list-style-type: none"> <li>• Set the Control Lock to OFF.</li> </ul>
No sound or picture is produced.	<ul style="list-style-type: none"> <li>• Is the monitor's power cord plugged into a power outlet?</li> </ul>	<ul style="list-style-type: none"> <li>• Plug the monitor's power cord into a power outlet.</li> </ul>
Picture appears but no sound is produced.	<ul style="list-style-type: none"> <li>• Is the volume set at the minimum?</li> <li>• Is the mute mode set?</li> <li>• Are the speakers properly connected?</li> <li>• Is AUDIO INPUT set correctly?</li> </ul>	<ul style="list-style-type: none"> <li>• Increase the volume.</li> <li>• Press the remote control's MUTE button.</li> <li>• Connect the speakers properly.</li> <li>• Set AUDIO INPUT on the AUDIO menu correctly.</li> </ul>
Poor picture with VIDEO signal input.	<ul style="list-style-type: none"> <li>• Improper control setting.</li> <li>• Local interference.</li> <li>• Cable interconnections.</li> <li>• Input impedance is not correct level.</li> </ul>	<ul style="list-style-type: none"> <li>• Adjust picture control as needed.</li> <li>• Try another location for the monitor.</li> <li>• Be sure all connections are secure.</li> </ul>
Poor picture with RGB signal input.	<ul style="list-style-type: none"> <li>• Improper control setting.</li> <li>• Incorrect 15 PIN connector pin connections.</li> </ul>	<ul style="list-style-type: none"> <li>• Adjust picture controls as needed.</li> <li>• Check pin assignments and connections.</li> </ul>
Tint is poor or colors are weak.	<ul style="list-style-type: none"> <li>• Are the tint and colors properly adjusted?</li> </ul>	<ul style="list-style-type: none"> <li>• Adjust the tint and color (under PICTURE).</li> </ul>
Nothing appears on screen.	<ul style="list-style-type: none"> <li>• Is the computer's power turned on?</li> <li>• Is a source connected?</li> <li>• Is the power management function in the standby or off mode?</li> <li>• Is LOOP OUT set to ON?</li> </ul>	<ul style="list-style-type: none"> <li>• Turn on the computer's power.</li> <li>• Connect source to the monitor.</li> <li>• Operate the computer (move the mouse, etc.).</li> <li>• Set LOOP OUT OFF.</li> </ul>
Part of picture is cut off or picture is not centered.	<ul style="list-style-type: none"> <li>• Is the position adjustment appropriate?</li> </ul>	<ul style="list-style-type: none"> <li>• Adjust the IMAGE ADJUST properly.</li> </ul>
Image is too large or too small.	<ul style="list-style-type: none"> <li>• Is the screen size adjustment appropriate?</li> </ul>	<ul style="list-style-type: none"> <li>• Press the WIDE button on the remote control and adjust properly.</li> </ul>
Picture is unstable.	<ul style="list-style-type: none"> <li>• Is the computer's resolution setting appropriate?</li> </ul>	<ul style="list-style-type: none"> <li>• Set to the proper resolution.</li> </ul>
POWER/STANDBY indicator is lighted in red.	<ul style="list-style-type: none"> <li>• Horizontal and / or vertical sync signal is not present when the Intelligent Power Manager control is on.</li> </ul>	<ul style="list-style-type: none"> <li>• Check the input signal.</li> </ul>
POWER/STANDBY indicator is blinking in red.	<ul style="list-style-type: none"> <li>• The temperature inside the main unit has become too high and has activated the protector.</li> </ul>	<ul style="list-style-type: none"> <li>• Promptly switch off the power of the main unit and wait until the internal temperature drops. See*1.</li> </ul>
POWER/STANDBY indicator is blinking in green and red, or green.	<ul style="list-style-type: none"> <li>• _____</li> </ul>	<ul style="list-style-type: none"> <li>• Promptly switch off the power of the main unit. See *2.</li> </ul>

---

\*1 Overheat protector

If the monitor becomes too hot, the overheat protector will be activated and the monitor will be turned off. If this happens, turn off the power to the monitor and unplug the power cord. If the room where the monitor is installed is particularly hot, move the monitor to a cooler location and wait for the monitor to cool for 60 minutes. If the problem persists, contact your dealer.

\*2 In the following case, power off the monitor immediately and contact your dealer or authorized Service Center.

The monitor turns off 5 seconds after powering on and then the POWER/STANDBY indicator blinks. It indicates that the power supply circuit, plasma display panel, temperature sensor, or one or more fans have been damaged.



# Limited Warranty Plasma Monitors

## Faroudja warrants

this product to be free from defects in material and workmanship under the following terms and, subject to the conditions set forth below, agrees to repair or replace (at Faroudja's sole option) any part of the enclosed unit which proves defective. Replacement parts or products may be new or refurbished and will meet specifications of the original parts or products.

## HOW LONG IS THE WARRANTY?

Parts and labor are warranted for (4) four years from the date of the first customer purchase.

## WHO IS PROTECTED?

This warranty may be enforced only by the first purchaser.

## WHAT IS COVERED AND WHAT IS NOT COVERED

Except as specified below, this warranty covers all defects in material or workmanship in this product. The following are not covered by the warranty:

1. Any product which is not distributed in the U.S.A. or Canada by Faroudja or which is not purchased in the U.S.A. or Canada from an authorized Faroudja dealer.
2. Any product of which the serial number has been defaced, modified or removed.
3. Damage, deterioration or malfunction resulting from:
  - a. Accident, misuse, abuse, neglect, fire, water, lightning or other acts of nature, unauthorized product modification, or failure to follow instructions supplied with the product.
  - b. Repair or attempted repair by anyone not authorized by Faroudja.
  - c. Any shipment of the product (claims must be presented to the carrier).
  - d. Removal or installation of the product.
  - e. Any other cause which does not relate to a product defect.
  - f. Burns or residual images upon the phosphor of the panel.
4. Cartons, carrying cases, batteries, external cabinets, magnetic tapes, or any accessories used in connection with the product.
5. Service outside of the U.S.A. and Canada.

## WHAT WE WILL PAY FOR AND WHAT WE WILL NOT PAY FOR

We will pay labor and material expenses for covered items, but we will not pay for the following:

1. Removal or installation charges.
2. Costs of initial technical adjustments (set-up), including adjustment of user controls. These costs are the responsibility of the Faroudja dealer from whom the product was purchased.
3. Shipping charges.

## HOW YOU CAN GET WARRANTY SERVICE

1. To obtain service on your product, consult the dealer from whom you purchased the product.
2. Whenever warranty service is required, the original dated invoice (or a copy) must be presented as proof of warranty coverage. Please also include in any mailing your name, address and a description of the problem(s).
3. For the name of the nearest Faroudja authorized service center, call Faroudja at 408 735 1492.

## LIMITATIONS OF LIABILITY

Except for the obligations specifically set forth in this warranty statement, we will not be liable for any direct, indirect, special, incidental, consequential, or other types of damages, whether based on contract, tort, or any other legal theory, whether or not we have been advised of the possibility of such damages. This warranty is in lieu of all other warranties expressed or implied, including, but not limited to, the implied warranties of merchantability or fitness for a particular purpose.

## EXCLUSION OF DAMAGES

Faroudja's liability for any defective product is limited to the repair or replacement of the product at our option. Faroudja shall not be liable for:

1. Damage to other property caused by any defects in this product, damages based upon inconvenience, loss of use of the product, loss of time, commercial loss; or
2. Any other damages whether incidental, consequential or otherwise. Some states do not allow limitation on how long an implied warranty lasts and/or do not allow the exclusion or limitation of incidental or consequential damages, so the above limitations and exclusions may not apply to you.

## HOW STATE LAW RELATES TO THE WARRANTY

This warranty gives you specific legal rights, and you may also have other rights which vary from state to state.

FOR MORE INFORMATION,  
TELEPHONE 408 735 1492  
Faroudja  
750 Palomar Ave.  
Sunnyvale, CA 94085

**Note:** All products returned to Faroudja, for service **MUST** have prior approval. To get approval, call 408 735 1492 or visit the Support page at [www.faroudja.com](http://www.faroudja.com).

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>