



DJM-700

defining the industry standard.

For all your product info, dealers and more: www.PioneerDJ.com 800-782-7210

DJM-700

FEATURES

World's First Effect Frequency Filter

The Pioneer DJM-700 is the world's first mixer to include an Effect Frequency Filter that allows the user to limit the frequency bands subjected to effects. Conventional effectors are limited to manipulating the entire frequency range, whereas the Effect Frequency Filter now expands the user's ability to showcase their own mixing style.

Manual Filter Capabilities

The DJM-700 mixer also utilizes the same manual filter found on the well-renowned DJM-800. The manual filter enables more intuitive settings for multi-layered effects expanding the DJs creativity with their music. Combining multi-effect options such as the Beat Effect, along with the manual filter allows for a wider range of DJ style and expression.

Multiple Effects Capabilities

The DJM-700 also features multiple effects that can be synced with its tempo (beat) capabilities:

- **Beat Effect:** Pioneered from the DJM-600, the beat effect has evolved into a 96kHz / 24-bit high performance effect in the DJM-700. The mixer automatically detects the tempo, also known as beats per minute (BPM), of the tune so the effects are aligned perfectly with the beat. The DJM-700 features various effects such as delay, echo, transformer, filter, flanger, phaser, reverb, robot and crush.
- **Roll Sampler:** The DJM-700 incorporates a new roll sampler with a 96kHz/24-bit output which allows for real-time sampling of sounds. Four patterns of sampling are available which includes roll, reverse roll, pitch up roll and pitch down roll.
- **Beat Select Buttons:** The mixer incorporates two beat select buttons letting the user quickly select the effect timing to add even further control over the effects.

Fully Assignable MIDI functions

DJs with external equipment such as DJ Effectors or DJ software applications that support MIDI control can rely on the DJM-700 to work in unison to create the ultimate DJ experience. 49 of the buttons, knobs and switches on the DJM-700 provide direct MIDI signal output for a variety of control options of external devices.

Additional Features:

- **Digital Output Terminal:** Outputs 96kHz/24-bit sampling rate for the highest quality sound
- **Cross Fader Assign:** Each channel of the mixer can be assigned to the cross fader
- **3-Band Equalizer:** A built-in equalizer on each channel enables level control within a -26 dB to +6 dB range for high, mid and low bands, respectively
- **Fader Curve Adjust:** The user can change the cross fader/channel fader curve
- **Talk Over:** The mixer automatically lowers track volume when it senses vocal input on the microphone
- **Peak Level Meter:** A 15 segment LED meter shows the input audio levels for each channel plus the master output level
- **Fader Start:** With Pioneer CDJ products, the fader can automatically start the players by simply sliding the cross fader or channel fader

For more information and streaming demo videos, visit

www.pioneerdj.com/gear_DJM700

SPECIFICATIONS

Frequency Response	20Hz - 20kHz	Output Terminal	MASTER OUTx2 (RCA x1, XLR x1)
Signal-to-Noise Ratio	104dB (LINE)		BOOTH OUT x1 (RCA)
Total Harmonic Distortion	0.005% or less		HEADPHONE MONITOR OUT x1(TOP PANEL 1/4" PHONE x1)
Power Requirements	AC 120V, 60Hz		REC OUT x1(RCA)
Power Consumption.....	34W		DIGITAL OUT x1 (COAXIAL)
Net Weight	14.5lbs	Other Terminals	SEND x1(1/4" PHONE)
Dimensions.....	12.6" (W) x 14.9" (D) x 4.25" (H)		RETURN x1(1/4"PHONE)
Head Room.....	19dB		MIDI OUT x1(5P DIN)
A/D, D/A Converter	24-bit		CONTROL OUT (3.5 MINI JACK) x2
Sampling Rate.....	96kHz		
Input Terminal	CD/LINE x5 (RCA)		
	PHONO x3 (RCA)		
	MIC x2 (XLR x1, 1/4" PHONE x1)		

Pioneer

PIONEER CORPORATION
1-4-1 Meguro, MEGURO-KU, TOKYO 153-8654, JAPAN
TEL: 81-3-3495-5246 • FAX: 81-3-3495-9827

PIONEER ELECTRONICS (USA), INC.
2265 East 220th Street, Long Beach, CA 90810, U.S.A.
TEL: 800-421-1404 • FAX: 310-952-2990

PIONEER ELECTRONICS ASIACENTRE, PTE. LTD. (PAC Head Office)
253 Alexandra Road, #04-01, SINGAPORE 159936
TEL: 65-6427-1111

PIONEER EUROPE NV - MULTIMEDIA DIV. (PEE-London)
Pioneer House, Hollybush Hill, Stoke Poges Slough, SL2 4QP, UNITED KINGDOM
TEL: 44-1753-789-789

PIONEER CHINA HOLDINGS CO., LTD. (PCH)
18F New Hua Lian Mansion (West), 775 Huai Hai Zhong Road (M), Shanghai 200020, CHINA
TEL: 86-21-6431-4466

PIONEER HIGH FIDELITY TAIWAN CO., LTD. (PTC)
13th FL, No.44, Jhongshan N Road, Taipei City, 10448 TAIWAN
TEL: 886-2-2521-3588

PIONEER ELECTRONICS AUSTRALIA PTY. LTD. (PTY)
178-184 Boundary Road, Braeside, Victoria 3195, AUSTRALIA
TEL: 507-300-3900

PIONEER INTERNATIONAL LATIN AMERICA S.A. (PILASA)
Plaza Credicorp Bank, 14th Floor, Calle 50 No.120, Panama City 0816-01361, R.O., PANAMA
Tel: 507-300-3900

Features and specifications subject to change without notification.

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>