

marantz



7.2 Channel 4K & 3D Pass Through, Networking Home Theater Receiver with AirPlay

Simplicity and elegance characterize the SR7007. With the blue illuminated and iconic porthole display plus the drop-down door in all brushed aluminum front panel, the receiver offers both style and comprehensive features, including an Ethernet port, seven HDMI inputs, three HDMI outputs, and playback of the latest hi-definition audio formats. AirPlay[®] allows you to stream music wirelessly from your iPhone[®], iPod[®] Touch and iPad[®] over your home network. Three audio and video zones, networking, and support for Bluetooth devices deliver the flexibility you need. While our proprietary HDAM (Hyper-Dynamic Amplifier Module) audio circuits, Current Feedback topology, and seven fully-discrete, 125 watt amplifiers provide the crushing dynamics detail retrieval you demand.

Audio/Video Quality

- Fully discrete power amplifier for all 7 channels (125 W x 7 ch, 80hm 20-20kHz 0.08%)
- Current feedback & HDAM pre amplifier circuit
- 4K video support (path-through and GUI overlay)
- 3D pass-through technology for enjoying 3D video entertainment with dynamic surround sound
- 1080p/24Hz upscaling via HDMI
- 4K (3840×2160) upscaling via HDMI

Connectivity, Flexibility & Expandability

Airplay: Stream music from your iPad, iPhone or iPod Touch or from your iTunes music library

■ Internet Radio

Networking Ready: Stream internet radio, Pandra, SIRIUS XM, as well as music and photos over the home network

Bluetooth wireless connectivity (M-XPort) via optional RX-101 adaptor

 Gold plated 7.2 Channel Pre-amp outputs (parallel) allow the connection of external power amplifiers if needed

Front Panel USB Input Direct digital play for iPod, iPhone and USB drives ■ 7 (front: 1) /2 HDMI In/Out

-Simultaneous dual outputs allows two video devices connected and output same source simultaneously

- -CEC (Control)
- -ARC (Audio Return Channel)
- -Standby source setting via HDMI control -Auto Lip Sync.
- -Deep Color, "x.v.Color"
- -Pass through in standby mode
- -Zone2 HDMI output allows different source for zone2
- Audyssey MultEQ XT setup
- Audyssey Dynamic EQ & Dynamic Volume
- 3/1 (gold plated) Component In/Out
- 4 (front: 1) / 2 (gold plated) Composite In/Out
- 2/2 Optical/Coaxial (gold plated)Digital In
- Headphone output
- HD Radio (AM/FM) and FM Tuner
- 56 Tuner Presets
- 6 Audio inputs (incl. front input) and an output(gold plated)
- Phono input (gold plated)
- 7.1 ch Input

Ease of Use

Improved System Setup with menu assist.

Rich overlay GUI with English, French, or Spanish

New LCD Learning Remote handset

Auto Power Off

Mobile App control with advanced media browsing.
(iOS & Android)

Additional Features

Power amp Assign for 7.1ch (SB ch.), 5.1ch + Front Height, 5.1 ch + Front Wide, 5.1ch + Bi-Amp, 5.1ch + zone, or 5.1ch + Front B

Selectable zone component monitor, Zone 2

CVBS monitor, and Zone 2 HDMI monitor

- 3 source Zone 3 capability
- IR Flasher In
- RS232C control (AMX/Crestron command)
- C4 certified (IP/232C)

Assignable DC trigger (+12V, 150mA x 2)

Firmware Upgradable via Internet

Marantz Audio Advantage

- Pure Direct / Source Direct
- M-DAX (Marantz Dynamic Audio eXpander)
- 192kHz/24-bit Audio DACs
- Transparent binding post speaker terminals (gold plated)
- DSD to PCM convert playback capability
- Aluminum front panel with trap door and aluminum knobs

Download from Www.Somanuals.com. All Manuals Search And Download.

Specifications

Audio Section Power amplifier Rated output: Front: 125 W + 125 W (8 ohm, 20 Hz - 20 kHz with 0.08 % T.H.D.) 195 W + 195 W (6 ohm, 1 kHz with 10 % T.H.D.) Center: 125 W (8 ohm, 20 Hz - 20 kHz with 0.08 % T.H.D.) 195 W (6 ohm, 1 kHz with 10 % T.H.D.) Surround: 125 W + 125 W (8 ohm, 20 Hz - 20 kHz with 0.08 % T.H.D.) 195 W + 195 W (6 ohm, 1 kHz with 10 % T.H.D.) Surround back: 125 W + 125 W (8 ohm, 20 Hz - 20 kHz with 0.08 % T.H.D.) 195 W + 195 W (6 ohm, 1 kHz with 10 % T.H.D.) Analog Input sensitivity/Input impedance: 200 mV/47 k ohm Frequency response: 10 Hz - 100 kHz - +1, -3 dB (DIRECT mode) S/N: 102 dB (IHF-A weighted, DIRECT mode) Digital D/A output: Rated output - 2 V (at 0 dB playback) Total harmonic distortion - 0.008 % (1 kHz, at 0 dB) S/N ratio — 102 dB Dynamic range — 100 dB Digital input: Format - Digital audio interface

Phono equalizer (PHONO input)

Input sensitivity: 2.5 mV RIAA deviation: ±1 dB (20 Hz to 20 kHz) S/N: 74 dB (A weighting, with 5 mV input) Rated output: 150 mV Distortion factor: 0.03 % (1 kHz, 3 V)

Video Section

Standard video connectors Input/output level and impedance: 1 Vp-p, 75 ohm Frequency response: 5 Hz – 10 MHz 0, –3 dB Color component video connector

Input/output level and impedance: Y signal — 1 Vp-p, 75 ohm PB / CB signal — 0.7 Vp-p, 75 ohm PR / CR signal — 0.7 Vp-p, 75 ohm Frequency response: 5 Hz – 60 MHz — 0, –3 dB

Tuner Section

[FM] (Note: μV at 75 ohm , 0 dBf = 1 x 10–15 W) Receiving Range:87.5 MHz – 107.9 MHz Usable Sensitivity: 1.5 μV (14.8 dBf) S/N: MONO 78 dB (IHF–A weighted, DIRECT mode) STEREO 68 dB (IHF–A weighted, DIRECT mode) HD 85 dB Total harmonic Distortion (at 1 kHz): MONO 0.1 % STEREO 0.2 % HD 0.02%

[AM]

Receiving Range:AM: 530kHz – 1710kHz Usable Sensitivity: 20 µV S/N: HD 85 dB Total harmonic Distortion (at 1 kHz): HD 0.02 %

General

AirPlay

Power supply: AC 120 V, 60 Hz Power consumption: 670 W 0. 2 W (Standby mode) 0.5 W (CEC standby mode) 2.7W (network standby mode) Dimensions (W x H x D): 17 21/64" x 7 23/64 " x 15 63/64" 440 x 187 x 406 mm Weight: 27 lbs 9oz, 12.5 kg

Technology





H) Radio



(((SiriusXM)))



PANDORA[°]





4K video support (Video passthrough, video upscaling) Dual HDMI outputs





Stream music from your iPad®, iPhone® or iPod New Apps Touch® or from your iTunes® music library.



w o -۲ All and . \odot 000 0 0 0 0 0 I

©2012 Marantz America, LLC.

For purposes of improvement, specifications and design are subject to change without notice.All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, LLC. or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors Being made by dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.

1-855-ONE-MARANTZ 1-855-663-6272 Call for Assistance: 9:00AM to 8:00PM M-F E.S.T. For frequently asked questions please visit www.marantz.com

www.marantz.com

Download from Www.Somanuals.com. All Manuals Search And Download.

Free Manuals Download Website <u>http://myh66.com</u> <u>http://usermanuals.us</u> <u>http://www.somanuals.com</u> <u>http://www.4manuals.cc</u> <u>http://www.4manuals.cc</u> <u>http://www.4manuals.cc</u> <u>http://www.4manuals.com</u> <u>http://www.404manual.com</u> <u>http://www.luxmanual.com</u> <u>http://aubethermostatmanual.com</u> Golf course search by state

http://golfingnear.com Email search by domain

http://emailbydomain.com Auto manuals search

http://auto.somanuals.com TV manuals search

http://tv.somanuals.com