# **SPECIFICATIONS SHEET**



# SI-2125 SYSTEM INTEGRATION AMPLIFIERS®





# High Current, Bridgeable Power Amplifier

- 2 Channel Amplifier
- 125W RMS per channel; Bridgeable to 300W RMS

## **Stereo Power Amplifiers**



# SI-2125

Model	Stock Number
Standard	FG01055
Rack Mount	FG01056
Export Version	FG01057

Stable into low-impedance loads (2.66 ohms in stereo mode, 4 ohms in bridged mode)

#### PROTECTION:

DC, short-circuit, and overload protection with automatic reset

2 X 125W RMS/channel into 8 ohms (both channels driven) 2 X 200W RMS/channel into 4 ohms (both channels driven) 1 X 300W RMS, one channel bridged into 8 ohms

#### SPECIFICATIONS:

- Rated current draw: 8 amps
- Rack mount version takes up three rack spaces

impedance loads are handled with ease

- Overall dimensions: 17" wide (standard), 19" wide (rack mount) x 5-1/2" high (including feet) x 14" deep (including binding posts)
- Warranty: Two-year limited

2003 Audio Video International Hi-Fi Grand Prix Award



## Technology

#### HIGH CURRENT DESIGN

Assures that even the most demanding loads are handled with ease

MULTIPLE TURN ON MODES Provide system design flexibility and reliable operation

## CASCADE OUTPUTS

Facilitate multiple amplifier connections

#### INDEPENDENT LEVEL CONTROLS

Provide installer-adjustable level for every channel

#### CHANNEL BRIDGING

Increases output power for demanding loads and high sound pressure levels

## Details

# GOLD PLATED INPUT JACKS AND OUTPUT TERMINALS

Ensure positive connections over long periods of time

# REMOVABLE TWO-PRONG IEC COMPATIBLE POWER CORD

Simplifies installation and servicing

# FRONT PANEL DISPLAY INDICATORS

Relay critical information about on/off status and protection modes

#### MASSIVE HEAT SINKS

Maintain cool operating temperatures without the use of noisy fans

#### TOROIDAL POWER TRANSFORMERS

Deliver ideal performance even under the most demanding circumstances

#### SHELF OR RACK MOUNT CONFIGURATIONS

Accommodate every installation need

#### POWER Fully discrete, high-current stereo amplifier design ensures that even the most demanding low

Free Manuals Download Website <u>http://myh66.com</u> <u>http://usermanuals.us</u> <u>http://www.somanuals.com</u> <u>http://www.4manuals.cc</u> <u>http://www.4manuals.cc</u> <u>http://www.4manuals.cc</u> <u>http://www.4manuals.com</u> <u>http://www.404manual.com</u> <u>http://www.luxmanual.com</u> <u>http://aubethermostatmanual.com</u> Golf course search by state

http://golfingnear.com Email search by domain

http://emailbydomain.com Auto manuals search

http://auto.somanuals.com TV manuals search

http://tv.somanuals.com