



OK-NIP10-A420 OK-NIP10-A420P OK-NIP10-A420G – Wireless OK-NIP10-A420GP – Wireless PTZ X10 MPEG4/JPEG IP Camera

Quick Installation Guide

This guide describes the basic functions of Network Camera with Pan/Tilt/Zoom. All detailed information is described in the user's manual.





 \bigcirc Power off the Network Camera as soon as it is found smoking or smelt unusual.



Contact your distributor when such cases happen.

◎ Keep the Network Camera away from the water. If the Network Camera is wet, power off immediately.



Contact your distributor when such cases happen.

 \odot Do not place the Network Camera around the heat sources, such as television or oven.



O Refer to your user's manual for the operating temperature.



 \bigcirc Keep the Network Camera away from the direct sunlight.



O not place the Network Camera in high humid environments.



 \bigcirc Do not place the Network Camera on unsteady surfaces.





Do not touch the Network Camera when it's lightening.



O not disassemble the Network Camera.



 \bigcirc Do not drop the Network Camera.



 \bigcirc Do not manually pan and tilt the Network Camera when are power is on.



 \bigcirc Do not insert any object into the Network Camera, such as needles.





1. Check Package contents

O The Network Camera (Wire or Wireless model)



⊘ Power adapter



◎ Camera stand



◎ A/V cable





◎ Antennas for wireless model only

○ Software CD



O Remote controller





2. Physical description

◎ Front panel



O Rear panel





3. Install your Network Camera in Ethernet network



3. Finally, connect power cord to a power outlet.



4. Assign IP address

- 1. Run the "Installer Wizard" under the Software Utility directory from software CD.
- 2. The program will search the servers or cameras on the same LAN.



2. Physical description

- Click "Link to selected device(s)" to connect the Internet Explorer to the Network Camera.
- %If there is no DHCP server on the LAN, please refer to the user's manual for the methods of assigning an IP address.

_	Serial Number	IP Address	Azigred	Aes P
Setup >	00-02-01-00-00-56	192,168,1,100	Yer	Vez
	00.02.01.00.56.F1	192,168,1,118	Yes	Yes
Apgrade	00-02-01-00-00-57	192,168,1.99	Ves	Vez
	00-02-01-28-00-2E	192,168,1,83	Vez	Ver
	00-02-01-00-00-4A	192,168,1,215	Yez	Yes
set to detaut	0042-01-00-00-23	192,168,1.55	Yes	Yes
	0042-0140-0530	192,168,1,69	Yes	Yes
	0042-01-00-00-15	192, 168, 1, 203	Ves	Vez
	00402-01-24400-07	192,168,1,208	Ver	Vez
	00-02-01-00-00-49	192,168.1,215	Yez	Yes
Lat .				
Red	Search Add	lenove	Incheck All	link to selected device Ø



5. The Internet Explorer Connects to the Network Camera



For setup further configuration, please check user's manual on the software CD.



6. Client Settings (Windows XP/2000/Me/98SE)

At the initial access to the "Connection type" page in Windows, the web browser will ask for a new plug-in installation, the plug-in being the Network Camera. This plug-in has been registered for certification and can be used to change the parameters at the client's site. The user may click on to install the plug-in. If the web browser does not allow the user to complete the installation, check the Internet security to lower the security level or contact your IT or networking supervisor.

1. Initial IE browser, select function item "Tools"-> "Internet Options"



2. Security-> Default Level





3. Lower down the security level bar to "Low", and press "Apply"

Select a		ontent zone t	o specify	its securit	y setting	3 5.	
Secur -	Interne This zon haven't j Move - Low - N - A	t e contains al placed in oth or this zone - the slider to linimal safegu lost content i la active cont	I Web sit er zones set the s uards and is downlo	es you ecurity lev d warning paded and run	rel for the run with	is zone.	ded bts
		ppropriate fo	r sites the <u>C</u> ustom	Level	Canc	Default L	

4. Refresh IE Browser, a question frame will pop-up to ask for download Active-X. press "Yes".





7. Client Settings (Windows XP SP2)

<u>File E</u> d	lit <u>V</u> iew	Favorites	<u>Tools</u> <u>H</u> elp	
← → → → Back Forward		Mail and News		
A <u>d</u> dress [http://19	2.168.0.99	Win	dows <u>U</u> pdate w Related Links
		8	510	w <u>R</u> elated BHIKS

1. Initial IE browser, select function item "Tools"→ "Internet Options"

2. Security →"Custom Level"





3. Security Settings → Download unsigned ActiveX Controls set "Enable" and press "OK"

Security Se	ettings	?×
Settings:		
	wnload signed ActiveX contr Disable Enable Prompt wnload unsigned ActiveX cor Disable Enable Prompt cialize and script ActiveX con Disable Enable Prompt	rols
	A device to the controls and plage	
Reset cust	om settings	
Reset to:	Medium	Reset
L		OK Cancel

4. Press "Apply" and then "OK"





5. Key-In camera's IP address and press "OK" on Information Bar.



6. Click the blue bar under the Camera's IP address in the browser, then choose "Install ActiveX Control"

Install ActiveX Control	
What's the Risk?	
Information Bar Help	

7. Recover security settings. Download unsigned ActiveX Controls set

"Disable" and press "OK" and "Apply"

Security Sec	ettings		?×
Settings:			
Do Do	wnload signed Ad	tiveX controls	~
8) Enable		
_ 0	Prompt		
	wnload unsigned	ActiveX controls	
	Disable		
l s	Prompt		
🕼 Ini	itialize and script A	ActiveX controls not ma	irked as safe
	Disable		
	Enable		
	n ActiveX controls	s and plug-ins	
	·		×
Reset cus	tom settings		
Reset to:	Medium	~	Reset
<u> </u>			
		ОК	Cancel

Free Manuals Download Website <u>http://myh66.com</u> <u>http://usermanuals.us</u> <u>http://www.somanuals.com</u> <u>http://www.4manuals.cc</u> <u>http://www.4manuals.cc</u> <u>http://www.4manuals.cc</u> <u>http://www.4manuals.com</u> <u>http://www.404manual.com</u> <u>http://www.luxmanual.com</u> <u>http://aubethermostatmanual.com</u> Golf course search by state

http://golfingnear.com Email search by domain

http://emailbydomain.com Auto manuals search

http://auto.somanuals.com TV manuals search

http://tv.somanuals.com