



*SBAH-821



*SBAL-600

SBAH-821 / SBAL-600

Features - SBAH-821

- * 3 spaced outlets design provides room for the large transformer blocks
- * 2-in-1 rocker switch integrated with a 15 Amp overload circuit breaker
- * Sliding safety covers - help to protect users and their children, keep dust and debris away from unused outlets
- * EMI / RFI noise filter - to eliminate AC line noise
- * Surge protection - to provide a safety power to avoid damage from a surge strike
- * Telephone line protection - protects your internet modem or FAX / TEL from surges and spikes
- * Coax / DSS protection - protects the Antenna / CATV / MATV coaxial cable from surges and spikes
- * Mounting key holes
- * 6 feet SJT14AWG x 3C heavy duty power cord

Features - SBAL-600

- * 2-in-1 rocker switch integrated with a 15 Amp overload circuit breaker
- * Sliding safety covers—help to protect users and their children, keep dust and debris away from unused outlets
- * Surge protection—to provide a safety power to avoid damage from surge strike
- * Mounting key holes
- * 4 feet SJT14AWG x 3C heavy duty power cord

Specifications

| Model Name | | SBAH-821 | SBAL-600 |
|------------------------------|-------------------|------------------------------------|----------|
| Outlets Number | | 8 | 6 |
| Outlets Type | | American Type | |
| Electrical Rating | | 15A, 125VAC, 1875W | |
| Surge Energy Joule Rating | | 3240 J | 241 J |
| Surge Protection Mode | | L-N, L-G, N-G | L-N |
| Clamping Voltage | | 330 V | |
| Max. Peak Spike Current | | 216000A | 12000A |
| Max. Spike Voltage | | 6kV | |
| EMI/RFI Noise Filter | Frequency | 150 kHz~100 MHz | N/A |
| | Attenuation | Up to 60 dB | N/A |
| DSS/COAX Cable Protection | Jack Type | F Connector | N/A |
| | Breakdown Voltage | < 75 V | N/A |
| | Insertion Loss | < 0.1 dB | N/A |
| | Surge Arrestor | Gas Tube | N/A |
| TEL/FAX/MODEM Protection | Jack type | RJ11/6P2C (1 in 2 out) | N/A |
| | Energy | 160J | N/A |
| Line Protection | | 1 Line | N/A |
| Surge Protected Indicator | | Red | N/A |
| Ground OK Indicator | | Green | N/A |
| Power OK Indicator | | N/A | N/A |
| Surge Circuit Shut Down | | Yes | N/A |
| Power Safety Shut Down (L-N) | | Yes | N/A |
| Accessories | | 6 ft. TEL cord + 6 ft. Coax. Cable | N/A |



Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>