



Perreaux

Model: PMF2000

Date of Manufacture: 1980

Product Type: Stereo Power Amplifier

Power Output (*per channel into 8Ω*): $200W_{\text{rms}}$

Specifications:

Power Output

200W_{rms} minimum per channel both channels driven into 8Ω from 20Hz to 20kHz at no more than 0.06% Total Harmonic Distortion from 0.25W to rated output.

Output per channel at onset of clipping at 1kHz

Both channels driven into 8Ω..... 200W_{rms}
Both channels driven into 4Ω..... 300W_{rms}

Dynamic Headroom 1.5dB

Frequency Response

Rated output 10Hz-100kHz ±0.1dB

Total Harmonic Distortion

175W_{rms} into 8Ω from 20Hz to 20kHz..... < 0.06%
190W_{rms} into 8Ω at 1kHz < 0.006%

Intermodulation Distortion (*S.M.P.T.E. method 60Hz and 7kHz mixed 4:1*)

2W to 20W into 8Ω < 0.005%
20W to rated output into 8Ω..... < 0.008%
Rated power..... Typically 0.005%

Slewing Rate..... 70V/μs

Transient Response 0.8μs

Phase Response +1° at 20Hz -1° at 20kHz

Hum and Noise..... 95dB below rated output 20Hz to 20kHz (100dB "A")

Damping Factor

10Hz-1kHz at 8Ω > 150

Input Impedance..... 10kΩ

Input Sensitivity

For rated output at 1kHz..... 1.5V_{rms}

Load Impedance

Rated for 8Ω usage but will safely drive any load from 4Ω up, including reactive loads such as full range electrostatic loudspeakers.

Dimensions

Width 483mm (19.0")

Height 133mm (5.3")

Depth 338mm (13.3")

Weight..... 15.5kg (34.2lb)

Schematic diagram

Product manual

info@perreaux.com

www.perreaux.com

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>