

## Clock Radio

- **Repeat Alarm**

Switches off the alarm for 9 minutes.

- **Wake Up to Radio or Buzzer**

Gives you the choice of waking up to your favourite radio station or alarm buzzer.

- **Alarm Reset**

Automatically resets the alarm for the same time on the next day, so you don't have to keep manually resetting the alarm.

- **Easy Alarm/Time Set**

- **Slumber**

- **Battery Back-Up**

\* AJ3195 is a quartz-operated version which ensures the time stays correct whilst mains frequencies may fluctuate



**Standard product information****Clock/Alarm**

- Electronic clock
- Quartz-operated clock : AJ3195 /01, /14, /12\*
- Wake up by radio or buzzer
- Alarm : Single alarm (radio & buzzer),  
Slumber function, Repeat alarm (9 minutes)
- Time/alarm setting : Hours/minutes

**Tuner**

- FM/AM tuning
- Wavebands /04 : FM stereo/LW  
/00, /01, /05, /13, /19 : FM stereo/MW  
/14 : FM Stereo (Ext)/MW  
/11, /12\* : FM stereo/MW  
/10 : FM/AM
- Frequency ranges /14 : FM 87.5 - 108 MHz  
: FM 65 - 108 MHz  
: MW 525 - 1607 kHz  
: LW 148.5 - 284 kHz  
: AM 530 - 1710 kHz

**Amplifier**

- Max. output power (RMS)  
( $\pm 1$  dB ; D < 10%) : 80 m Watts

**Sound System**

- Loudspeaker : 64 mm (2.5")

**Display**

- Red LED : 0.6" (15 mm) digit height
- Clock indication : 24 hours  
/01, /10, /13, /11, /12\*, /19 : 12 hours with pm indication

**Power Supply**

- AC mains /01, /11, /19 : 120/230 V, 50/60 Hz (switchable)  
/00, /04, /05, /14 : 230 V, 50 Hz  
/12\* : 230 V, 50 Hz  
/13 : 220 V, 60 Hz
- Backup battery : 6F22, 9 V (not included)

**General**

- Material : Polystyrene
- Weight : 0.6 Kg
- Dimensions : 192 mm W x 52 mm H x 152 mm D
- Packaging dimensions : 235 mm W x 75 mm H x 176 mm D
- Packaging dimensions : 270 mm W x 75 mm H x 176 mm D  
(for /05, /10)
- Quantity /mastercarton : 4

\* /12 is SKD of /01 for India

**Product Highlights**• **FM/MW or FM/LW Tuner**

Gives you a wide selection of radio stations to choose from.

• **LED**

Fashionable, red backlit display.

• **Slumber**

Lets you enjoy up to 59 minutes of radio entertainment while going to sleep.

After the pre-set time the radio switches off automatically.

• **Battery Back-Up**

A 9-Volt battery (not included) ensures that clock and alarm settings are maintained in the event of a mains interrupt or failure. Should this happen the display will not illuminate but the alarm and clock settings remain active.

• **Radio On/Off Switch**

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>