



Description

Rotel's RSX-1560 receiver delivers top-of-the-line performance and all of the features you have come to expect from our premium brand. At 7 x 100 watts into 8 ohms, or 7 x 200 watts into 4 ohms, this advanced surround receiver can fill your family or media room with the most dynamic, pulse-pounding, sound effects. Yet, it is just as adept at providing all of the most delicate nuances from voice tracks and music. The RSX-1560 surround receiver features an audiophile quality Class D amplifier design, along with HDMI 1.3 connections and the ability to decode Dolby TrueHD, Dolby Digital Plus, dts-HD Master Audio and dts HD Hi-Resolution audio codecs. The RSX-1060 is a true theater command center and can also provide a multiroom audio solution with up to three additional audio zones throughout the home. All 15 series components are available in silver or black finishes.

**Note – all Rotel 15 series components may be rack mounted and remotely controlled via RS-232, IR, or 12 volt (depending on model) for complete stealth operation.*

Specifications

| | | | |
|---|--|---|-------------------------|
| Power Output all channels driven | 100 watts x 7/ch (20-20kHz, <0.03% THD, 8 ohms) 200 watts x 7/ch (20-20kHz, <0.03% THD, 4 ohms) | Signal / Noise Ratio (at 65 dBf) | 70 dBf |
| IM Distortion | <0.05% | Harmonic Distortion (at 65 dBf) | 0.03% |
| Analogue Bypass | 95 dB | Stereo Separation (1 kHz) | 45 dB |
| Digital Input | 92 dB | Output Level | 1 V |
| Input Sens. / Impedance | Line Level : 200 mV/100K ohms | Antenna Input | 75 ohms unbalanced |
| Contour (LF/HF) | +/- 6 dB at 50 Hz / 15 kHz | AM Tuner | |
| Preamp Output Levels | 1.0V / 1K ohm | Sensitivity | 500 uV/m |
| Decodable Digital Input Signal | Dolby Digital, Dolby Digital EX, Dolby Prologic IIx, DTS, DTS_ES, DTS96/24, LPCM (up to 192K), Dolby TrueHD and DTS HD Mster Audio | Signal to Noise Ratio | 40 dB |
| Video | | Output Level | 500 mV |
| Frequency Response | 3 Hz - 10 MHz, +/-3 dB (Composite, S-Video) 3 Hz - 100 MHz, +/- 3 dB (Component Video) | Antenna Input | Loop Antenna |
| S/N Ratio | 45 dB | Power Consumption (Rating) | 500 watts |
| Input Impedance | 75 ohm | Power Consumption (Idling) | 79 watts |
| Output Impedance | 75 ohm | Power Consumption (Standby) | 3 watts |
| Output Level | 1.0 Volt | Power Requirements USA | 120 volts, 60 Hz |
| FM Tuner | | Power Requirements CE | 230 volts, 50 Hz |
| Usable Sensitivity | 14.2 dBf | Dimensions (W x H x D) mm | 431 x 188 x 422 mm |
| | | Dimensions (W x H x D) in. | 17 x 7 3/8 x 16 5/8 in. |
| | | Weight (net) | 15.5 Kg / 38 lbs. |
| | | Front Panel Height | 4U / 177 mm / 7 in. |

www.rotel.com

The Rotel Co. Ltd.
10-10 Shinsen-Cho
Shibuya-Ku,
Tokyo 150, Japan

Rotel of America
54 Concord St.
N. Reading, MA 01864
USA
T +1 978 664 3820
F +1 978 664 4109

Rotel Europe
Dale Road
Worthing
West Sussex BN11 2BH, UK
T +44 (0) 1903 221 763
F +44 (0) 1903 221 525

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>