



APSX3024SW Estimated Runtime

Load in Watts

| Inverter | Battery Qty. | Battery Type (Total Amp Hours, Voltage) | 500W | 1000W | 1500W | 1750W | 2000W | 2250W | 2500W | 2750W | 3000W |
|------------|--------------|---|------|-------|-------|-------|-------|-------|-------|-------|-------|
| APSX3024SW | 2 | 12V 75AH* (or 75AH @ 24VDC total) | 142 | 63 | 38 | 32 | 28 | 24 | 21 | 19 | 17 |
| APSX3024SW | 4 | 12V 75AH* (or 150AH @ 24VDC total) | 316 | 147 | 91 | 77 | 67 | 59 | 52 | 47 | 42 |
| APSX3024SW | 6 | 12V 75AH* (or 225AH @ 24VDC total) | 493 | 236 | 149 | 126 | 111 | 97 | 87 | 78 | 71 |
| APSX3024SW | 8 | 12V 75AH* (or 300AH @ 24VDC total) | 669 | 326 | 209 | 178 | 156 | 137 | 123 | 110 | 101 |
| APSX3024SW | 10 | 12V 75AH* (or 375AH @ 24VDC total) | 844 | 418 | 269 | 230 | 202 | 178 | 160 | 144 | 132 |
| APSX3024SW | 12 | 12V 75AH* (or 450AH @ 24VDC total) | 1017 | 509 | 330 | 283 | 249 | 220 | 198 | 179 | 163 |
| APSX3024SW | 14 | 12V 75AH* (or 525AH @ 24VDC total) | 1188 | 600 | 392 | 337 | 297 | 263 | 237 | 214 | 196 |
| APSX3024SW | 16 | 12V 75AH* (or 600AH @ 24VDC total) | 1357 | 691 | 453 | 390 | 345 | 305 | 276 | 249 | 228 |
| APSX3024SW | 18 | 12V 75AH* (or 675AH @ 24VDC total) | 1524 | 781 | 515 | 444 | 393 | 348 | 315 | 285 | 261 |
| APSX3024SW | 20 | 12V 75AH* (or 750AH @ 24VDC total) | 1689 | 871 | 576 | 497 | 440 | 391 | 354 | 320 | 294 |
| APSX3024SW | 22 | 12V 75AH* (or 825AH @ 24VDC total) | 1852 | 960 | 637 | 551 | 488 | 434 | 393 | 356 | 327 |
| APSX3024SW | 24 | 12V 75AH* (or 900AH @ 24VDC total) | 2013 | 1049 | 698 | 604 | 536 | 477 | 432 | 392 | 360 |
| APSX3024SW | 26 | 12V 75AH* (or 975AH @ 24VDC total) | 2172 | 1137 | 759 | 657 | 584 | 520 | 472 | 428 | 393 |
| APSX3024SW | 28 | 12V 75AH* (or 1050AH @ 24VDC total) | 2329 | 1225 | 820 | 711 | 632 | 563 | 511 | 464 | 427 |
| APSX3024SW | 30 | 12V 75AH* (or 1125AH @ 24VDC total) | 2484 | 1312 | 880 | 764 | 679 | 606 | 550 | 499 | 460 |
| APSX3024SW | 32 | 12V 75AH* (or 1200AH @ 24VDC total) | 2637 | 1399 | 940 | 816 | 727 | 648 | 589 | 535 | 493 |

All runtime values are in minutes.

***IMPORTANT NOTES** - Battery set must be professionally configured to 24VDC. See manual.

Tripp Lite part number "98-121" is a single 12V 75AH sealed lead acid battery. All wiring and required fusing is user supplied.

All runtimes are based on non-inductive continuous loading. Runtime is subject to capacity degradation over time.

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>