



TRIPP LITE UPS SYSTEMS SOLUTION GUIDE AND RUNTIME CHART FOR CISCO

IDEAL FOR PROTECTING AND POWERING MISSION-CRITICAL CISCO EQUIPMENT



Questions? Contact:

David Inwood



New Business Development Manager

Tel +44 (0)1622 852827 david@simms.co.uk

Gary Crook - Account Manager

Tel: +44 (0)1622 852816 gary@simms.co.uk

Samuel Hartridge - Account Manager

Tel: +44 (0)1622 852813 samuel@simms.co.uk

Recommended UPS Systems

SmartPro® UPS

SmartOnline™ UPS

Cisco Device	Power Requirement	Estimated Runtime in Minutes*											
		SMX500RT1U	SMX1000RT2U	SMX1500XLR2U	SMX1500RXLRT2U + BP36V15-2U	SMX2200XLR2U	SMX2200RXLRT2U + BP48V60RT3U	SUIN10002TXL2Ua	SUIN1000RTXL2Ua+ BP24V28-2U	SUIN1500RTXL2Ua	SUIN1500RTXL2Ua+ BP48V24-2U	SUIN2200RTXL2Ua	SUIN2200RTXL2Ua+ BP48V60RT3U
Cisco 1841	50w	31	140	197	807	328	1894	136	516	191	838	220	1344
Cisco 2801	150w	8	46	72	289	113	756	45	218	72	350	91	626
Cisco 2801 with IP Phone Power	270w	3	23	37	153	58	423	22	121	37	195	49	367
Cisco 2811	170w	7	40	63	254	98	671	39	194	63	311	80	591
Cisco 2811 with IP Phone Power	370w	—	15	26	107	40	305	15	86	26	139	35	269
Cisco 2821	280w	3	22	36	146	55	407	21	116	36	187	47	354
Cisco 2821 with IP Phone Power	550w	—	8	16	66	24	197	9	53	16	89	22	178
Cisco 2851	280w	3	22	36	146	55	407	21	116	36	187	47	354
Cisco 2851 with IP Phone Power	730w	—	—	11	45	18	143	6	37	11	63	15	63
Cisco 3825	330w	—	18	30	122	46	344	17	98	30	157	38	302
Cisco 3825 with IP Phone Power	650w	—	7	13	53	20	163	7	43	13	73	18	148
Cisco 3845	440w	—	12	21	87	32	253	12	70	21	115	28	225
Cisco 3845 with IP Phone Power	720w	—	—	11	46	18	145	6	38	11	64	15	132
Cisco ASA 5505	96w	13	64	117	412	164	1038	60	297	102	477	125	821
Cisco ASA 5510	190w	6	35	56	226	87	603	34	174	56	279	72	511
Cisco ASA 5520	190w	6	35	56	226	87	603	34	174	56	279	72	511
Cisco ASA 5540	190w	6	35	56	226	87	603	34	174	56	279	72	511
Cisco ASA 5550	190w	6	35	56	226	87	603	34	174	56	279	72	511
Cisco ASA 5580	800w	—	—	9	40	17	129	4	33	10	56	14	117
Cisco Catalyst 2960-24LT-L	175w	6	36	64	240	93	637	35	184	59	295	76	537
Cisco Catalyst 2960-24PC-L	470w	—	11	19	80	30	235	11	65	19	106	26	210
Cisco Catalyst 2960-24TC-L	30w	54	211	381	1205	492	2672	153	686	269	1133	294	1722
Cisco Catalyst 2960-24TT-L	30w	54	211	381	1205	492	2672	153	686	269	1133	294	1722
Cisco Catalyst 2960-48TC-L	45w	34	144	267	872	355	2028	119	547	205	892	234	1416
Cisco Catalyst 2960-48TT-L	45w	34	144	267	872	355	2028	119	547	205	892	234	1416
Cisco Catalyst 2960-8TC-L	20w	71	247	475	1474	601	3184	180	793	319	1321	340	1955
Cisco Catalyst 2960G-24TC-L	75w	19	91	166	566	228	1383	81	389	138	628	165	1049
Cisco Catalyst 2960G-48TC-L	140w	9	47	85	309	121	802	45	231	76	371	97	660
Cisco Catalyst 2960G-8TC-L	30w	54	211	381	1205	492	2672	153	686	269	1133	294	1722
Cisco Catalyst 2960PD-8TT-L	11w	107	390	507	2211	902	4776	381	1190	477	726	187	1075

* Runtimes may vary due to load and battery condition. Tripp Lite follows a policy of continuous improvement. Specifications are subject to change without notice.

Questions? Contact: **simms**

David Inwood

New Business Development Manager

Tel +44 (0)1622 852827 david@simms.co.uk

Gary Crook - Account Manager

Tel: +44 (0)1622 852816 gary@simms.co.uk

Samuel Hartridge - Account Manager

Tel: +44 (0)1622 852813 samuel@simms.co.uk

Recommended UPS Systems

SmartPro® UPS

SmartOnline™ UPS

SmartPro® UPS	SmartOnline™ UPS
SMX500RT1U	SUINT10002TXL2Ua
SMX1000RT2U	SUINT1000RTXL2Ua+ BP24V28-2U
SMX1500XLR2U	SUINT1500RTXL2Ua
SMX1500XLR2U + BP36V15-2U	SUINT1500RTXL2Ua+ BP48V24-2U
SMX2200XLR2U	SUINT2200RTXL2Ua
SMX2200XLR2U + BP48V60RT3U	SUINT2200RTXL2Ua+ BP48V60RT3U

Cisco Device	Power Requirement	Estimated Runtime in Minutes*											
Cisco Catalyst 3560-24TS-S/E	45w	34	144	267	872	355	2028	119	547	205	892	234	1416
Cisco Catalyst 3560-48TS-S/E	65w	22	104	190	641	259	1546	91	431	155	697	183	1149
Cisco Catalyst 3560-8PC-S	204w	5	29	52	197	75	531	29	153	48	246	63	454
Cisco Catalyst 3560E-12D	300w	3	20	33	135	51	379	19	108	33	174	44	331
Cisco Catalyst 3560E-12SD	300w	3	20	33	135	51	379	19	108	33	174	44	331
Cisco Catalyst 3560E-24PD	750w	—	—	10	44	18	139	5	36	11	61	15	126
Cisco Catalyst 3560E-24TD	265w	4	22	39	156	59	431	23	123	38	198	50	374
Cisco Catalyst 3560E-48PD	750w	—	—	10	44	18	139	5	36	11	61	15	126
Cisco Catalyst 3560E-48PD-SF	1150w	—	—	—	—	9	81	—	—	6	36	8	75
Cisco Catalyst 3560E-48TD	265w	4	22	39	156	59	431	23	123	38	198	50	374
Cisco Catalyst Express 520-24LC	110w	12	65	99	395	157	1001	63	287	98	461	121	801
Cisco Catalyst Express 520-24PC	460w	—	11	20	82	30	241	11	66	20	109	27	215
Cisco Catalyst Express 520-24TT	30w	54	183	381	1205	192	2672	153	687	269	1133	293	1722
Cisco Catalyst Express 520G-24TC	45w	34	145	267	872	355	2028	119	547	205	892	234	1416
Cisco Secure ACS Engine	345w	—	17	29	116	43	328	17	93	28	150	37	289
Cisco UC520 – 8-user	190w	6	35	56	226	87	603	34	174	56	279	72	511
Cisco UC520 – 16-user	190w	6	35	56	226	87	603	34	174	56	279	72	511
Cisco UC520 – 24-user	200w	5	33	53	213	82	572	32	165	53	265	68	487
Cisco UC520 – 32-user	200w	5	33	53	213	82	572	32	165	53	265	68	487
Cisco UC520 – 48-user	200w	5	33	53	213	82	572	32	165	53	265	68	487
MCS-7815-I2	400W	—	14	23	97	36	280	12	79	23	127	32	249
MCS-7825-H2	450W	—	12	20	85	31	247	11	68	20	112	27	220
MCS-7825-I2	350W	—	17	28	114	42	323	16	92	28	148	37	285
MCS-7835-12	835W REDUNDANT P/S	—	—	9	38	15	122	—	—	9	53	13	111
MCS-7835-H2	1000W REDUNDANT P/S	—	—	7	29	11	97	—	—	7	42	10	92
WS-C3550G-24PS/WS-3750G-24PS	540W	—	9	16	67	25	201	9	54	16	91	22	181
WS-C3560-24PS/WS-C3750-24PS	485W/495W	—	10	18	77	28	225	10	61	18	102	25	201
WS-C3560-48PS/WS-C3750-48PS	530W/540W	—	9	16	67	25	201	9	54	16	91	22	181
WS-C3560G-48PS/WS-3750G-48PS	590W	—	8	14	60	22	182	8	49	14	82	20	165
WS-CE500-24PC	460W	—	11	20	82	30	241	11	66	20	109	27	215

* Runtimes may vary due to load and battery condition. Tripp Lite follows a policy of continuous improvement. Specifications are subject to change without notice.

A Tripp Lite SNMP/Web card (model: SNMPWEBCARD) is recommended with each UPS system for remote power management. A Tripp Lite 2-post rackmount kit (model: 2POSTRMKITWM) is also recommended for systems that are going to be installed in 2-post rackmount environments.



Tripp Lite's PowerAlert Software, version 12.5, has tested compatible with Cisco CallManager, versions 4.0 and 4.1, Cisco 7600 Series Routers, 7500 Series Routers and Catalyst 65XX Layer 3 Switch. Tripp Lite PowerAlert Software, version 12, has tested compatible with Cisco CallManager, versions 3.3(4)-MCS and 4.0(2)-MCS. Go to www.tripplite.com/logodisclaimer for details. Tripp Lite is a Cisco Technology Developer Partner in the Cisco Technology Developer Program. Cisco, Cisco Systems, the Cisco Systems logo, and the Cisco Square Bridge logo are registered trademarks or trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and certain other countries. SmartPro and SmartOnline are registered trademarks or trademarks of Tripp Lite.



Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>