

## Power Supply/Chargers

ST-1206-1.5A	1.5A continuous. 6/12VDC
ST-2406-2A	1.5A continuous. 6/12/24VDC
ST-2406-3A	2.5A continuous. 6/12/24VDC
ST-2406-5A	4.0A continuous. 6/12/24VDC
ST-2406-7A	7.0A continuous. 6/12/24VDC
ST-2406-10A	9.0A continuous. 6/12/24VDC

### Features:

- ▶ Convert low-voltage AC input power to low-voltage DC output power.
- ▶ Regulated and filtered output voltage.
- ▶ Short circuit protection.
- ▶ Thermal protection and compensation.
- ▶ Built-in backup battery charger.
- ▶ Switches automatically in case of power loss.
- ▶ Fused protection for battery charger.
- ▶ 2 LEDs to indicate AC power input and DC power output status.
- ▶ Compatible with lead acid or gel-type rechargeable battery.
- ▶ Reverse polarity protected.
- ▶ Includes foam tape and battery terminals for easy installation.



ST-1206-1.5A



ST-2406-2A



ST-2406-3A



ST-2406-5A



ST-2406-7A



ST-2406-10A

### Specifications:

Modelo #	Voltaje DC	Corriente (continua)	Corriente (max)	Maximum Charge Corriente	Tamaño+
ST-1206-1.5A	6/12	1.5A	2.0A	6V =200mA, 12V = 400mA	2-7/8" x 2-1/4" x 1" (73 x 57 x 25 mm)
ST-2406-2A	6/12/24	1.5A	3.0A	6V =180mA, 12V = 350mA, 24v = 700mA	2-7/8" x 2-1/2" x 1-3/8" (73 x 64 x 35 mm)
ST-2406-3A	6/12/24	2.5A	3.0A	6V =180mA, 12V = 350mA, 24v = 700mA	3-3/8" x 2-7/8" x 1-5/16" (81x 73 x 33 mm)
ST-2406-5A	6/12/24	4.0A	5.0A	6V =180mA, 12V = 350mA, 24v = 700mA	3-3/4" x 2-7/8" x 1-9/16" (95 x 73 x 40 mm)
ST-2406-7A	6/12/24	7.0A	7.5A	6V =180mA, 12V = 350mA, 24v = 700mA	5-1/2" x 5-1/8" x 2-11/64" (140 x 130 x 55 mm)
ST-2406-10A	6/12/24	9.0A	10.0A	6V =180mA, 12V = 350mA, 24v = 700mA	5-1/2" x 5-1/10" x 2" (140 x 130 x 51 mm)

SECO-LARM carries a full-line of Open-Frame Transformers that compliment the ST-2406 Series Power Supply/Chargers. To find the transformer for a specific application, please refer to the chart below:

### Transformer Selection Table:

Output voltage	ST-1206-1.5AQ	ST-2406-2AQ	ST-2406-3AQ	ST-2406-5AQ	ST-2406-7AQ	ST-2406-10AQ
6VDC	12VAC/20VA	12VAC/20VA	ST-UV24-W50Q 24VAC/50VA	ST-UV16-W100Q 16VAC/100VA	ST-UVDA-W180Q 24-28VAC/180VA	ST-UV16-W100Q 16VAC/100VA
12VDC	16VAC/40VA	16VAC/40VA	ST-UVDA-W100Q 24-28VAC/100VA	ST-UV-W100Q 16VAC/100VA	ST-UVDA-W180Q 24-28VAC/180VA	ST-UVDA-W180Q 24-28VAC/180VA
24VDC	N/A	ST-UV24-W50Q 24VAC/50VA	ST-UVDA-W100Q 24-28VAC/100VA	ST-UVDA-W180Q 24-28VAC/180VA	24-28VAC/210VA	ST-UV28-T350Q 28VAC/350VA

## Open-Frame Transformers

ST-UV24-W50Q	<i>24VAC/50W</i>
ST-UV16-W100Q	<i>16VAC/100W</i>
ST-UVDA-W100Q	<i>24/28VAC/100W</i>
ST-UVDA-W180Q	<i>24/28VAC/180W</i>
ST-UV28-T350Q	<i>28VAC/350W</i>

### Features:

- ▶ Shielded windings to reduce electromagnetic interference (EMI).
- ▶ Selectable input voltage
- ▶ Selectable output voltage on some models.
- ▶ T350Q is a torodial-type transformer



### Specifications:

Model	Output voltage	Amperage	VA	Input Voltage
ST-UV24-W50Q	24VAC	2.1	50VA	120VAC or 240VAC 50/60Hz
ST-UV16-W100Q	16VAC	6.3	100VA	120VAC or 240VAC 50/60Hz
ST-UDVA-W100Q	24VAC	4.2	100VA	120VAC or 240VAC 50/60Hz
	28VAC	3.6	100VA	120VAC or 240VAC 50/60Hz
ST-UVDA-W180Q	24VAC	7.5	180VA	120VAC or 240VAC 50/60Hz
	28VAC	6.4	180VA	120VAC or 240VAC 50/60Hz
ST-UV28-T350Q	28VAC	12.5	350VA	120VAC or 240VAC 50/60Hz

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>