# **Operation Guide 3130**

# CASIO


### **About This Manual**



- Button operations are indicated using the letters shown
- in the illustration.

  Each section of this manual provides you with the information you need to perform operations in each

### **General Guide**



# Timekeeping



Use the Timekeeping Mode to view the current time and

date.Day of the week is displayed as follows.

SU: Sunday MO : Monday TU : Tuesday TH : Thursday SA : Saturday WE : Wednesday FR : Friday

To toggle between 12-hour and 24-hour timekeeping In the Timekeeping Mode, press © to switch between the 12-hour and 24-hour formats.

- 12-hour and 24-hour formats.
  With the 12-hour format, the PM indicator (P) appears for times in the range of noon to 11:59 p.m. and no indicator appears for times in the range of midnight to 11:59 a.m.
  With the 24-hour format, times are displayed in the range of 0:00 to 23:59, with 24H indicator.


### **Backlight Precautions**

- The backlight uses an EL (electro-luminescent) panel that causes the entire display to glow for easy reading in the dark. In any mode, press (a) to illuminate the display.

   The electro-luminescent panel that provides illumination loses power after very long
- use.

  The illumination provided by the backlight may be hard to see when viewed under
- The match may emit an audible sound whenever the display is illuminated. This is due to vibration of the EL panel used for illumination, and does not indicate
- Frequent use of the backlight shortens the battery life.

## Alarm




When the Daily Alarm is turned on, the alarm sounds for 20 seconds at the preset time each day. When the Hourly Time Signal is turned on, the watch beeps every hour on

All of the operations in this section are performed in the Alarm Mode, which you enter by pressing (B).

- 1. Hold down (A) while in the Alarm Mode until the hour digits start to flash on the display. The hour digits flash because they are selected.

  This operation automatically turns on the alarm.

2. Press (A) to change the selection in the following sequence Pressing (A) also illuminates the display.



- 3. Press © to increase the selected digits. Holding down © changes the number at
  - high speed.
     The format (12-hour and 24-hour) of the alarm time matches the format you select
- The format (12-hour and 24-hour) of the alarm time matches the format you series for normal timekeeping.


  When setting the alarm time using the 12-hour format, take care to set the time correctly as morning or afternoon (P).

  After you set the alarm time, press (A) to return to the Alarm Mode.

  If you do not operate any button for a few minutes while a selection is flashing, the flashing stops and the watch goes back to the Timekeeping Mode automatically.

To stop the alarm
Press (A) to stop the alarm after it starts to sound.

To switch the Daily Alarm and Hourly Time Signal on and off Press © while in the Alarm Mode to change the status of the Daily Alarm and Hourly Time Signal in the following sequence.



# To test the alarm

Hold down © while in the Alarm Mode to sound the alarm.

# Stopwatch



The Stopwatch Mode lets you measure elapsed time, split times, and two finishes. The range of the stopwatch is 59 minutes, 59.99 seconds.

The stopwatch continues to run, restarting from zero after it reaches its limit, until you stop it.

The stopwatch measurement operation continues even if you exit the Stopwatch Mode.

Fitting the Stopwatch Mode.

- If you exit the Stopwatch Mode.

  Exiting the Stopwatch Mode while a split time is frozen on the display clears the split time and returns to elapsed time measurement.


  All of the operations in this section are performed in the Stopwatch Mode, which you enter by pressing (a).

### 1/100 s To measure times with the stopwatch



. Pressing (A) also illuminates the display.

# Time Setting



- 3. While the second's digits are selected (flashing), press © to reset the seconds to \$\mathbb{III}\$. If you press © while the second's count is in the range of 30 to 59, the seconds are reset to \$\mathbb{III}\$ and 1 is added to the minutes. If the second's count is in the range of 00 to 29, the minute's count is unchanged.

  4. While any other digits (besides seconds) are selected (flashing), press © to increase the number. While the day of the week is selected, pressing © advances to the next day. Holding down © changes the current selection at high speed.

  5. After you set the time and date, press ® to return to the Timekeeping Mode.

  If you do not operate any button for a few minutes while a selection is flashing, the flashing stops and the watch goes back to the Timekeeping Mode automatically.

Free Manuals Download Website

http://myh66.com

http://usermanuals.us

http://www.somanuals.com

http://www.4manuals.cc

http://www.manual-lib.com

http://www.404manual.com

http://www.luxmanual.com

http://aubethermostatmanual.com

Golf course search by state

http://golfingnear.com

Email search by domain

http://emailbydomain.com

Auto manuals search

http://auto.somanuals.com

TV manuals search

http://tv.somanuals.com