

# ATTIX 30 H / M / PC / XC ATTIX 50 H / M / PC / XC

### **Operating Instructions**







### **Contents**

| 1 | Important safety instructions |       |                                                           | 2  |
|---|-------------------------------|-------|-----------------------------------------------------------|----|
| 2 | Description                   | 2.1   | Operating elements                                        | 7  |
|   | ·                             | 2.2   | Operating panel                                           | 8  |
| 3 | Before starting the           | 3.1   | Assembling the vacuum cleaner                             | 9  |
|   | cleaner                       | 3.1.1 | Taking accessories out of the packaging *)                | 9  |
|   |                               |       | Attaching the suction pipe holder to the suction pipe *). |    |
|   |                               | 3.2   | Before starting the cleaner                               |    |
|   |                               | 3.3   | Insert the safety filter bag "H"                          |    |
|   |                               | 3.4   | Inserting the filter bag "M"                              |    |
| 4 | Control / Operation           | 4.1   | Connections                                               | 13 |
|   |                               | 4.1.1 | Connecting the suction hose                               | 13 |
|   |                               |       | Electrical connection                                     |    |
|   |                               | 4.2   | Switching on the vacuum cleaner                           |    |
|   |                               | 4.2.1 | Switch " 0-I " *)                                         |    |
|   |                               |       | Switch " auto-0-I " *)                                    |    |
|   |                               | 4.2.3 | Suction power control *)                                  | 14 |
|   |                               |       | Auto-On/Off-Operation - "auto" switch position *)         |    |
|   |                               | 4.3   | Cleaning the filter element                               | 15 |
|   |                               | 4.3.1 | Cleaning the filter element " Push&Clean System "         |    |
|   |                               |       | (ATTIX 30- / 50-xx PC)                                    | 15 |
|   |                               | 4.3.2 | Cleaning the filter element " XtremeClean "               |    |
|   |                               |       | (ATTIX 30- / 50-xx XC)                                    |    |
|   |                               |       | Check the volume flow monitor                             |    |
|   |                               | 4.3.4 | Acoustic warning                                          | 15 |
| 5 | Applications and              | 5.1   | Techniques                                                | 16 |
|   | methods                       | 5.1.1 | Picking up dry substances                                 | 16 |
|   |                               | 5.1.2 | Picking up liquids                                        | 16 |
| 6 | After using the cleaner       | 6.1   | Switching the vacuum cleaner off and storage              | 17 |
| 7 | Maintenance                   | 7.1   | Maintenance plan                                          | 18 |
|   |                               | 7.2   | Maintenance work                                          |    |
|   |                               |       | Emptying the dirt tank                                    |    |
|   |                               |       | Replacing the safety filter bag "H"                       |    |
|   |                               |       | Replacing the filter bag "M"                              |    |
|   |                               |       | Replacing the disposal bag "M"                            |    |
|   |                               |       | Replacing filter element "H" (Push & Clean System)        |    |
|   |                               |       | Replacing filter element "H" (Xtreme Clean System)        |    |
|   |                               |       | Replacing filter element "M" (Push & Clean System)        |    |
|   |                               | 7.2.8 | Replacing filter element "M" (XtremeClean System)         | 25 |
| 8 | Troubleshooting               |       |                                                           | 26 |
| 9 | Further information           | 9.1   | Recycling the cleaner                                     | 27 |
|   |                               | 9.2   | Guarantee                                                 |    |
|   |                               | 9.3   | Tests and approvals                                       |    |
|   |                               | 9.4   | EC declaration of conformity                              |    |
|   |                               | 9.5   | Technical data                                            |    |
|   |                               | 9.6   | Optional accessories                                      | 28 |

enalish

### 1 Important safety instructions

### Symbols used to mark instructions



Prior to using the appliance for the first time, be sure to read this document through and keep it ready to hand.



#### **DANGER**

Danger that leads directly to serious or irreversible injuries, or even death.



#### **WARNING**

Danger that can lead to serious injuries or even death.



#### **CAUTION**

Danger that can lead to minor injuries and damage.

#### The appliance must

- only be used by persons, who have been instructed in its correct usage and explicitly commissioned with the task of operating it
- only be operated under supervision
- not be used by children
- not be used by mentally or physically disabled persons

Before starting work, the operating staff must be informed on and trained within:

- · use of the vacuum cleaner
- risks associated with the material to be picked up
- safe disposal of the picked up material
- 1. Do not use any unsafe work techniques.
- 2. Never use the vacuum cleaner without a filter.
- 3. Switch off the appliance and disconnect the mains plug in the following situations:
  - Prior to cleaning and servicing
  - Prior to replacing components
  - Prior to changing over the appliance
  - If foam develops or liquid emerges

Besides the operating instructions and the binding accident prevention regulations valid in the country of use, observe recognised regulations for safety and proper use.

#### Purpose and intended use

Since 1997, there is a new division of hazardous dusts and their assigned vacuum machines. These are regulated by IEC 60335-2-69 (world wide) and by EN 60335-2-69 (European wide).

The safety label on the machine warns:

This appliance contains dust hazardous to health. Emptying and maintenance operations, including removal of the dust collecting means, must only be carried out by authorised personnel wearing suitable personal protection. Operate only after the full filtration system has been fitted and checked.

H

Dust Class H (high). The dusts which belong to this class are: dusts with OEL values<sup>1)</sup>, all carcinogenic dusts and dusts which are mixed with pathogenic agents. Vacuums for Dust

Class H are tested in their entirety and have a maximum degree of permeability of 0.005%. The disposal must be dust free.

M

Dust Class M (medium). The dusts which belong to this class are: dusts with OEL values<sup>1)</sup>  $\geq$  0.1 mg/m³ as well as saw dust. The machine is tested in its entirety by vacuums for this dust

class. The maximum degree of permeability is 0.1% and the disposal must be low dust.

The air flow in Safety Vacuum systems has to be strictly controlled to achieve a minimum flow rate of  $V_{min} = 20$  m/s in the suction hose.

The vacuum cleaners ATTIX 30-XH and ATTIX 50-XH are suitable to pick up

 dry, nonflammable dust, non flammable liquids, hazadous dusts with OEL values, carcinogenic dusts, dusts containing germs

The vacuum cleaners ATTIX 30-XH PC e ATTIX 50-XH PC are also approved for asbestos abatement (TRGS 519).

The vacuum cleaners ATTIX 30-XM and ATTIX 50-XM are suitable to pick up

 dry, nonflammable dust, non flammable liquids, sawdust and hazadous dusts with OEL values ≥ 0.1 mg/m³

The vacuum cleaners are suitable for commercial use, such as e.g. in

Hotels, Schools, Hospitals, Factories, Shops, Offices, Hire shops

Any other use is considered as improper use. The manufacturer accepts no liability for any damage resulting for such use. The risk for such use is borne solely by the user.

Proper use also includes proper operation, servicing and repairs as specified by the manufacturer.

#### **Transport**

- 1. Before transporting the dirt tank, close all the locks.
- 2. Do not tilt the cleaner if there is liquid in the dirt tank.
- 3. Do not use a crane hook to lift the cleaner.

#### **Storage**

1. Store the appliance in a dry place, protected from frost.

#### **Electrical connection**

- 1. It is recommended that the vacuum cleaner should be connected via a residual current circuit breaker.
- 2. Arrange the electrical parts (sockets, plugs and couplings) and lay down the extension lead so that the protection class is maintained
- 3. Connectors and couplings of power supply cords and extension leads must be watertight.

#### **Extension lead**

- 1. As an extension lead, only use the version specified by the manufacturer or one of a higher quality. See operating instructions.
- 2. When using an extension lead, check the minimum cross-sections of the cable:

| Cable length | Cross section       |                     |
|--------------|---------------------|---------------------|
|              | < 16 A              | < 25 A              |
| up to 20 m   | 1.5 mm <sup>2</sup> | 2.5 mm <sup>2</sup> |
| 20 to 50 m   | 2.5 mm <sup>2</sup> | 4.0 mm <sup>2</sup> |

### Maintenance, cleaning and repair

During the following work, ensure that dust is not unnecessarily spread around. Wear a P2 bresthing mask.

CAUTION: In the case of asbestos abatement wear additional single-use clothing.

Clean the water level limiting device regularly and check for signs of damage.

Only carry out maintenance work described in the operating instructions.

Always pull the out the mains plug before cleaning and maintenance of the vacuum cleaner.

During maintenance and cleaning, handle the vacuum cleaner in such a manner that there is no danger for maintenance staff or other persons.

In the maintenance area

- 1. Use filtered compulsory ventilation
- 2. Wear protective clothing
- 3. Clean the maintenance area so that no harmful substances get into the surroundings.

Before removing the vacuum cleaner from the area contaminated with harmful substances:

- 1. Clean the outside of the vacuum cleaner, wipe it clean or pack the vacuum cleaner in well sealed packaging
- 2. and avoid spreading deposited harmful dust.

After use, in asbestos contaminated areas, the machine must be cleaned by an authorised person according to TGRS 519.

During maintenance and repair work all contaminated parts that could not be cleaned satisfactorily must be:

- 1. packed in well sealed bags
- 2. disposed of in a manner that complies with valid regulations for such waste removal.

At least once a year, a Nilfisk-ALTO technician or an instructed person must perform a technical inspection including filters, air tightness and control mechanisms. According to AA.22.201.2 appliances in class H must have their filtration efficiency checked once a year. If the effiency of the filter does not fulfil the requirements for dust class H, the filter must be replaced, and the new filter must be tested according to AA.22.201.2.

### **Risks**

#### **Electrical components**



#### **DANGER**

Electric shock due to faulty mains connecting lead.

Touching a faulty mains connecting lead can result in serious or even fatal injuries.

- 1. Do not damage the mains power lead (e.g. by driving over it, pulling or crushing it).
- 2. Regularly check whether the power cord is damaged or shows signs of ageing.
- Have the faulty mains connecting lead replaced by your Nilfisk-Alto service representative or a qualified electrician prior to using the appliance again.



#### **DANGER**

The upper section of the vacuum cleaner contains live components.

Contact with live components leads to serious or even fatal injuries.

1. Never spray water on to the upper section of the vacuum cleaner.



#### **CAUTION**

Appliance socket\*).

The appliance socket is only designed for the purposes defined in the operating instructions. The connection of different appliances can result in damage.

- 1. Prior to plugging in an appliance, always switch off the vacuum cleaner and the appliance that is to be connected.
- 2. Read the operating instructions to the appliance to be connected and observe the safety notes contained in these.



#### **CAUTION**

Damage due to unsuitable mains voltage.

The appliance can be damaged as a result of being connected to an unsuitable mains voltage.

1. Ensure that the voltage shown on the rating plate corresponds to the voltage of the local mains power supply.

#### Picking up liquids



#### **CAUTION**

Picking up liquids.

Do not pick up flammable liquids.

- Before liquids are picked up, always remove the filter bag/ waste bag and check that the float ") or the water level limit ") works properly.
- 2. The use of a separate filter element or filter screen is recommended.
- 3. If foam appears, stop work immediately and empty the tank.

<sup>\*)</sup> Optional accessories / Option depending on model

english Hazardous materials



#### WARNING

Hazardous materials.

Vacuuming up hazardous materials can lead to serious or even fatal injuries

- The following materials must not be picked up by the vacuum cleaner:
  - hot materials (burning cigarettes, hot ash, etc.)
  - flammable, explosive, aggressive liquids (e.g. petrol, solvents, acids, alkalis, etc.)
  - flammable, explosive dust (e.g. magnesium or aluminium dust, etc.)

Using the vacuum cleaner for asbestos abatement work



#### **WARNING**

To pick up materials containing asbestos:

- 1. ATTIX 30-XH and ATTIX 50-XH can be used for picking up asbestos.
- 2. Use a suction hose with a diameter of 36 mm.

Use the closable plastic sack to ensure dust-free transport of the vacuum cleaner and contaminated parts (hose, hand pipe, nozzles, etc.). Once the asbestos vacuum cleaner has been used in an exclusion area as defined in TRGS 519, it should no longer be used in so-called "white" areas. Exceptions are only permitted if the asbestos cleaner has previously been completely decontaminated by a specialist as specified in TRGS 519 No. 2.7 (e.g. not only the outer case but also, for example, the cooling air rooms, the installation rooms for electrical supplies, the supplies themselves, etc.). A written report must be made by a specialist and signed by him.

When picking up materials containing asbestos the exhaust air must not be returned into the room. Use the exhaust air socket and a hose with a length of maximum 4 m and a nominal diameter of minimum 50 mm.

#### Spare parts and accessories



#### CAUTION

Spare parts and accessories.

The use of non-genuine spare parts and accessories can impair the safety of the appliance.

- 1. Only use spare parts and accessories from Nilfisk-Alto.
- 2. Use only the brushes supplied with the vacuum cleaner or specified in the operating manual.

#### **Emptying dirt tank**



#### **CAUTION**

Picking up environmentally hazardous materials.


Materials picked up can present a hazard to the environment.

1. Dispose of the dirt in accordance with legal regulations.

## 2 Description


#### 2.1 Operating elements


- 1 Handle with receptacle for electrical lead
- 2 Fixing point for suction pipe holder
- 3 Retaining clamp
- 4 Castor
- 5 Dirt tank
- 6 Inlet fitting
- 7 Applicance switch
- 8 Hose diameter setting
- 9 Appliance socket \*)
- 10 Operating knob for filter cleaning \*)



<sup>\*)</sup> Optional accessories / Option depending on model


#### 2.2 Operating panel





### 3 Before starting the cleaner

- 3.1 Assembling the vacuum cleaner
- 3.1.1 Taking accessories out of the packaging ')



3.1.2 Attaching the suction pipe holder to the suction pipe ')



- Take vacuum cleaner and accessories out of the packaging.
- The mains plug should not yet be inserted into a socket
- Open the retaining clamps

   (A) and remove the upper section of the vacuum cleaner.
- Take the accessories \*) out of the dirt tank and the packaging.
- 1. Attach the suction pipe holder to the suction pipe.

### 3.2 Before starting the cleaner

Depending on how hazardous the dust is, the cleaner must be fitted with appropriate fiters.

| with appropriate mers.                                                                                                                   |        |                                                                                                                                       |  |
|------------------------------------------------------------------------------------------------------------------------------------------|--------|---------------------------------------------------------------------------------------------------------------------------------------|--|
| H                                                                                                                                        |        |                                                                                                                                       |  |
| Type of dust                                                                                                                             | Filter | bag/waste bag/filter element                                                                                                          |  |
| Dusts with OEL values¹) (observe any additional national regulations)     Carcinogenic dusts     Dust with pathogenic agents             |        | Recommended for safe dust<br>free disposal: Safety filter<br>bag "H"<br>Order No.<br>ATTIX 30-XH: 107400233<br>ATTIX 50-XH: 107400236 |  |
| Dusts with OEL values <sup>1)</sup> (observe any additional national regulations)     Carcinogenic dusts     Dust with pathogenic agents |        | Filter bag<br>Order No.<br>ATTIX 30-XH: 302004000<br>ATTIX 50-XH: 302004004                                                           |  |
| Dusts with OEL values <sup>1)</sup> (observe any additional national regulations)     Carcinogenic dusts                                 |        | Filter element "H"<br>Order No.<br>302000658                                                                                          |  |
| Dust with pathogenic agents                                                                                                              |        | Flat filter element "H"<br>Order No.<br>107400449                                                                                     |  |

<sup>\*)</sup> Optional accessories / Option depending on model


| M                                                                                                                  |        |                                                                                     |  |
|--------------------------------------------------------------------------------------------------------------------|--------|-------------------------------------------------------------------------------------|--|
| Type of dust                                                                                                       | Filter | bag/waste bag/filter element                                                        |  |
| Dusts with OEL values ≥0.1 mg/m³ (observe any additional national regulations)     Wood dusts & concrete dusts     |        | Waste bag (5 pcs.)<br>Order No.<br>ATTIX 30-XM: 302000804<br>ATTIX 50-XM: 302000728 |  |
| Dusts with OEL values<br>≥0.1 mg/m³ (observe any additional national regulations)     Wood dusts & concrete dusts  |        | Filter bag<br>Order No.<br>ATTIX 30-XM: 302004000<br>ATTIX 50-XM: 302004004         |  |
| Dusts with OEL values     ≥0.1 mg/m³ (observe any additional national regulations)     Wood dusts & concrete dusts |        | Filter element "M" PC:<br>Order No.<br>302000490                                    |  |
| Wood dusts a concrete dusts                                                                                        |        | Flat filter element "M" XC:<br>Order No.<br>302002842                               |  |

Before picking up dust with occupational exposure limit values:


- 1. Check that all the filters are present and properly fitted
- 2. The hose diameter and the setting for the suction hose diameter must be the same.
- 3. When the motor is running, hold the suction hose shut. For safety reasons, an acoustic warning sounds if the air speed in the suction hose drops to below 20 m/s.

### 3.3 Insert the safety filter bag "H"






- 1. The mains plug should not yet be inserted into a socket.
- Open the retaining clamps (A) and remove the upper section of the vacuum cleaner.




- 3. Insert the safety filer bag into the dirt tank.
- 4. Press the safety bag connection firmly into the inlet fitting.
- Check that the ventilation holes (B) remain inside the dirt tank.
- Fold the top edge of the disposal bag over the rim of the dirt tank.



- 7. Attach the upper section of the vacuum cleaner.
- 8. Close the retaining clamps (A). Ensure that the retaining clamps fit properly.


### 3.4 Inserting the filter bag "M"






- 1. The mains plug should not yet be inserted into a socket.
- Open the retaining clamps


   (A) and remove the upper section of the vacuum cleaner.



3. Insert the filter bag into the dirt tank.



4. Press the filter bag connection firmly on to the inlet fitting.




- 5. Attach the upper section of the vacuum cleaner.
- 6. Close the retaining clamps (A). Ensure that the retaining clamps fit properly.

### 4 Control / Operation

#### 4.1 Connections


### 4.1.1 Connecting the suction hose



1. Connect the suction hose.

#### 4.1.2 Electrical connection

The operating voltage shown on the rating plate must correspond to the voltage of the mains power supply.




- 1. Ensure that the cleaner is switched off.
- Insert the power cord into a properly installed and fused socket with earthing contact.

### 4.2 Switching on the vacuum cleaner

4.2.1 Switch " 0-I " \*)

The hose diameter and the setting for suction hose diameter must be the same.

| ø27 | ø27 |
|-----|-----|
| ø32 | ø32 |
| ø36 | ø36 |
| ø38 | ø38 |




| Switch position | Function |
|-----------------|----------|
| 0               | Off      |
| I               | On       |

#### 4.2.2 Switch " auto-0-I " \*)

The hose diameter and the setting for the suction hose diameter must be the same.


| ø27 | ø27 |
|-----|-----|
| ø32 | ø32 |
| ø36 | ø36 |
| ø38 | ø38 |



| Switch position | Function            |
|-----------------|---------------------|
| 0               | Off                 |
| auto            | Auto On/Off         |
| I               | On / manual<br>mode |

<sup>\*)</sup> Optional accessories / Option depending on model

english 4.2.3 Suction power control \*)



| Switch position | Function                                                                                                      |
|-----------------|---------------------------------------------------------------------------------------------------------------|
|                 | The suction power control switch allows precise adaptation of the suction power for different cleaning tasks. |


### 4.2.4 Auto-On/Off-Operation - "auto" switch position \*)

The vacuum cleaner is switched on and off by the power tool connected. Dirt is picked up from the source of dust immediately.


To comply with regulations, only approved dust producing tools should be connected.

The maximum power consumption of the connected electrical appliance is stated in section "Technical data".


Before switching the switch to position "auto", ensure that the tool connected to the appliance socket is switched off



- 1. Switch off the vacuum cleaner.
- 2. Switch off the power tool.



- 3. Connect the power tool and the vacuum cleaner with a suction hose.
- Insert the plug of the power tool into the tool socket on the operating panel of the vacuum cleaner.



- 5. Switch on the vacuum cleaner. Switch in "auto" position.
- 6. Switch on the power tool. The vacuum cleaner motor starts when the connected power tool is switched on.

When the power tool is switched off, the vacuum cleaner continues to run for a short moment so that any dust in the suction hose is conveyed to the filter bag.

enalish

- 4.3 Cleaning the filter element
- 4.3.1 Cleaning the filter element " Push&Clean System " (ATTIX 30- / 50-xx PC)

Only for vacuum cleaning without a filter bag and without a cloth insert filter.



If suction performance drops:

- 1. Turn switch to position "I" (maximum suction power).
- 2. Close the nozzles or suction hose opening with the palm of your hand.
- 3. Press the button to start filter

cleaning three times. The resulting stream of air removes attached dust from the slats of the filter elements.

# 4.3.2 Cleaning the filter element " XtremeClean " (ATTIX 30- / 50-xx XC)

Only for vacuum cleaning without a cloth insert filter.

After picking up harmless dust using the waste bag.



To ensure that suction performance is always at its best, the filter element is automatically cleaned during operation. We recommend complete cleaning if the filter element becomes extremely dirty.

- Switch off the vacuum cleaner
- 2. Close the nozzles or suction hose opening with the palm of your hand.
- Turn the switch to position "I" and let the cleaner operate for approx. 10 seconds with the suction hose opening closed.

### 4.3.3 Check the volume flow monitor

Before picking up dust with maximum room concentration values:

- 1. Check that all the filters are present and properly fitted.
- When the motor is running, hold the suction hose shut. An acoustic warning sounds after approx. 1 second.

#### 4.3.4 Acoustic warning

For safety reasons, an acoustic warning sounds if the air speed in the suction hose drops to below 20 m/s. See section "Troubleshooting"

### 5 Applications and techniques

#### 5.1 Techniques

If used correctly, additional accessories, suction nozzles and suction hoses can enhance the cleaning action and reduce the cleaning effort.

Effective cleaning is achieved if you follow just a few guidelines in combination with your own practical experience in special fields.

Here are some basic tips.

### 5.1.1 Picking up dry substances

#### **CAUTION!**

Do not pick up flammable substances.

There must always be a safety filter bag in the tank before dry substances with maximum room concentration values are picked up. See section "Accessories" for ordering number.

To pick up harmless dust we resommend the use of a waste bag. See section "Accessories" for ordering number. Disposal of the picked up material is then simple and hygenic.

After picking up liquidsm the filter element is wet. A damp filter element clogs more quickly when dry substances are picked up. For this reason the filter element should be washed and dried or replaced by a dry element before dry substances are picked up.

#### 5.1.2 Picking up liquids

#### **CAUTION!**

Do not pick up flammable liquids.

Before liquids are picked up, always remove the filter bag/disposal bag.


The use of a seperate filter element or filter screen is recommended.


If foam appears, stop work immediately and empty the tank.


To reduce the amount of foam, use foam killer Nilfisk-ALTO Foam Stop (see section "Accessories" for order number).

### 6 After finishing work

### 6.1 Switching the vacuum cleaner off and storage







- After picking up hazardous dust, vacuum clean the outside of the cleaner.
- Switch off the cleaner and pull the mains plug out of the socket.
- 3. Remove the suction hose form the vacuum cleaner and close the inlet fitting (A) with the plug (B).
- 4. Wind up the power cord onto the handle (C). Begin winding up the cord at the cleaner end and not the plug end to prevent the power cord from tangling up.
- 5. Empty the dirt tank and clean the vacuum cleaner.
- After picking up liquids: Store the upper section of the vacuum cleaner separately so that the filter element can dry.
- Hang the suction hose with the floor nozzle (D) in the brackets and pack the accessories (E) away.
- 8. Store the cleaner in a dry room where it is protected from unauthorized use.

### 7 Maintenance

#### 7.1 Maintenance plan


|       |                                               | After finishing work | When required |
|-------|-----------------------------------------------|----------------------|---------------|
| 7.2.1 | Emptying dirt tank                            | •                    |               |
| 7.2.2 | Replacing the safety filter bag "H"           |                      | •             |
| 7.2.3 | Replacing the filter bag "M"                  |                      | •             |
| 7.2.4 | Replacing the disposal bag "M"                |                      | •             |
| 7.2.5 | 2.5 Replacing filter element "H" (Push&Clean) |                      | •             |
| 7.2.6 | 6 Replacing filter element "H" (XtremeClean)  |                      | •             |
| 7.2.7 | Replacing filter element "M" (Push&Clean)     |                      | •             |
| 7.2.8 | Replacing filter element "M" (XtremeClean)    |                      | •             |

### 7.2 Maintenance work7.2.1 Emptying the dirt tank


After emptying the tank: clean the rim of the tank and the seals in the intermediate ring and the upper section of cleaner before refitting them

If the seal or groove is dirty or damaged, the suction performance will be reduced.


Before reinserting the suction hose: clean the inlet fitting and hose collar.



- 1. Switch off the vacuum cleaner and pull the mains plug out of the socket.
- 2. Open the retaining clamps (A) and remove the upper section of the vacuum cleaner.



- 4. Tip out the collected dirt.
- 5. Dispose of the dirt in accordance with legal regulations.



- 6. Attach the upper section of the vacuum cleaner.
- 7. Close the retaining clamps (A). Ensure that the retaining clamps fit properly.


### 7.2.2 Replacing the safety filter bag "H"



During the following work, ensure that dust is not unnecessarily spread around, Wear a P2 breathing mask.

CAUTION! In the case of asbestos abatement wear additional single-use clothing.


Never use the vacuum cleaner without a filter.



Open the retaining clamps


 (A) and remove the upper section of the vacuum cleaner.

enalish




### Removing the safety disposal bag

- 1. Close the disposal bag with the string (B).
- Carefully remove the filter bag connection from the inlet fitting.
- 3. Close the disposal bag connection with the slider
- 4. Dispose of the disposal bag in accordance with legal regulations.




### Inserting the safety disposal bag

- 5. Clean the dirt tank.
- 6. Insert the safety disposal bag into the dirt tank.
- 7. Check that the ventilation holes (C) remain inside the dirt tank.
- 8. Press the bush of the new filterbag firmly on to the inlet fitting
- 9. Fold the top edge of the disposal bag over the rim of the dirt tank.



11. Close the retaining clamps (A). Ensure that the retaining clamps fit properly.




### 7.2.3 Replacing the filter bag "M"



During the following work, ensure that dust is not unnecessarily spread around, Wear a P2 breathing mask.

Never use the vacuum cleaner without a filter.



Removing the filter bag:

out of the socket.


4. Carefully remove the filter bag connection from the inlet fitting (B).

1. Switch off the vacuum clean-

 Open the retaining clamps
 (A) and remove the upper section of the vacuum clean-


er and pull the mains plug


- 5. Close the filter bag connection (C) with the slider.
- Dispose of the filter bag in accordance with legal regulations.



#### Inserting the filter bag:

- 7. Clean the dirt tank.
- 8. Insert the filter bag in the dirt tank.
- 9. Press the bush of the new filter bag firmly on to the inlet fitting (D).





- 10. Attach the upper section of the vacuum cleaner.
- 11.Close the retaining clamps (A). Ensure that the retaining clamps fit properly.


retain-


#### 7.2.4 Replacing the disposal bag "M"



During the following work, ensure that dust is not unnecessarily spread around, Wear a P2 breathing mask.

Never use the vacuum cleaner without a filter.





3. Close the disposal bag with string (B).

1. Switch off the vacuum

plug out of the socket.


2. Open

cleaner and pull the mains


the

ing clamps (A) and remove the upper section of the vacuum cleaner.


- 4. Carefully remove the filter bag connection from the inlet fitting (C).
- nection (D) with the slider.
- in accordance with legal regulations.



B




- 5. Close the disposal bag con-
- 6. Dispose of the disposal bag



#### Inserting the disposal bag:

- 7. Clean the dirt tank.
- 8. Insert the disposal bag into the dirt tank.
- 9. Check that the ventilation holes (E) remain inside the dirt tank.
- 10. Press the bush of the new filter bag firmly on to the inlet fitting.
- 11. Fold the top edge of the disposal bag over the rim of the dirt tank.



- 12. Attach the upper section of the vacuum cleaner.
- 13. Close the retaining clamps (A). Ensure that the retaining clamps fit properly.

english


#### 7.2.5 Replacing filter element "H" (Push & Clean System)




During the following work, ensure that dust is not unnecessarily spread around, Wear a P2 breathing mask.


CAUTION! In the case of asbestos abatement wear additional single-use clothing.


Never use the vacuum cleaner without a filter.











- 1. Switch off the vacuum cleaner and pull the mains plug out of the socket.
- 2. Open the retaining clamps (A) and remove the upper section of the vacuum cleaner.

#### Removing the filter element:

- 3. Using the enclosed tool (C), turn the filter holder (D) anticlockwise and remove it.
- 4. Carefully remove the filter element.
- Clean the filter seal (B). Check it for damage and replace it if necessary.
- 6. Place the protective filter bag over the filter element.
- Carefully remove the filter element and close the protective filter bag with a knot.
- 8. Dispose of the used filter element in accordance with legal regulations.

#### Inserting the filter element:

Using the enclosed tool, attach the filter holder and turn it clockwise to lock it.

- 10. Attach the upper section of the vacuum cleaner.
- 11. Close the retaining clamps (A). Ensure that the retaining clamps fit properly.


#### 7.2.6 Replacing filter element "H" (Xtreme Clean System)



During the following work, ensure that dust is not unnecessarily spread around, Wear a P2 breathing mask.

CAUTION! In the case of asbestos abatement wear additional single-use clothing.


Never use the vacuum cleaner without a filter.



- 1. Switch off the vacuum cleaner and pull the mains plug out of the socket.
- Open the retaining clamps


   (A) and remove the upper section of the vacuum cleaner.






#### Removing the filter elements:

- 3. Unscrew the screw and open filter tension part (B).
- 4. Remove carefully the cassettes with filter elements.




- 5. Place the protective filter bag over the filter element.
- Carefully remove the filter element and close the protective filter bag with a knot.
- 7. Dispose of the used filter element in acordance with legal regulations.



#### Inserting the filter elements:

- 8. Insert new filter elements (C) into the cassettes (D).
- 9. Attach the cassettes with the filter elements onto the upper section of the vacuum cleaner.
- 10.Fix the filter tension part (B) and attach the screw.




- 11. Attach the upper section of the vacuum cleaner.
- 12. Close the retaining clamps (A). Ensure that the retaining clamps fit properly.

#### 7.2.7 Replacing filter element "M" (Push & Clean System)




During the following work, ensure that dust is not unnecessarily spread around, Wear a P2 breathing mask.

Never use the vacuum cleaner without a filter.




- 1. Switch off the vacuum cleaner and pull the mains plug out of the socket.
- Open the retaining clamps

   (A) and remove the upper section of the vacuum cleaner.




#### Removing the filter element:

- 3. Turn the filter holder anticlockwise and remove it .
- 4. Carefully remove the filter element.
- 5. Clean the filter seal (B). Check it for damage and replace it if necessary.



#### Inserting the filter element:

- 6. Fit the filter holder and turn it clockwise to secure it.
- 7. Dispose of the used filter element in accordance with legal regulations.



- 8. Attach the upper section of the vacuum cleaner.
- Close the retaining clamps


   (A). Ensure that the retaining clamps fit properly.


#### 7.2.8 Replacing filter element "M" (XtremeClean System)



During the following work, ensure that dust is not unnecessarily spread around, Wear a P2 breathing mask.

Never use the vacuum cleaner without a filter.






### Switch off the vacuum cleaner and pull the mains plug out of the socket.

2. Open the retaining clamps (A) and remove the upper section of the vacuum cleaner.


#### Removing the filter elements:

- 3. Open filter tension part (B).
- 4. Remove carefully the cassettes with filter elements.



#### Inserting the filter elements:

- 5. Insert new filter elements (C) into the cassettes (D).
- Attach the cassettes with the filter elements onto the upper section of the vacuum cleaner.
- 7. Fix the filter tension part (B).
- 8. Dispose of the used filter elements in accordance with legal regulations.



- 9. Attach the upper section of the vacuum cleaner.
- Close the retaining clamps
   (A). Ensure that the retaining clamps fit properly.

# 8 Troubleshooting

|   | Fault                                                | Cause                                                                                         | Remedy                                                                                                                                                                          |
|---|------------------------------------------------------|-----------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| ‡ | Motor does not start                                 | > Fuse of the mains socket has blown.                                                         | Connect mains fuse.                                                                                                                                                             |
|   |                                                      | > Overload protection switch has tripped.                                                     | Switch off the vacuum cleaner<br>and allow it to cool for approx.<br>5 minutes. If the cleaner<br>cannot be started again,<br>contact the Nilfisk-Alto service<br>department.   |
|   |                                                      | > Motor is faulty.                                                                            | Have motor changed by<br>Nilfisk-Alto Service.                                                                                                                                  |
| ‡ | Motor does not run in automatic mode *)              | <ul> <li>Power tool/pneumatic tool is<br/>defective or not connected<br/>properly.</li> </ul> | Check that the power tool<br>works or that the plug is<br>inserted correctly.                                                                                                   |
|   |                                                      | > The power rating of the electrical tool is too low.                                         | Note that minimum power rating is P>40W                                                                                                                                         |
| ‡ | The acoustic warning sounds. (Reduced suction power) | > Suction power selected with suction power control*) is too low.                             | Set suction power in accordance with section "Setting suction power".                                                                                                           |
|   |                                                      | Hose diameter does not correspond with switch position                                        | Set correct switch position for<br>hose diameter                                                                                                                                |
|   |                                                      | > Clogged suction hose/nozzle.                                                                | Clean suction hose/nozzle                                                                                                                                                       |
|   |                                                      | > Tank, disposal bag or filter<br>bag is full.                                                | See "Emptying tank" or     "Replacing disposal bag, filter bag" sections.                                                                                                       |
|   |                                                      | > Filter element is clogged.                                                                  | See section "Cleaning filter<br>element" and "Replacing filter<br>element".                                                                                                     |
|   |                                                      | > Seal between tank and upper<br>section of vacuum cleaner is<br>faulty or missing.           | Replace seal.                                                                                                                                                                   |
|   |                                                      | > Cleaning mechanism is defective.                                                            | Contact Nilfisk-Alto Service.                                                                                                                                                   |
| ‡ | No suction power during wet cleaning                 | > Tank is full.                                                                               | Switch off the cleaner. Empty the tank.                                                                                                                                         |
| ‡ | Voltage fluctuations                                 | > Impedance of power supply is too high.                                                      | • Connect the cleaner to another socket closer to the fuse box. Voltage fluctuations over $7\%$ should not occur if the impedance at the transfer point is $\leq 0.15~\Omega$ . |

### 9 Further information

#### 9.1 Recycling the cleaner

Make the old cleaner unusable immediately.

- 1. Unplug the cleaner.
- 2. Cut the power cord.
- 3. Do not discard of electrical appliances with household waste.



As specified in European Directive 2002/96/EC on old electrical and electronic appliances, used electrical goods must be collected separately and recycled ecologically. Contact your local authorities or your nearest dealer for further information.

#### 9.2 Guarantee

Our general conditions of business are applicable with regard to the guarantee.

Unauthorised modifications to the appliance, the use of incorrect brushes in addition to using the appliance in a way other than for the intended purpose exempt the manufacturer from any liability for the resulting damage.

#### 9.3 Tests and approvals

Electrical tests must be performed in accordance with the provisions of safety regulations (BGV A3) and to DIN VDE 0701 Part 1 and Part 3. In accordance with DIN VDE 0702 these tests must be performed at regular intervals and after repairs or modifications.

The vacuum cleaner has been approved in accordance with IEC/EN 60335-2-69.

### 9.4 EC declaration of conformity

| CE                                                                              | EC declaration of conformity                                                                     |
|---------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------|
| Nilfisk-Advance A/S<br>Industrivej 1<br>DK-9560 Hadsund                         |                                                                                                  |
| Product:                                                                        | Vacuum cleaner for wet and dry operation                                                         |
| Model:                                                                          | ATTIX 30 -/50 -/0H/0M/PC/XC<br>ATTIX 30 -/50 -/2H/2M/PC/XC                                       |
| Description:                                                                    | 110/230-240V 50Hz                                                                                |
| The design of the appliance corresponds to the following pertinent regulations: | EC Machine Directive 2006/42/EC EC Low Voltage Directive 2006/95/EC EC EMC Directive 2004/108/EC |
| Applied harmonized standards:                                                   | EN ISO 12100-1, EN ISO 12100-2<br>EN 60335-2-69<br>EN 55014-1, EN 55014-2, EN 61000-3-2          |
| Applied national standards and technical specifications:                        | DIN EN 60335-1<br>DIN EN 60335-2-69                                                              |
| Dipl. Ing. Wolfgang Nieuwkamp<br>Tests and approvals                            | Hadsund, 01.12.2008                                                                              |

#### 9.5 Technical data

|                   |    | ATTIX 30-50 Safety |              |          |
|-------------------|----|--------------------|--------------|----------|
|                   |    | EU                 | GB 230/240 V | GB 110 V |
| Voltage           | V  | 230                | 230/240      | 110      |
| Mains frequency   | Hz | 50                 |              |          |
| Fuse              | Α  | 16                 | 13           | 32       |
| Power consumption | W  | 1200               |              | 1000     |

|                                                             |                                        | 30-0H PC/XC<br>30-0M PC/XC                                                                                           | 50 0H PC/XC<br>50-0M PC/XC | 30-2H PC/XC<br>30-2M PC/XC                       | 50-2H PC/XC<br>50-2M PC/XC |  |  |
|-------------------------------------------------------------|----------------------------------------|----------------------------------------------------------------------------------------------------------------------|----------------------------|--------------------------------------------------|----------------------------|--|--|
| Connected load for appliance socket                         | W                                      | 2400 (EU)<br>1750 (GB 230/240)<br>1400 (GB 110V)                                                                     |                            | (230/240)                                        |                            |  |  |
| Total connected load                                        | W                                      | 1200 (EU, GB 230/240)<br>1000 (GB 110V)                                                                              |                            | 3600 (EU)<br>2950 (GB 230/240)<br>2400 (GB 110V) |                            |  |  |
| Air flow rate                                               | m³/h<br>l/min                          | 222 (EU, GB 230/240) / 192 (GB 110V)<br>3700 (EU, GB 230/240) / 3200 (GB 110V)                                       |                            |                                                  |                            |  |  |
| Vacuum                                                      | hPa                                    | 250 (EU, GB 230/240)<br>230 (GB 110V)                                                                                |                            |                                                  |                            |  |  |
| Sound pressure<br>level at a distance of<br>1 m, EN 60704-1 | dB(A)                                  | 62                                                                                                                   |                            |                                                  |                            |  |  |
| Working sound level                                         | dB(A)                                  | 59                                                                                                                   |                            |                                                  |                            |  |  |
| Power cord: Length                                          |                                        | 7,5                                                                                                                  |                            |                                                  |                            |  |  |
| Power cord: Type                                            |                                        | 2) (GB 110 V) 1) (EU) 1) (EU)<br>4) (EU) 2) (GB 110 V) 3) (GB110V)<br>5) (GB 230/240) 5) (GB 230/240) 5) (GB 230/240 |                            | 3110V)                                           |                            |  |  |
| Protection class                                            |                                        | i                                                                                                                    |                            |                                                  |                            |  |  |
| Type of protection                                          |                                        | IP X4                                                                                                                |                            |                                                  |                            |  |  |
| Radio interference level                                    |                                        | EN 55014-1                                                                                                           |                            |                                                  |                            |  |  |
| Tank volume                                                 | I                                      | 30                                                                                                                   | 45                         | 30                                               | 45                         |  |  |
| Width                                                       | mm                                     | 380                                                                                                                  |                            |                                                  |                            |  |  |
| Depth                                                       | mm                                     | 450                                                                                                                  |                            |                                                  |                            |  |  |
| Height                                                      | mm                                     | 595                                                                                                                  | 750                        | 595                                              | 750                        |  |  |
| Weight                                                      | kg                                     | 10                                                                                                                   | 11                         | 10 (PC)<br>12 (XC)                               | 11 (PC)<br>12 (XC)         |  |  |
| 1) = H05RR-F 3G1,5                                          | 2) = H05BQ-F 3G1,0                     |                                                                                                                      | 3) = H07BQ-F<br>3G2,5      | 4) = H07RN-F 3G1,5                               | 5) = H05RR-F<br>3G1,5      |  |  |
|                                                             | CAUTION! Only use the cables mentioned |                                                                                                                      |                            |                                                  |                            |  |  |

### 9.6 Optional accessories

| Description                             | Order No. |
|-----------------------------------------|-----------|
| Safety filter bag "H" ATTIX 30 (5 pcs.) | 107400233 |
| Safety filter bag "H" ATTIX 50 (5 pcs.) | 107400236 |
| Fleece filter bag ATTIX 30 (5 pcs.)     | 302004000 |
| Fleece filter bag ATTIX 50 (5 pcs.)     | 302004004 |
| Zylindrical H-filter element PC         | 302000658 |
| Zylindrical M-filter element PC         | 302000490 |
| Flat H-filter element XC (2 pcs.)       | 107400449 |
| Flat M-filter element XC (2 pcs.)       | 302002842 |
| Motor Cooling air filter                | 302003721 |
| Blowing adapter                         | 302003717 |
| Cloth insert filter ATTIX 30,50         | 302000525 |
| Nilfisk-Alto-Foam-Stop (6x1l)           | 8469      |





Why Compromise

www.nilfisk-alto.com

### **HEADQUARTER**

#### **DENMARK**

Nilfisk-Advance Group Sognevej 25 2605 Brøndby Denmark Tel.: (+45) 43 23 81 00

Fax: (+45) 43 43 77 00 E-mail: mail@nilfisk-advance.dk

#### **SALES COMPANIES**

**AUSTRALIA** 

Nilfisk-ALTO 48 Egerton St. PO box 6046 Silverwater NSW 2128 Australia

Tel.: (+61) 2 8748 5966 Fax: (+61) 2 8748 5960

#### **AUSTRIA**

Nilfisk-Advance GmbH Nilfisk-ALTO Metzgerstrasse 68 A-5101 Bergheim bei Salzburg Tel.: (+43) 662 456 400-0 Fax: (+43) 662 456 400-34 E-mail: info@nilfisk-alto.at www.nilfisk-alto.at

#### **BELGIUM**

Nilfisk-ALTO Division of Nilfisk-Advance n.v-s.a. Dornveld/Sphere Business Park Industrie Asse 3, nr 11 – bus 41 1731 Zellik-Asse Belaium

Tel.: (+32) 02 467 60 50 Fax: (+32) 02 466 61 50 E-mail: info.be@nilfisk-alto.com

#### CANADA

Clarke Canada Part of the Nilfisk-Advance Group 4080 B Sladeview Crescent, Unit 1 Mississauga, Ontario L5L 5Y5 Canada

Tel.: (+1) 905 569 0266 Fax: (+1) 905 569 8586

#### **CZECH REPUBLIC** ALTO Ceskà republika s.r.o.

Zateckých 9 14000 Praha 4 Czech Republic Tel.: (+420) 24 14 08 419 Fax: (+420) 24 14 08 439 E-mail: info@alto-cz.com

#### **DENMARK**

Nilfisk-ALTO Division of Nilfisk-Advance A/S Industrivei 1 9560 Hadsund Denmark

Tel.: (+45) 72 18 21 00 Fax: (+45) 72 18 21 11 E-mail: salg@nilfisk-alto.dk E-mail: service@nilfisk-alto.dk www nilfisk-alto dk

Nilfisk-ALTO Food Division Division of Nilfisk-Advance A/S Blytækkervej 2, 9000 Aalborg Denmark

Tel.: (+45) 72 18 21 00 Fax: (+45) 72 18 20 99

E-mail: scanio.technology@nilfisk-alto.dk www.nilfisk-alto.com

**FRANCE** 

Nilfisk-ALTO ALTO France SAS Aéroparc 1, 19 rue Icare 67960 Entzheim France Tel.: (+33) 3 88 28 84 00

Fax: (+33) 3 88 30 05 00 E-mail: info@nilfisk-alto.fr www.nilfisk-alto.com

#### **GERMANY**

Nilfisk-ALTO Division of Nilfisk-Advance AG Guido-Oberdorfer-Str. 10 89287 Bellenberg Germany Tel.: (+49) (0) 180 5 37 37 37

Fax: (+49) (0) 180 5 37 37 38 E-mail: info@nilfisk-alto.de www.nilfisk-alto.de

#### **GREECE**

Nilfisk-Advance SA 8, Thoukididou str. 164 52 Argiroupolis Greece

Tel.: (+30) 210 96 33443 Fax: (+30) 210 96 52187 E-mail: nilfisk-advance@clean.gr

#### HOLLAND

Nilfisk-ALTO Division of Nilfisk-Advance BV Camerastraat 9 NL-1322 BB Almere Tel.: (+31) 36 5460 760 Fax: (+31) 36 5460 761 E-mail: info@nilfisk-alto.nl www.nilfisk-alto.nl

#### HONG KONG

Nilfisk-Advance Ltd. 2001 HK Worsted Mills Ind'l Bldg., 31-39 Wo Tong Tsui St. Kwai Chung, Hong Kong Tel.: (+852) 2427 5951 Fax: (+852) 2487 5828

#### HUNGARY Nilfisk-Advance Kereskedelmi Kft.

II. Rákóczi Ferenc út 10 2310 Szigetszentmiklos-Lakihegy Hungary Tel.: (+36) 24 475 550 Fax: (+36) 24 475 551 E-mail: info@nilfisk-advance.hu Sales: ertekesites@nilfisk-advance.hu Service: service@nilfisk-advance.hu www.nilfisk-advance.hu

#### **ITALY**

Nilfisk-Al TO Divisione di Nilfisk-Advance A/S Località Novella Terza 26862 Guardamiglio (LO) Italy E-mail: d.puglia@nilfisk-advance.it

**JAPAN** 

Nilfisk-Advance, Inc. 1-6-6 Kita-shinyokohama, Kouhoku-ku, Yokohama, 223-0059 Japan

Tel.: (+81) 45 548 2571 Fax: (+81) 45 548 2541

#### MALAYSIA

Nilfisk-Advance Sdn Bhd Sd 14, Jalan KIP 11 Taman Perindustrian KIP Sri Damansara 52200 Kuala Lumpur Malaysia

Tel.: (+60) 3 603 6275 3120 Fax: (+60) 3 603 6274 6318

#### NORWAY

Nilfisk-Advance AS Bjørnerudveien 24 1266 Oslo Norway

Tel.: (+47) 22 75 17 70 Fax: (+47) 22 75 17 71 E-mail: info@nilfisk-alto.no

www.nilfisk-alto.no

#### PEOPLE'S REPUBLIC OF CHINA

Nilfisk-Advance (Shenzhen) Ltd Block 3, Unit 130, 1001 Honghua Road Int. Commercial & Trade Center Fuitian Free Trade Zone 518038 Shenzhen P.R. China Tel.: (+86) 755 8359 7937 Fax: (+86) 755 8359 1063

#### **POLAND**

05-800 Pruszków ul. 3-go MAJA 8 Poland Tel.: (+48) 22 738 37 50 Fax: (+48) 22 738 37 51 info@nilfisk-alto.pl www.nilfisk-alto.pl

Nilfisk-Advance Sp. Z.O.O.

#### **PORTUGAL**

Nilfisk-ALTO Division of Nilfisk-Advance Lda Sintra Business Park Zona Industrial da Abrunheira Edificio 1, 1° A P-2710-089 Sintra Tel.: (+35) 808 200 537 Fax: (+35) 121 911 2679 E-mail: mkt@nilfisk-advance.es www.nilfisk-alto.com

#### RUSSIA

Nilfisk-Advance LLC 127015 Moskow Vyatskaya str. 27, bld. 7 Russia

Tel.: (+7) 495 783 96 02 Fax: (+7) 495 783 96 03 E-mail: info@nilfisk-advance.ru

#### SINGAPORE

Nilfisk-Advance Pte. Ltd. Nilfisk-ALTO Division 40 Loyang Drive Singapore 508961 Tel.: (+65) 6 759 9100 Fax: (+65) 6 759 9133 E-mail: sales@nilfisk-advance.com.sg

#### **SPAIN**

Nilfisk-ALTO Division of Nilfisk-Advance S.A. Torre D'Ara Paseo del Rengle, 5 Pl. 10 E-08302 Mataró Tel.: (+34) 902 200 201 Fax: (+34) 93 757 8020 E-mail: mkt@nilfisk-advance.es www.nilfisk-alto.com

#### **SWEDEN**

ALTO Sverige AB Member of Nilfisk-Advance Group Aminogatan 18, Box 4029 S-431 04 Mölndal Sweden Tel.: (+46) 31 706 73 00 Fax: (+46) 31 706 73 40 E-mail: info@nilfisk-alto.se

#### **TAIWAN**

www.nilfisk-alto.se

Nilfisk-Advance Taiwan Branch No. 5, Wan Fang Road Taipei Taiwan, R.O.C. Tel.: (+886) 227 002 268 Fax: (+886) 227 840 843

**THAILAND** 

Nilfisk-Advance Co. Ltd. 89 Soi Chokechai-Ruammitr Viphavadee-Rangsit Road Ladyao, Jatuchak, Bangkok 10900 Thailand

Tel.: (+66) 2 275 5630 Fax: (+66) 2 691 4079

#### TURKEY

Nilfisk-Advance Profesyonel Temizlik Ekipmanları Tic. AŞ. Necla Cad. Nl.: 48 Yenisahra /Kadiköy Istanbul Turkey Tel.: (+90) 216 470 08 - 60 Fax: (+90) 216 470 08 - 63 www.nilfisk-advance.com

#### **UNITED KINGDOM**

Nilfisk-ALTO Division of Nilfisk-Advance Ltd. Bowerbank Way Gilwilly Industrial Estate Penrith Cumbria CA11 9BQ Great Britain Tel.: (+44) (0) 1768 868995 Fax: (+44) (0) 1768 864713 E-mail: sales@nilfisk-alto.co.uk www.nilfisk-alto.co.uk

#### **VIETNAM**

Nilfisk-Advance Representative Office No. 46 Doc Ngu Str. Ba Dinh Dist. Hanoi SR. Vietnam Tel.: (+84) 4 761 5642 Fax: (+84) 4 761 5643 E-mail: nilfisk@vnn.vn

ALTO Cleaning Systems Inc. Part of the Nilfisk-Advance Group 12249 Nations Ford Road Pineville, NC 28134 USA Tel.: (+1) 704 971 1240 Fax: (+1) 704 971 1241 E-mail: info@altocsi.com

#### Clarke

2100 Highway 265 Springdale, AR 72764 USA Tel.: (+1) 479 750 8450

Fax: (+1) 479 750 4540

E-mail: customerservice@clarkeus.com www.ClarkeUS.com

Clarke American Sanders 2100 Highway 265 Springdale, AR 72764 USA Tel.: (+1) 479 750 1000

Fax: (+1) 479 750 4540 E-mail:

customerservice@americansanders.com www.AmericanSanders.com

American Lincoln 1100 Haskins Road Bowling Green, OH 43402 USA

Tel.: (+1) 419 352 7511 option 2 Fax: (+1) 419 373 4221

customerservice@americanlincoln.com www.AmericanLincoln.com

Free Manuals Download Website

http://myh66.com

http://usermanuals.us

http://www.somanuals.com

http://www.4manuals.cc

http://www.manual-lib.com

http://www.404manual.com

http://www.luxmanual.com

http://aubethermostatmanual.com

Golf course search by state

http://golfingnear.com

Email search by domain

http://emailbydomain.com

Auto manuals search

http://auto.somanuals.com

TV manuals search

http://tv.somanuals.com