
Clock Radio

User manual



AJ3120



English

CONTROLS

1 SLEEP - activates the radio for sleep function

Clock control

- CLOCK : to run on clock time
- SET ALARM : sets the alarm time
- SET TIME : sets the clock time
- HR/MIN : adjusts the hours/ minutes for the clock and alarm times
- 3 ALARM RESET stops the active alarm for 24 hours

(4) SLEEP OFF /REPEAT ALARM

- switches off the radio sleep function
- switches off the active alarm for a 8-9 minute period
- (5) DISPLAY show the clock/ alarm times and status of the set
- 6 VOLUME adjusts the sound level
- (7) BAND select FM/AM (MW or LW) waveband
- (8) TUNING tunes to radio stations
- 9 RADIO OFF ON switches the radio off/on
- 0 ALARM
 - OFF switches off the alarm
 - RAD activates the radio for alarm setting
 - BUZ activates the buzzer for alarm setting
- Battery door opens to store a 9 volt 6F22 type battery (not included) for clock memory backup
- (2) Mains lead for AC mains supply
- 13 Pigtail aerial improves FM reception

nload from WWW.Bopharnus lectord. Althenhafthans Steared And Downlo

INSTALLATION

POWER SUPPLY

- 1 Check if the mains supply, as shown on the type plate located on the bottom of the set, corresponds to your local mains supply. If it does not, consult your dealer or service centre.
- 2 Connect the mains lead to the wall socket.
- 3 To disconnect the set from the mains supply completely, remove the plug from the wall socket.

CLOCK MEMORY BACKUP

The clock memory backup allows your alarm and clock time settings to be stored for up to a day when there is a power interruption e.g. mains failure. The complete clock radio and display illumination will be switched off. As soon as the mains supply returns, the display will indicate the correct time.

- Remove the battery door to insert a 9 volt 6F22 type battery (not included) for backup.
- 2 Replace the battery door.
- NOTE: If no backup battery is installed or the power interruption is prolonged, you will need to set the clock and alarm times again.

Batteries contain chemical substances so should be disposed of properly.

CAUTION

Use of controls or adjustments or performance of procedures other than herein may result in unsafe operation.

RADIO

You can use this set solely as a radio!

- 1 Adjust RADIO OFF ON to ON to switch on the radio.
- 2 Select your waveband by adjusting the BAND switch.
- 3 Adjust TUNING to tune to your desired station.
- 4 Turn the VOLUME control to adjust the volume level.
- 5 Adjust RADIO OFF ON to OFF to switch off the radio.

To improve reception:

- FM: extend and position the pigtail for optimum reception.
- AM: uses a built-in aerial inside the set. Direct the aerial by adjusting the position of your set.

SETTING THE CLOCK AND ALARM TIMES

The time is displayed using the 24-hour clock

IMPORTANT! To adjust the clock and alarm times accurately, always make sure you press the HR or MIN buttons separately and not simultaneously.

- Turn the clock control to SET TIME or SET ALARM to set the clock or alarm time respectively.
- 2 Press HR or MIN repeatedly or hold down on the respective button to adjust the hours and minutes.
- 3 Release HR or MIN when you reach the correct setting.
- 4 After you have set both the hour and minutes, turn the clock control to CLOCK to run on clock time.

SELECTING THE ALARM MODE

GENERAL

If you wish to use the alarm, you must first set the alarm time first. You can choose from two different alarm modes to wake you up: by radio or buzzer.

· Select your choice of alarm mode by adjusting ALARM to RAD or BUZ.

SWITCHING OFF THE ALARM

There are three ways of switching off the alarm. Unless you cancel the alarm completely, the **24 hour alarm reset option** will be automatically selected after 1 hour and 59 minutes, from the time your alarm time first goes off.

24 HOUR ALARM RESET

If you want the alarm mode to be stopped immediately but also wish to retain the same alarm setting for the following day:

Press ALARM RESET during the alarm call.

CANCELING THE ALARM COMPLETELY

To cancel the set alarm time before it goes off, or during the alarm call:

• Adjust ALARM to OFF position.

REPEAT ALARM

This repeats your alarm call at 8-9 minute intervals.

- 1 During the alarm call, press SLEEP OFF /REPEAT ALARM.
- 2 Repeat if desired for up to 1 hour and 59 minutes.

SLEEP

About Sleep

This set has a built-in timer which enables the set to be automatically switched off during radio playback after a fixed period of 59 minutes. This allows you to lie back, listen and fall asleep.

Setting SLEEP

- 1 Check that the clock control is in CLOCK position.
- 2 Set RADIO to OFF position.
- 3 Press SLEEP to activate the sleep function.
 - → To cancel sleep, or to switch off the sleep period ends press SLEEP OFF /REPEAT ALARM.

AUSTRALIA - Philips Manufacturers Warranty for Australia only

These warranty conditions are valid for the following consumer electronics products: Colour Televisions, Projection TV, Plasma & LCD TV, Video Cassette Recorders, CD Recorders, DVD Recorders, DVD Recorders, DVD Recorders with HDD,Audio Systems, Home Theatre systems, Digital Set Top Box & Portable Audio products.

The benefits given to the purchaser by this warranty are in addition to all other rights and remedies which the purchaser has in respect of the product under the Trade Practices Act or other Commonwealth or State Law.

Philips Consumer Electronics warrants its products to the purchaser as follows and subject to the stated conditions.

1 Year Free Repair Service - at Philips ASC

Colour Television, Plasma Television, LCD Television, Projection Television, DVDR/VCR Combo, DVD Recorders with Hard Drive, LCD Projectors, Wireless Audio Systems, Audio Systems, Home Theatre Systems & Digital Set-Top-Box.

1 Year Free Replacement - at your Retailer

Portable Audio, MP3 Infotainment products, Video Cassette recorders, DVD Player, DVD/VCR Combo Player, DVD Recorder without HDD & Portable DVD/LCD players.

Conditions of Repair Warranty

- All claims for warranty service should be made to your nearest. Philips Authorised Service Centre or the Philips Technology Care Centre. Reasonable evidence of date of purchase must be provided.
- This warranty extends only to defects in material or workmanship occurring under normal use of the product when operated in accordance with the instructions.
- If a replacement product is supplied under the repair policy it is warranted for the remainder of the warranty of the original purchased product only.
- 4. Hore service is provided only within the normal service area fore of our recommended Authorities Service Centres (ASC). It will be provided for television receiver only with a service side of 67ms or above (product includes CRT_LCD TV_PTV_and Plasma TV). Felevions with screen side less than 67ms and all other products types are to be taken or sent by the commer to the workshop of your nearest Authorised Service Centre, at the Consumer's expense.
- This Manufacturers Warranty is limited to 3 months for the above listed Consumer Electronics products if used in commercial applications.
- Philips may, at its discretion choose to replace rather than repair any product covered by this warranty.
- Product accessories are covered by the same warranty period. Please contact the Philips Technology Care Centre for free replacement of faulty accessories.

 This Manufacturers Warranty is neither transferable nor valid in countries other than Australia.

This warranty does not cover:

a) Mileage or travel outside the normal service area covered by selected Authorised Service Centre.

b) Service costs arising from failure to correctly adjust the controls of the product or to observe the instructions, or inspections that reveal that the product is in normal working order.

c) Product failures caused by misuse, neglect, accidental breakage, transit damage, inexpert repairs or modification by un-authorised persons, external fires, lighting strikes, floods, vermin infestation or liquid spillage.

d) Cleaning of video or audio heads.

e) Inadequate receiving antennae.

 Replacement of worn or used batteries or other consumables.

g) Consumer products used in commercial applications (This warranty is limited to 3 months only).

h) Second hand products.

The conditions contained in this warranty card replace and override the provision of the Philips World-Wide Guarantee for products purchased in Australia and used in Australia.

Service is provided through more than 100 accredited Authorised Service Centres throughout Australia. For direct contact with the nearest recommended Authorised Service Centre in capital & regional cities/towns

Authorised Service Centre Network 1300 361 392

Customer support is provided in Australia by our trained call centre staff. For assistance with product features and specifications, please call

Technology Care Centre 1300 363 391

Please record the following information for your records and keep in a safe place. We recommend retaining your purchase receipt to assist with any warranty claim.

Model number:_____

Serial number:

Date of purchase

Retailer:....

Philips Consumer Electronics

a division of **Philips Electronics Australia Limited** ABN 24 008 445 743, Level 1, 65 Epping Road NORTH RYDE NSW 2113.

SAFETY & MAINTENANCE INFORMATION

- Install the unit near the AC outlet and where the AC power plug can be easily reached.
- · The apparatus shall not be exposed to dripping or splashing.
- If you do not intend to use the set for a long time, withdraw the mains plug from the wall socket. In addition to this, it is advisable to remove the battery from the clock radio. This will prevent any danger of leakage and the clock radio will not be damaged.
- Do not expose the set to humidity, rain, sand or excessive heat caused by heating equipment or direct sunlight.
- To clean the set, use a soft, slightly dampened chamois leather. Do not use any cleaning agents containing alcohol, ammonia, benzene or abrasives as these may harm the housing.

ENVIRONMENTAL INFORMATION

All unnecessary packaging material has been omitted. The packaging can be easily separated into three materials: cardboard, polystyrene and plastic.

Your set consists of materials which can be recycled if disassembled by a specialized company. Please observe the local regulations regarding the disposal of packaging, dead batteries and old equipment.

TROUBLESHOOTING

If a fault occurs, first check the points listed below before taking the set for repair. If you are unable to remedy a problem by following these hints, consult your dealer or service centre.

WARNING: Under no circumstances should you try to repair the set yourself, as this will invalidate the guarantee. Do not open the set as there is a risk of electric shock.

Problem

- Possible Cause
- Remedy

No sound/power

- Volume not adjusted
- · Adjust the volume

Occasional crackling sound during FM broadcast

- Weak signal
- · Extend and position the pigtail

Continuous crackling/hiss disturbance during AM broadcast

- Electrical interference from TV, computer, fluorescent lamp, etc.
- Move set away from other electrical equipment

The alarm does not function

- Alarm time not set and or alarm mode not selected
- Set the alarm time and / select alarm mode
- Volume too low for RADIO
- · Adjust the volume
- Radio alarm not adjusted to radio station
- · Tune to a radio station

NEW ZEALAND - Guarantee and Service for New Zealand

Thank-you for purchasing this quality Philips product.

Philips New Zealand Ltd guarantees this product against defective components and faulty workmanship for a period of 12 months. Any defect in materials or workmanship occurring within 12 months from the date of purchase subject to the following conditions will be rectified free of charge by the retailer from whom this product was purchased.

Conditions

- The product must have been purchased in New Zealand.As proof of purchase, retain the original sales docket indicating the date of purchase.
- The guarantee applies only to faults caused by defective components, or faulty workmanship on the part of the manufacturer.
- 3. The guarantee does not cover failures caused by misuse, neglect, normal wear and tear, accidental breakage, use onthe incorrect voltage, use contrary to operating instructions, or unauthorised modification to the product or repair by an unauthorised technician.
- 4. Reasonable evidence (in the form of a sales docket) must be supplied to indicate that the product was purchased no more than 12 months prior to the date of your claim.
- In the event of a failure, Philips shall be under no liability for any injury, or any loss or damage caused to property or products other than the product under guarantee.

This guarantee does not prejudice your rights under common law and statute, and is in addition to the normal responsibilities of the retailer and Philips.

How to claim

Should your Philips product fail within the guarantee period, please return it to the retailer from whom it was purchased. In most cases the retailer will be able to satisfactorily repair or replace the product.

However, should the retailer not be able to conclude the matter satisfactorily, or if you have other difficulties claiming under this guarantee, please contact

The Guarantee Controller Philips New Zealand Ltd. ଗ୍ରେମ୍ବାର ଅନ୍ୟ 1.021 Auckland ଫୁ (୦୭) 84 94 160 /nloadsárመମ (୦୭) ୫୫୨୦ Manuals.com. All Manuals Search And Downlo

AJ 3120 - Clock radio





Free Manuals Download Website <u>http://myh66.com</u> <u>http://usermanuals.us</u> <u>http://www.somanuals.com</u> <u>http://www.4manuals.cc</u> <u>http://www.4manuals.cc</u> <u>http://www.4manuals.cc</u> <u>http://www.4manuals.com</u> <u>http://www.404manual.com</u> <u>http://www.luxmanual.com</u> <u>http://aubethermostatmanual.com</u> Golf course search by state

http://golfingnear.com Email search by domain

http://emailbydomain.com Auto manuals search

http://auto.somanuals.com TV manuals search

http://tv.somanuals.com