

The unique bedroom TV-Video Combi

- Built in Digital Clock Radio
- Dual Alarm Timer choose between radio or buzzer
- Wake up timer for your favourite tape, TV, radio station or buzzer
- Slumber Function gently fall asleep....
- Large clock display with adjustable brightness
- Turbo Drive fast access and immediate feedback on the tape position
- Formatter reduces the black bars in case of 16:9 programs
- Plug & Play the most convenient installation of your Combi
- Digital Studio Picture Control excellent playback performance
- Tele Text / Fast Text with favourite page memory
- SMART Clock for automatic time & date download









SHOWVIEW









PHILIPS

14" TV-Video Combi

Product information

Clock Radio

- Quartz operated Clock: 24 hrs indication, auto-set via smart clock
- LED Display: Large green 4 digits, 4-step brightness control FM Radio: Digital PLL
- Tuning: Autostore (2 sensitivity levels), 9 presets, manual
 Dual Alarm: Via Radio and Buzzer
- Wake up timer: Via TV, VCR or Radio
- · Slumber, Repeat alarm, Weekend sleeper
- · Smooth volume change (for Radio alarm and slumber)

- Tuning System: 1 PLL Tuner
- Tuning pre-sets: 99
 Install Features: ACI, Autostore+ (Autoinstall for /05)

- Picture Display / Processing
 Format /Size(visual): 4:3/14 (13)" / 37 (34) cm
- Picture Control: Brightness, Colour, Contrast, Sharpness, Tint for NTSC Pb
- Picture Features: Formatter

- Speaker / System: Full Range 4" / Mono
- Special Feature: Automatic Volume Leveller
 Power: 3W MPO, 1.5W rms

User Interface

- Indicators front: On / Off LED, Record LED, Timer LED, Buzzer alarm LED, Radio alarm LED
- Multi Colour Menu: Cursor Control & Intelligent Help-line
- · Special Features: Auto Stby, Child Lock, Hotel mode, Prog.list

Computer Controlled Tele Text

- Tele Text / Fast Text: WST lev. 1.5
- Tele Text features: Conceal reveal, Transparent mode, Enlarge, Cancel, Hold, Sub-pages, 1 Fav. Page / Channel

- Turbo Drive: VHS-HQ, 2 Video Heads
- · Head Cleaning Mode: Automatic, Manual
- Stop to Play Time: 0.4 sec.
- Tape Counter: Time used/left, Non linear NTSC Pb
 Rew. / Winding Time: 100 sec. (for E180)

Tape Functions

- Play / Still Feature: +1x, -1x, Repeat / Standard
 Fast Speed: +2x / -3x, +5x / -5x, +9x / -9x
- VISS: Next / Prev. index and Record End Search

- **VCR Picture Quality** Resolution: HQ+ / >240 lines
- Tracking System: Digital Studio Tracking
 Digital Studio Picture Control, Edge Noise Canceller

- ProgrammingNumber of Events: 6 / month
- Rec. Control: PDC / VPS (also for Transm. Identification)
- Programming System: ShowView / Video+, OTR
- Record Speed: Standard Play (SP), Long Play (LP, PAL only)

Connectors Rear

- EXT1: Euro CVBS, RGB in
- · Antenna in: 75 Ohms (IEC type, for TV tuner only)

Connectors Side

- · EXT2: Cinch CVBS in, Cinch mono in
- Headphone Out: Mini-Jack 3.5mm, Mono

- Voltage / Frequency: 198-264V / 50 / 60Hz
 Voltage / Frequency: 198-264V / 50 / 60Hz
 Power Cons. in W: Operating 44 / Standby <6
 Backup Presets / Clock: >1 yr / >10 min
 Set Size in mm: 398 x 407 x 392 (h x d x w)
 Packaging in mm: 522 x 514 x 474 (h x d x w)
 Weight in kg: 15 / 12.6 incl. / excl. Box

Accessories

- · Documents / Manuals: DFU, Guarantee doc., Promotion Screen Sticker
- Aux. Equipm. Supplied: Batteries for RC, fixed wire Radio antenna

Remote Control

• Remote Control - type: RT797 / 101

Product Highlights

Enjoy the ease of use and the comfort of one of the fastest VCR decks in the world.

• **Plug & Play**Installing a Combi has never been easier! No need of the user manual. Just let the Combi guide you through the installation steps.

Wake-up and Sleep Timer

Automatically turns the Combi off at a preset time of up to 180 minutes from the time the feature is activated. Sleep timer settings are programmed in 15-minute increments.

Dual Alarm

Allows separate alarm settings to accomodate couples with different schedules or provide additional security. This function comes in addition to the Wake up timer.

Repeat Alarm

With hit on any remote key — standby switches it off — the alarm is repeated after 10 minutes.

• Tele Text / Fast Text

with Favourite Page Memory

For even faster access to your favourite information, assign one "favourite bage" per channel.

Weekend Sleeper

Can be programmed not to sound on weekends, allowing users additional uninterrupted sleep.

• Digital Studio Picture Control

Be sure to obtain the best picture quality with any kind of tape thanks to a digitally controlled Noise-Reduction Circuitry.

• Full Auto Feature Package Incorporated into every PHILIPS Combi and includes:

- Automatic Power On when a tape is inserted.

 Automatic Digital Studio Tracking, assuring proper movements of video and audio heads for perfect recordings and viewing every time.

 Auto Play, inserting pre-recorded tapes will activate the Play mode.
- Auto Rewind as soon as the tape reaches the end.
- Auto Eject after record at the end of the tape, so tapes are not inadvertently left in the Combi.

	/05 S	/39 S
Full (UHF + VHF) Tuner	-	+
TV System off Air	PAL I	PAL B/G/I
		SECAM L/LIB/G
Radio FM frequ. range	87,5-108 MHz	87,5-108 MHz
Record / Playback Std.	PAL	PAL, SECAM, MESECAM
NTSC Playback Std.	SP LP SLP	SP LP SLP
PDC/VPS	+	+
Video Longplay	+	PAL only
OSD Menu Languages	l II	l l

Subject to modification without notice

Show View and Video+ are registered Trademarks of Gemstar Development Cooperation.







Free Manuals Download Website

http://myh66.com

http://usermanuals.us

http://www.somanuals.com

http://www.4manuals.cc

http://www.manual-lib.com

http://www.404manual.com

http://www.luxmanual.com

http://aubethermostatmanual.com

Golf course search by state

http://golfingnear.com

Email search by domain

http://emailbydomain.com

Auto manuals search

http://auto.somanuals.com

TV manuals search

http://tv.somanuals.com