

2 head mono VCR

VR287

## 2 head mono VCR

- **Longplay** possibility for tape-space saving
- **Shuttle Control** – you can precisely and easily locate a point on the tape
- **One-Button** automatic installation including auto time setup and correction
- **Follow TV** sorts the channels in the same order as your TV
- **ShowView™/VideoPlus™** – the easiest way to programme a Timer
- **Digital Studio Picture Control** for an excellent picture quality
- **Laser-Cut Video Heads** – the maximum precision for the ultimate recording quality
- **Automatic** time used indication
- **Easy-to-read** big VCR Display

**TURBO  
DRIVE**

**SHOWVIEW**

**VIDEOplus+**



Let's make things better.

Download from [www.Somanuals.com](http://www.Somanuals.com). All Manuals Search And Download.



**PHILIPS**

## Product Information

### Reception

- Tuning: PLL, CH - FREQ entry, 99 presets
- Tuning / Install Features: Automatic Search, Manual Search / Store
- Automatic Time / Date Download: PDC, Text (Time)

### User Interface

- OSD Menu Languages: Dutch, English, French, German, Italian, Spanish, Swedish
- Special Features: Child Lock
- Picture Improvement System: Digital Studio Picture Control, Edge Noise Canceller
- Audio Record System: Linear
- Audio Record Level: Automatic
- TV Related Functions: FollowTV, Direct Record

### Programming

- Number of Events: 6 / month
- Programming Mode: OTR, Remote
- Recording Control & Transmitter Identification: PDC, VPS
- Programming System: Daily / Weekly
- Automatic Sat. Recording: From EXT2

### Tape Deck

- Number of Video / FM Audio / Erase Heads: 2 / 0 / 0
- Play: +1x, -1x
- Playback Features: Still, Multiple Search Speeds, Variable Slow Motion Speed
- Index Search: Next / Previous index search
- Tape Length Recognition: Automatic
- Tape Counter: Linear relative, Linear time used
- Automatic Functions at Tape End: Rewind after Play – Eject after Record
- Winding / Rewinding Time (E180): 100 sec.
- Head Cleaning Mode: Automatic, Manual

### Connectors Rear

- EXT1: Black, Euro CVBS In & Out
- EXT2: Blue, Euro CVBS In & Out, Euro Decoder, RGB loop through
- Antenna In & Out: 75 Ohms (IECtype)
- Mains Connector: Standard (IECtype)

### General

- Voltage / Frequency: 198-264 V / 50Hz
- Backup Presets: 1yr
- Backup Clock, Timer Events & Calendar: 7hrs
- Power Cons. in Play/Std-By/Low Power Std-By: 12.5W / 9.5W / <6W
- Remote Control: RT184
- Equipment Supplied: Antenna cable, Mains cord, Batteries
- Set Size – W x D x H (mm): 380 x 260 x 93
- Packaging – W x D x H (mm): 450 x 382 x 180
- Weight including / excluding package in kg: 5.5 / 3.6

## Product Highlights

### • Digital Studio Picture Control

Thanks to a digital Noise-Reduction Circuit, you are sure to obtain the best picture quality with any kind of tape.

### • Automatic Time Download

At the first installation, your VCR will automatically download the time. Your VCR will be the clock reference in your home, as the time is readjusted every day. You don't even have to worry anymore about changing from summer to winter time!

### • Child Lock

Now there is no way that your children can see a movie without your permission. Just don't forget to hide the remote control!

### • Follow TV

You can now automatically arrange your VCR channels in the same order as your TV.

### • Direct Record

Record instantly what you see on your TV just by pressing one button. You don't have to worry anymore about selecting the right channel on your VCR.

### • TURBO DRIVE

Enjoy the ease of use and the comfort of one of the fastest VCR decks in the world.

### • Automatic Head Cleaning

Clean heads ensure an optimum picture quality. Each time you put a tape in your VCR, the heads will be cleaned automatically.

	/02	/07	/13	/39
Full (UHF+VHF) Tuner	x	x	x	x
TV System Off Air	PAL B/G	PAL I	PAL B/G	PAL B/G-I, SECAM B/G-L'L'
Programming System	ShowView™	VideoPlus™	ShowView™	ShowView™
Record/Playback Std	PAL	PAL	PAL	PAL-SEC-MESEC
Additional Playback Std	NTSC	NTSC	NTSC	NTSC
Record Speed	SP / LP	SP / LP	SP / LP	SP
Modulator System	PAL G	PAL I	PAL G	-
Modulator Range	Ch 21 - 55	Ch 21 - 55	Ch 21 - 55	-
Modulator Feature	-	Auto Seek	-	-
Modulator Preadjustment	Ch 36	Ch 35	Ch 36	-
Delivery Menu Language	English	English	English	French
Remote RT184 /	101	101	101	104

Subject to modification without notice

ShowView and VideoPlus are Trademarks of Gemstar Development Group

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>