

DuraSpin™ Cordless Screw Driver Model DS162-14v



Designed for high-speed screw fastening in drywall applications, the DuraSpin DS162-14v drives screws from 1" to 1 1/8" long.



Tool Specifications:

Voltage: 14.4 volts

Battery Ampacity: 1700 mAh

RPM: 4000 rev/min Weight: 4.9 lbs. (2.2 kg) Height: 10 inches (254 mm) Length: 13.8 inches (350 mm) Width: 2.8 inches (70 mm) Recharge Time: 1 hour

Screw Drives/Charge: see chart on reverse side Fastener Capacity: 50 screws (one strip)

Torque Delivered: 25 in-lbs Generated Noise: 74 dBA Vibration: less than 2.5m/sec²

Applications:

Drywall (to wood or steel studs).

Features and Benefits:

- 14.4 volt battery provides the optimum balance of power, weight and run-time across the full range of screws
- 4,000 RPM high-speed motor drives screws FAST!
- · Patented clutch design means long-lasting durability
- One-hour charger and extra battery ensures a backup battery with a full charge
- Easy depth-of-drive adjustment regulates the precise amount of countersink
- · Easy bit change
- Belt hook DuraSpin goes where you go
- · One full year warranty

Fastener Specifications:

Screw Lengths: 1" (25 mm) to 1 5/8" (41 mm)

Screw Diameters: #6

Application:	Drywall to Wood	Drywall to Light Gauge Steel	Drywall to Heavy Gauge Steel
Drive/Head:	#2 Phillips Bugle	#2 Phillips Bugle	#2 Phillips Bugle
Thread:	Coarse	Fine	Fine
Point:	Sharp	Sharp	Drill
Finish:	Grey Phosphate	Grey Phosphate	Clear Zinc
Screw:	#6 X 1 %" #6 X 1 %"	#6X1½"	#6 X 1 ¹ / ₄ *



DuraSpin™ Cordless Screw Driver Model DS162-14v



Typical Applications and Screws Used	Average Number of Screws Driven Per Charge	Screw Reorder Code		
Drywall to Wood				
#6 X 1" Screws	1100	06A100PB		
#6 X 1 ¹ / ₄ " Screws	975	06A125P		
#6 X 15/8" Screws	650	06A162P		
Drywall to Light Gauge Steel				
#6 X 11/4" Screws	925 (25 GAUGE) 900 (20 GAUGE)	06B125P		
Drywall to Heavy Gauge Steel				
#6 X 11/4" Screws	550 (18 GAUGE)	06C125C		

These are representative averages. Your results may vary based on specific work conditions.

For additional information on how Senco fastening systems will save you time, reduce costs and increase quality, call your nearest Authorized Senco Dealer or Distributor listed in the Yellow Pages under "Staples," or call our toll-free Action Line: 1-800-543-4596.

www.senco.com

Safety First. **47** The only way to work.®

Each tool comes complete with: Two 14.4 volt batteries, one-hour battery charger, 2 spare drive bits, and a rugged carrying case. Free Manuals Download Website

http://myh66.com

http://usermanuals.us

http://www.somanuals.com

http://www.4manuals.cc

http://www.manual-lib.com

http://www.404manual.com

http://www.luxmanual.com

http://aubethermostatmanual.com

Golf course search by state

http://golfingnear.com

Email search by domain

http://emailbydomain.com

Auto manuals search

http://auto.somanuals.com

TV manuals search

http://tv.somanuals.com