4-150-697-**13**(2) SONY

FM/AM Clock Radio

Operating Instructions

ICF-CS10iP

DREAM MACHINE





No Power No Problem is a trademark of Sony Corporation.

©2009 Sony Corporation

http://www.sony.net/

SONY®

LIMITED WARRANTY (U.S. Only)

Sony Electronics Inc. ("Sony") warrants this product against defects in material or workmanship for the time periods and as set forth below when purchased directly from Sony or a Sony Retailer. Pursuant to this Limited Warranty, Sony will, at its option, (i) repair the product using new or refurbished parts or (ii) replace the product with a new or refurbished product. For purposes of this Limited Warranty, "refurbished" means a product or part that has been returned to its original specifications. In the event of a defect, these are your exclusive rem-

Labor: For a period of one (1) year from the original date of purchase of the product ("Labor Warranty"), Sony will, at its option, repair or replace with new or refurbished product, product determined to be defective. If Sony elects to replace the product after this Labor Warranty has expired but while the Parts Warranty below is still in effect, it will do so for the applicable labor charge.

Parts: For a period of one (1) year from the original date of purchase of product ("Parts Warranty"), Sony will supply new or refurbished replacement parts in exchange for parts determined to be defective.

This Limited Warranty covers only the hardware components packaged with the Product. It does not cover technical assistance for hardware or software usage and it does not cover any software products whether or no contained in the Product; any such software is provided "AS IS" unless expressly provided for in any enclosed software Limited Warranty. Please refer to the End User License Agreements included with the Product for your rights and obligations with respect to the software.

Instructions: To obtain warranty service, you must deliver the product, freight prepaid, in either its original packaging or packaging affording an equal degree of protection to the Sony authorized service facility specified. It is your responsibility to backup any data, software or other materials you may have stored or preserved on your unit. It is likely that such data, software, or other materials will be lost or reformatted during service and Sony will not be responsible for any such damage or loss. A dated purchase receipt from Sony or a Sony Retailer is required. For specific instructions on how to obtain warranty service for your

Visit Sony's Web Site:

Or call the Sony Customer Information Service Center 1-800-222-SONY (7669)

For an accessory or part not available from your authorized dealer, call

Repair / Replacement Warranty: This Limited Warranty shall apply to any repair, replacement part or replacement product for the remainder of the original Limited Warranty period or for ninety (90) days, whichever is longer. Any parts or product replaced under this Limited Warranty will become the property of Sony.

This Limited Warranty only covers product issues caused by defects in material or workmanship during ordinary consumer use; it does not cover product issues caused by any other reason, including but not limited to product issues due to commercial use, acts of God, misuse, limitations of technology, or modification of or to any part of the Sony product or product purchased from other than Sony or a Sony Retailer. To determine if a retailer is part of the Sony Retailer Network, please contact Sony's Customer Service Call Center or go to www.sony.com/support. This Limited Warranty does not cover Sony products sold AS IS or WITH ALL FAULTS or consumables (such as fuses or batteries). This Limited Warranty is invalid if the factory-applied serial number has been altered or removed from the product. This Limited Warranty is valid only in the United States.

LIMITATION ON DAMAGES: SONY SHALL NOT BE LIABLE FOR ANY INCIDENTAL OR CONSEQUENTIAL DAMAGES FOR BREACH OF ANY EXPRESS OR IMPLIED WARRANTY ON THIS PRODUCT.

DURATION OF IMPLIED WARRANTIES: EXCEPT TO THE EXTENT PROHIBITED BY APPLICABLE LAW, ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE ON THIS PRODUCT IS LIMITED IN DURATION TO THE DURATION OF THIS WARRANTY.

Some states do not allow the exclusion or limitation of incidental or consequential damages, or allow limitation on how long an implied warranty lasts, so the above limitations or exclusions may not apply to you. This Limited Warranty gives you specific legal rights and you may have other rights which vary from state to state.

Owner's Record

Record the serial number in the space provided below. Refer to them whenever you call upon your Sony dealer regarding

Model No. ICF-CS10iP

Serial No.

For customers who purchased this product in the

Please register this product on line at Please register this product on line at http://www.sony.com/productregistration. Proper registration will enable us to send you periodic mailings about new products, service and other important announcements. Register your product will also allow us to contact you in the unlikely event that the product needs adjustment or modification. Thank you.

WARNING

To reduce the risk of fire or electric shock, do not expose this apparatus to rain or moisture.

To reduce the risk of fire, do not cover the ventilation of the apparatus with newspapers tablecloths, curtains, etc. And do not place lighted candles on the apparatus.

To reduce the risk of fire or electric shock, do not expose this apparatus to dripping or splashing, and do not place objects filled with liquids, such as vases, on the apparatus.

Do not install the appliance in a confined space, such as a bookcase or built-in cabinet.

Do not expose the batteries (battery pack or batteries installed) to excessive heat such as sunshine, fire or the like for a long time.

As the main plug is used to disconnect the unit from the mains, connect the unit to an easily accessible AC outlet. Should you notice an abnormality in the unit, disconnect the main plug from the AC outlet immediately.

The unit is not disconnected from the AC power source (mains) as long as it is connected to the wall outlet, even if the unit itself has been turned

The nameplate and important information concerning safety are located on the bottom exterior.

You are cautioned that any changes or modifications not expressly approved in this manual could void your authority to operate this

CAUTION

Danger of explosion if battery is incorrectly replaced. Replace only with the same type.









This symbol is intended to alert the user to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.



This symbol is intended to alert the user to the presence of important operating and enance (servicing) instructions in the iterature accompanying the appliance.

NOTE

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving
- Increase the separation between the equipment
- Connect the equipment into an outlet on a circuit different from that to which the receiver is
- Consult the dealer or an experienced radio/TV technician for help.

- Replace the battery for the clock backup with a Sony CR2032 lithium battery, and the battery for the remote commander with a Sony CR2025 lithium battery. Use of another battery may present a risk of fire or explosion.
- Battery may explode if mistreated. Do not recharge, disassemble or dispose of in fire.
- Dispose of used battery promptly. Keep away

Important Safety Instructions

1) Read these instructions

WARNING

- Keep these instructions.
- 3) Heed all warnings.
- 4) Follow all instructions

- 5) Do not use this apparatus near water. 6) Clean only with dry cloth.
- 7) Do not block any ventilation openings Install in accordance with the manufacturer's instructions. 8) Do not install near any heat sources such as
- radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce
- 9) Do not defeat the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades with one wider than the other. A grounding type plug has two blades and a third grounding prong. The wide blade or the third prong are provided for your safety. If the provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet. 10) Protect the power cord from being walked on
- or pinched particularly at plugs, convenience receptacles, and the point where they exit from the apparatus. 11) Only use attachments/accessories specified by
- the manufacturer.
- 12) Use only with the cart, stand, tripod, bracket, or table specified by the manufacturer, or sold with the apparatus. When a cart is used, use caution when moving the cart/apparatus combination to avoid injury from tip-over.



13) Unplug this apparatus during lightning storms or when unused for long periods of time.

14) Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way, such as power-supply cord or plug is damaged, liquid has been spilled or objects have fallen into the apparatus, the apparatus has been exposed to rain or moisture, does not operate normally, or has been dropped.

For the state of california, USA only

Perchlorate Material -special handling may apply, see www.dtsc.ca.gov/hazardouswaste/perchlorate Perchlorate Material: Lithium battery contains perchlorate

Precautions

- Play the unit on the power source specified in "Specifications."
- Since a strong magnet is used for the speaker, keep personal credit cards using magnetic coding or spring-wound watches away from the unit to prevent possible damage from the magnet.
- Do not leave the unit in a location near a heat source such as a radiator or airduct, or in a place subject to direct sunlight, excessive dust mechanical vibration, or shock.
- Allow adequate air circulation to prevent internal heat build-up. Do not place the unit on a surface (a rug, a blanket, etc.) or near materials (a curtain) which might block the ventilation holes
- Should any solid object or liquid fall into the unit, unplug the unit and have it checked by qualified ersonnel before operating it any further.

antenna during a thunderstorm. Furthermore

immediately disconnect the AC power cord

• To clean the casing, use a soft cloth dampened with a mild detergent solution. • Never touch the wire of the external FM

NOTES ON LITHIUM BATTERY

from the radio.

- Wipe the battery with a dry cloth to assure a good contact.
- Be sure to observe the correct polarity when installing the battery.
- · Do not hold the battery with metallic tweezers, otherwise a short-circuit may occur.

If you have any questions or problems concerning your unit, please consult your nearest Sony dealer

Download from Www.Somanuals.com. All Manuals Search And Download

Features

- Clock Radio compatible with iPod*/iPhone
- Wake or Sleep to iPod/Radio/Buzzer
- 2-5-7day alarm
- Easy to set A-B alarm

- LCD Brightness control MEGA BASS
- MEGA Xpand
- Wireless Remote Commander
- No Power No Problem alarm system to keep the clock and the alarm operating during a power interruption with a CR2032 battery

Specifications

AUDIO POWER SPECIFICATIONS

POWER OUTPUT AND TOTAL HARMONIC With 6 ohm loads both channels driven, from

150 Hz -10,000 Hz; rated 3 watts per channel minimum RMS power, with no more than 10 % total harmonic distortion.

Time display 12-hour s

Section for iPod

MAX: 500mA

Radio section Frequency range

| Band | Frequency | Channel step |
|------|---------------------|--------------|
| FM | 87.5 MHz – 108 MHz | 0.1 MHz |
| AM | 530 kHz – 1 710 kHz | 10 kHz |

General

Åpprox. 5.7 cm (2 $^{1}/_{4}$ inches) dia. 6 Ω

AUDIO IN jack (ø 3.5 mm stereo minijack)

Power output 3.5 W + 3.5 W (at 10% harmonic distortion) **Power requirements**

120 V AC, 60 Hz For clock back up: 3V DC, CR2032 battery (1)

Dimensions Approx. 290.5 mm \times 152.0 mm \times 139.5 mm (w/h/d)

including projecting parts and controls Mass Approx. 1.94 kg (4 lb 4 oz) including power

 $(11^{3}/_{8} \text{ inches} \times 5^{15}/_{16} \text{ inches} \times 5^{1}/_{2} \text{ inches})$

supply unit


Supplied accessories Remote commander (1)

AM loop antenna (1) Audio connecting cable (1) Universal Dock Adapter for iPhone (1) Universal Dock Adapter for iPhone 3G & iPhone

Universal Dock Adapter for iPhone 4 (1) Design and specifications are subject to change

Compatible iPod/iPhone models

Compatible iPod/iPhone models are as follows. Update your iPod/iPhone to use the latest software



iPhone 4

0

iPhone

iPod touch

iPod nano

iPod classic



iPod touch











iPod

Notes

- In these Operating Instructions, "iPod" is used as a general reference to iPod functions on an iPod or iPhone, unless otherwise specified by
- the text or illustrations. • The connector of the unit is for sole use with an iPod. If you use devices that do not match with the connector, connect to the AUDIO IN jack of this unit with the supplied audio connecting
- $\bullet\,$ Sony cannot accept responsibility in the event that data recorded to an iPod is lost or damaged when using an iPod connected to this unit.

Troubleshooting

Should any problem persist after you have made the following checks, consult your nearest Sony

The clock flashes "AM 12:00" due to a power interruption. • The battery is low. Replace the battery. Remove the old battery and install a new one.

The radio, iPod or buzzer alarm does not sound at the preset alarm time. • Check that alarm "A" or alarm "B" is properly

The radio or alarm of iPod is activated but no sound comes on at the preset alarm time.

 Check the alarm volume setting There is no sound from the iPod.

• Adjust the **VOLUME**. The iPod cannot be operated with this unit. Make sure the iPod is securely connected.

· Make sure the iPod is securely connected.

The iPod cannot be charged.

 Make sure the iPod is securely connected. When Daylight Saving Time (summer time) begins, the clock does not employ the Daylight Saving Time automatically.


• Make sure the clock is set correctly Press and hold CLOCK and SNOOZE/DATE/ **SLEEP OFF** simultaneously for at least 2 seconds to activate the Automatic DST

Connecting the antenna

To connect the AM loop antenna

The shape and the length of the antenna is designed to receive AM signals. Do not dismantle or roll up the antenna

- **1** Remove only the loop part from the plastic stand.
- **2** Set up the AM loop antenna.



3 Insert the AM antenna terminal into the **AM ANTENNA** jack on the rear of the



To remove the AM loop

Pull the AM antenna terminal while pushing up the terminal clamp.



Adjusting the AM loop antenna

Find a place and an orientation that provide good • Do not place the AM loop antenna near the

Adjust the direction of the AM loop antenna for best AM broadcast sound.

unit or other AV equipment, as noise may


Preparing the remote commander

Before using the card remote commander for the




To know when to replace the batterv

With normal use, the battery (CR2025) should last for about six months. When the remote commander no longer operates the unit, replac the battery with a new one



CR2025



If the time in the display is incorrect after the battery is changed (Reset)

reset button is in the small hole located in the battery compartment (see Fig. 2).

- Do not attempt to charge the battery.
- If you are not going to use the remote commander for a long time, remove the battery to avoid any damage that may be caused by leakage and corrosion.

About the backup battery

To keep accurate time, this unit contains a CR2032 battery as a backup power source. The battery keeps the clock and the alarm operating in the event of a power interruption

To know when to replace the battery

When the battery becomes weak, "♥\" appears in the display.

If a power interruption occurs while the battery is weak, the current time and alarm will be erased. Replace the battery with a Sony CR2032 lithium battery. Use of another battery may cause a fire or explosion.


If "AM 12:00" flashes in the display when the unit is connected to an AC outlet for the first time, the battery may be weak. In this case, consult your Sony dealer.


To replace the battery **1** Keep the AC plug connected to the AC


- outlet, remove the screw that secures the battery compartment lid at the bottom of the unit using a screwdriver, and open the lid (see Fig. 1). **2** Insert a new battery in the battery
- compartment with the **t** side facing up (see Fig. 2). **3** Close the battery compartment lid and
- secure it with the screw (see Fig. 3). 4 Press iPod & iPhone ►II, RADIO BAND, AUDIO IN or SNOOZE/DATE/ **SLEEP OFF** to turn "▷" off in the

display.


Note When you replace the battery, do not disconnect the plug from the AC outlet. Otherwise, the calendar, current time, alarm and station presets








This unit includes a preinstalled Sony Lithium battery (CR2032) as back-up power source for the clock, which is preset



The STATION • SELECT • PRESET 3, VOLUME + and iPod & iPhone ►II buttons have a



The ►II and VOL + buttons have a tactile dot.

When Daylight Saving Time

This model automatically adjusts for Daylight

end of Daylight Saving Time (summer time)

2:00 AM on the second Sunday of March.

"a" is displayed from the beginning of Daylight

Saving Time (summer time) and disappears at the

• Daylight Saving Time (summer time) begins at:

• Standard Time begins at: 2:00 AM on the first

To cancel Automatic DST/Summer Time

adjustment during the Daylight Saving

The Automatic DST/Summer Time adjustment

Press and hold **CLOCK** and **SNOOZE/DATE/**

SLEEP OFF at the same time at least 2 seconds

"and "OFF" appear in the display to show that Automatic DST/Summer Time adjustment has

adjustment by the unit (see above) are subject

djustment, cancel the Automatic DST/Summe

been canceled. The display returns to the clock.

• Changes to Automatic DST/Summer Time

to circumstances and laws in each country/

region. Should this interfere with desired

Time adjustment and set the DST display

country/region that does not use Daylight

Saving Time (summer time) must cancel

Automatic DST/Summer Time adjustment

manually as necessary. Customers living in a

Time (summer time) period

while the clock is displayed.

before using the unit.

can be canceled.

(summer time) begins

Saving Time (summer time).

Setting the clock for the first time

This unit is preset to the current EST (Eastern Standard Time) at the factory, and is powered by a backup battery. All you need to do the first time is just plug it in and select your time zone.

- 1 Plug in the unit. The current EST (Eastern Standard Time) appears in the display.
- 2 Press and hold TIME ZONE for at least 2 seconds.
- Area number "2" flashes in the display. **3** Press **TIME SET** + or – repeatedly to

select the number as follows:

| Area number | Time zone |
|-------------------|------------------------|
| 1 | Atlantic standard Time |
| 2 | Eastern standard Time |
| (default setting) | |
| 3 | Central standard Time |
| 4 | Mountain standard Time |
| 5 | Pacific standard Time |
| 6 | Yukon standard Time |
| 7 | Hawaiian standard Time |

4 Press • TIME ZONE to set.

Though the clock is correctly set at the factory, discrepancies may arise during transport or storage. If necessary, set the clock to the correct time by referring to "Setting the clock manually."

- To activate Automatic DST/Summer Time adjustment again, press and hold CLOCK and **SNOOZE/DATE/SLEEP OFF** at the same time
 - "and "On" appear in the display to show that Automatic DST/Summer Time adjustment has been activated. The display returns to the clock.

Setting the clock manually

- 1 Plug in the unit
- **2** Press and hold **CLOCK** until the year flashes in the display.
- **3** Press **TIME SET +** or repeatedly to set the vear
- 4 Press CLOCK.
- 5 Repeat steps 3 and 4 to set the month, day, hour and minute, and then press CLOCK.

The seconds start incrementing from zero.

- If you do not press any button for about 1 minute while setting the clock, the clock setting will be canceled. • A calendar is installed in this unit. When the
- date is set, the day of the week is automatically displayed. MON = Monday, TUE = Tuesday,

WED = Wednesday, THU = Thursday, FRI = Friday, SAT = Saturday, SUN = Sunday

To display the year and date

Press SNOOZE/DATE/SLEEP OFF (SNOOZE on the remote) once for the date, and press it again After a few seconds, the display will change back

to the current time automatically.

Setting the brightness of the display

Three levels of brightness are available by pressing BRIGHTNESS.

High (default) → Middle → Low

Even if you set the level of brightness to Low, it will be changed to Middle, while alarm is occurring.

Playing the radio

-Manual tuning

- **1** Press **RADIO BAND** to turn on the radio.
- **2** Press **RADIO BAND** repeatedly to select the desired band.

Each press changes the band as follows: \rightarrow FM1 \rightarrow FM2 \rightarrow AM \neg

FM1 and FM2 are the same frequency bands. 3 Press TUNING + or - (TUNE + or - on the remote) to tune into the desired

4 Adjust volume using **VOLUME** + or – (**VOL** + or – on the remote) To turn off the radio, press OFF

Tuning in to a station

station

The unit automatically scans AM or FM stations.

1 Follow steps 1 to 2 in "Manual tuning" and select the AM or FM band

2 Press and hold TUNING + or - (TUNE + or - on the remote).

+ : scans upward through the frequency bands. -: scans downwards through the frequency bands.

Scanning starts from the currently-tuned frequency. When a station is received, scanning stops.

3 Adjust the volume using **VOLUME +** or **-**(**VOL** + or – on the remote).


-Preset tuning

wish to preset.

You can preset up to 10 stations in FM (5 stations in FM1, 5 stations in FM2), and 5 stations in AM.

- Presetting a station 1 Follow steps 1 to 4 in "Manual tuning" and manually tune into the station you
- **2** Press and hold the desired **STATION SELECT - PRESET 1** to **5** buttons until the preset number display changes from flashing to fully lit.

Example: To preset FM 89.8 MHz onto the



After a while, the display will return to the current time

To preset another station, repeat these steps. To change the preset station, tune into the desired station and hold down the STATION • **SELECT ● PRESET 1** to **5** button. The new station will replace the previous station on the preset button

Tuning in to a preset station

- 1 Follow steps 1 to 2 in "Manual tuning" and select the AM or FM band.
- 2 Press one of the STATION SELECT
- PRESET buttons where the desired. station is stored. The preset station can also be selected by **PRESET** + or – on the remote
- **3** Adjust the volume using **VOLUME +** or **-**(**VOL** + or – on the remote).

-Auto preset tuning

1 Follow steps 1 to 2 in "Manual tuning" and select the AM or FM band.

2 Press and hold **RADIO BAND** until "AP"

- flashes in the display. 3 Press DISPLAY/MEMORY.
- The unit automatically presets the available channels in order.

To stop auto preset tuning, press $\ensuremath{\mathsf{OFF/ALARM}}$

To display the preset number and frequency of the current station

Press DISPLAY/MEMORY once for the preset number, and press it again for the frequency. If you press **DISPLAY/MEMORY** once only, the display shows the preset number for about 2 seconds, then changes to the frequency After a few moments, the display returns to the current time.

Improving the reception

FM: Extend the FM wire antenna fully to increase reception sensitivity.

AM: Connect the supplied AM loop antenna to the unit. Rotate the antenna horizontally for optimum reception.

Notes on radio reception

- Keep digital music players or mobile phones away from the AM loop antenna or the FM antenna, as this may lead to reception interference.
- When you are listening to the radio with an iPhone connected to the unit, interference with radio reception may occur.
- When you are listening to the radio while charging an iPod, interference with radio reception may occur.

If the FM broadcast is noisy, press **MODE** until "MONO" appears in the display, the radio will play in monaural and the sound will become

Playing an iPod

You can enjoy audio from iPod by connecting to this unit. To use an iPod, refer to the user's guide of your iPod.


If you are using an iPhone, iPhone 3G, iPhone 3GS or iPhone 4, attach the supplied universal dock adapter for iPhone, iPhone 3G, iPhone 3GS or iPhone 4 before connecting

The adapter number, 12, 15 or 19, is shown on the bottom-rear of the supplied universal dock adapters. (12) is for the iPhone, (15) is for the iPhone 3G & iPhone 3GS and (19) is for the iPhone 4. Check the adapter number before use.



Notes

- When inserting an iPod into the unit, be sure to use the universal dock adapter supplied with your iPod or commercially available from Apple Inc.
- The connector of the unit is exclusively for use with an iPod. If you use a device that does not match the connector, connect it to the AUDIO **IN** jack of this unit with the supplied audio connecting cable.
- Sony cannot accept responsibility in the event that data recorded on an iPod is lost or damaged when using an iPod connected to this unit.
- · For details of environmental conditions for operating your iPod, check the website of Apple
- 1 Attach the adapter for your iPod/iPhone.
- **2** Insert your iPod/iPhone into the connector of the unit



3 Press iPod & iPhone ►II.

The iPod begins to play automatically You can operate the connected iPod by this unit or the iPod buttons.

4 Adjust the volume using **VOLUME** + or – (**VOL** + or – on the remote).

| То | Press |
|---|---|
| Turn off the iPod | OFF, or press and hold iPod & iPhone ►II |
| Pause playback | iPod & iPhone ►II To resume play, press it again. |
| Go to the next track | ►► (forward) |
| Go back to the previous track | ◄ (backward)* |
| Locate a point while listening to the sound | ►► (forward) or ► (backward) while playing and hold it until you find the point. |
| Locate a point while observing the display | ►► (forward) or ► (backward) in pause and hold it until you find the point. |
| Go back to the previous menu | MENU** |

| Select a menu item or a track for playback | ♦ (up)/ ♦ (down)* | |
|---|---------------------------------|--|
| Execute the selected menu or begin playback | ENTER** | |
| Change to the shuffle mode | MODE | |
| * During playback this operation goes back to | | |

- ring playback, this operation goes the beginning of the current track. To go back to the previous track, press twice.
- **These operations are available only when using the supplied remote commander.

Notes

- When placing or removing the iPod, hold the iPod at the same angle as that of the connector on this unit, and do not twist or bend the iPod as connector damage may result.
- Do not carry the unit with an iPod set on the connector. Doing so may cause a malfunction. • When placing or removing the iPod, hold the
- Docking Tray securely with one hand and take care not to press the controls of the iPod by mistake.
- Before disconnecting the iPod, pause playback.

To use the unit as a battery charger You can use the unit as a battery charger.

Charging begins when the iPod is connected to Charging status appears in the display of iPod. For

details, see the user's guide of your iPod

On copyrights

iPhone, iPod, iPod classic, iPod nano, and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countrie

'Made for iPod," and "Made for iPhone" mean that an electronic accessory has been designed to connect specifically to iPod or iPhone. respectively, and has been certified by the developer to meet Apple performance standards Apple is not responsible for the operation of this device or its compliance with safety and regulatory standards. Please note that the use of this accessory with iPod or iPhone may affect wireless performance.

Setting the alarm

This clock radio is equipped with 3 alarm modes-iPod, radio and buzzer. Before setting the alarm, make sure to set the clock (see "Setting the clock for the first time")

To set the alarm

- 1 Press and hold ALARM SET A or B. "WAKE UP" appears and the hour flashes in the display
- 2 Press TIME SET + or repeatedly until the desired hour appears. To cycle the hour rapidly, press and hold **TIME**
- 3 Press ALARM SET A or B. The minute flashes
- 4 Repeat step 2 to set the minute.
- 5 Press ALARM SET A or B. The days of the week flash
- **6** Repeat step **2** to set the days of the week. You can select the days from the following three options Every day: MON TUE WED THU FRI SAT Week day: MON TUE WED THU FRI
- Week end: SAT SUN 7 Press - ALARM SET A or B. The alarm mode setting is entered
- **8** Press **TIME SET +** or repeatedly until the desired alarm mode flashes. You can choose one of 5 settings: "iPod", "FM1", "FM2", "AM" or "BUZZER." Set the alarm mode as follows: iPod: see "A Setting the iPod alarm."
- FM1, FM2 or AM: see "B Setting the radio - BUZZER: see "C Setting the buzzer alarm."

A Setting the iPod alarm

- **1** Perform steps **1** to **8** in "To set the alarm."
- 2 Press ALARM SET A or B to select "iPod" alarm mode. "VOLUME" appears in the display.
- **3** Press **TIME SET +** or **-** to adjust the
- 4 Press ALARM SET A or B. The setting is entered.
- **5** If "A" or "B" does not appear in the display, press • ALARM SET A or B

The iPod will sound at the set time. When using an iPod touch/iPhone

- To wake up to music stored in an iPod touch/ iPhone, connect the iPod touch/iPhone to the unit first, follow the steps above to set alarm time, and then select the music function.
- Even if the iPod alarm setting is complete, if you turn the iPod touch/iPhone power off before inserting the iPod touch/iPhone into the unit, the iPod alarm will not work.

B Setting the radio alarm

- **1** Perform steps **1** to **8** in "To set the alarm."
- 2 Press ALARM SET A or B to select radio band ("FM1", "FM2" or "AM"). Preset number flashes in the display
- **3** Press **TIME SET +** or to select the desired preset number corresponding the bands or "--". - -" is the last station received.
- 4 Press ALARM SET A or B. "VOLUME" appears in the display

6 Press - ALARM SET A or B.

The setting is entered.

5 Press **TIME SET** + or – to adjust the volume

- **7** If "A" or "B" does not appear in the display, press - ALARM SET A or B
- The radio will turn on at the set time.

C Setting the buzzer alarm

- **1** Perform steps **1** to **8** in "To set the alarm."
- 2 Press ALARM SET A or B to select "BUZZER" alarm mode. The setting is entered.
- **3** If "A" or "B" does not appear in the display, press • ALARM SET A or B

The buzzer will sound at the set time

The volume cannot be set for the buzzer alarm.

To confirm an alarm time setting Press **TIME SET +** or \neg . The setting will be

To change an alarm setting

Press and hold TIME SET + for at least 2 seconds to move the alarm time forwards. Press and hold **TIME SET** – for at least 2 seconds to move the alarm time back.

When you release the button, the changed time will flash for about 2 seconds. To change the alarm time again, press **TIME SET** + or – within these 2 seconds, otherwise the setting change will be fixed as displayed.

To doze for a few more minutes

Press SNOOZE/DATE/SLEEP OFF (SNOOZE on The sound turns off but will automatically come

on again after about 10 minutes You can change the snooze time by pressing SNOOZE/DATE/SLEEP OFF (SNOOZE on the remote) repeatedly within 4 seconds. The maximum length of the snooze time is 60 minutes.

To stop the snooze timer, press **OFF/ALARM RESET** (**OFF** on the remote)

To stop the alarm

Press **OFF/ALARM RESET** (**OFF** on the remote) to turn off the alarm.

The alarm will sound again at the same time the

To deactivate the alarm Press • ALARM ON/OFF A or B to turn off the

alarm A or B indicator from the display

To activate the alarm Press • ALARM ON/OFF A or B to turn on the alarm A or B indicator in the display

- With the alarm mode is set to iPod, when the alarm time met, if iPod is not attached to the
- unit, the alarm sound will be the buzzer. • The alarm function works as usual on the first and last day of Daylight Saving Time (summer time). As a result, if the Automatic DST/ Summer Time adjustment is set and the alarm is set at a time skipped when the Daylight Saving Time begins, the alarm is skipped; if the alarm is set to a time that overlaps when Daylight Saving Time ends, the alarm will
- sound twice. • If the same alarm time is set for both alarm A
- and B, alarm A takes priority. • If there is no operation while the alarm is occurring, the alarm will stop after about

60 minutes

Note on the alarm in the event of a power interruption

In the event of a power interruption, the alarm will work until the battery is totally discharged However, certain functions will be affected as • The backlight will not light up.

- If the alarm mode is set to iPod or radio, it will change to buzzer automatically. • If **OFF/ALARM RESET** is not pressed, the alarm
- will sound for about 5 minute \bullet If " $\mbox{``cp"}$ appears in the display, the alarm will not sound in the event of a power interruption. Replace the battery if "△¬" appears.
- The snooze function cannot be set during a power interruption. If the snooze function has already been set and a power interruption occurs, the snooze function will not work.
- During a power interruption, each alarm will sound at the set time only once

Setting the sleep timer

You can fall asleep to music, etc., using the sleep timer. The unit stops playback or radio automatically after a preset duration.

- **1** Press **SLEEP** while the unit is turned on. "SLEEP" appears and the sleep time flashes in
- the display **2** Press **SLEEP** to set the sleep timer

duration Each time you press **SLEEP**, the duration (in

minutes) changes as follows:

 $90 \longrightarrow 60 \longrightarrow 30 \longrightarrow 15$ — OFF ←

The display returns to clock mode for about 4 seconds after you have finished the duration setting and released **SLEEP**, and then the sleep

The unit plays for the duration you set, and then stops.

To turn off the unit before the preset Press SNOOZE/DATE/SLEEP OFF (SNOOZE on

To change the sleep timer setting You can press SLEEP repeatedly to select the

desired sleep timer setting even after the sleep

the remote) or OFF/ALARM RESET (OFF on the

timer has been activated. To deactivate the sleep timer Press **SLEEP** repeatedly to set the sleep timer to

"OFF" in step 2.

Other useful functions

To get the MEGA Xpand effect Press MEGA Xpand. "MEGA Xpand" appears in the display. You can get the effect of expansion of the sound field. To return to normal sound, press

To reinforce the bass sound Press MEGA BASS. "MEGA BASS" appears in the display. You can get the effect of bass of high


quality sound. To return to normal sound, press

Connecting external equipment

the button again.

the button again.

To listen to sound 1 Connect the AUDIO IN jack of the unit to the line out jack or headphone jack of the external equipment using the audio



- **2** Press **AUDIO IN** to display "AUDIO IN." **3** Play the equipment connected to the
- AUDIO IN jack. **4** Adjust the volume using **VOLUME** + or –

(**VOL** + or – on the remote).

First the preset number, then the frequency of the last station is shown in the display. To return to the iPod

Press iPod & iPhone ►II

Press RADIO BAND.

To return to the radio

To stop listening

away from the unit.

Press OFF/ALARM RESET (OFF on the remote), and stop playback on the connected unit.

case, use a cord suitable for the external equipment you are using. • When you listen to the radio with external equipment connected, turn off the connected equipment to prevent noise. If noise occurs, even when the equipment is turned off,

disconnect and place the external equipment

· Refer also to the connected equipment's manual

be used with some external equipment. In this

• The supplied audio connecting cable may not

Download from Www.Somanuals.com. All Manuals Search And Download

Free Manuals Download Website

http://myh66.com

http://usermanuals.us

http://www.somanuals.com

http://www.4manuals.cc

http://www.manual-lib.com

http://www.404manual.com

http://www.luxmanual.com

http://aubethermostatmanual.com

Golf course search by state

http://golfingnear.com

Email search by domain

http://emailbydomain.com

Auto manuals search

http://auto.somanuals.com

TV manuals search

http://tv.somanuals.com