

# Night Hawk Extra Wireless Outdoor Camera with Night Vision



- Quality color surveillance suitable for home, office and retail security
- DIY - no cable installation required, includes choice of 9V battery or power adapter
- Professional quality image
- Infra-red LEDs for night vision
- Switchable to 4-channels to avoid interference
- 2.4GHz wireless transmission to receiver (sold separately)
- Signal range of 100m/330ft\*
- **No receiver included**

\*Actual transmission range may vary according to location, interference & building construction





# Night Hawk Extra Wireless Outdoor Camera with Night Vision

Create your own security solution:

- Add to the Swann Night Hawk Wireless Outdoor Camera (SW-P-WOC) or MicroCam II (SW-P-MC2/A) for a DIY wireless surveillance solution with no cabling required
- Ideal addition to an existing wireless security solution

Place the camera anywhere within reception range up to 100m/330ft\*

- Under the eaves around the house
- Monitor the pool, yard, entrances, garage and driveway
- Protect your business, store or warehouse

Mains power adapter included

Note: IP Ratings stated on the front panel are for cameras only.\*Actual transmission range may vary according to location, interference & building construction.



## How the extra camera works:



### Technical Specifications

#### Camera Specifications

Image Sensor: 1/3" CMOS (8.5mm)

Video Format: NTSC (USA);

PAL (AU, UK, EU)

CMOS Total Pixels: 628 x 582pixels (PAL);  
510 X 492pixels (NTSC)

Minimum Illumination: 0 Lux

Horizontal Resolution: 380 TV lines

Frequency: ISM 2400 - 2483MHz 4CH

Channels: CH1 = 2414MHz

CH2 = 2450MHz

CH3 = 2468MHz

CH4 = 2432MHz

Output Power: 10mW (3mW in USA)

Power Supply: +8VDC

Power Consumption Current: 65mA/105mA (IR ON)

Operation Temperature: 0°C-45°C (32°F-113°F)

Operation Humidity: 85% RH

Dimensions (W) x (L) x (H): 53 x 43.5 x 64mm  
(2" x 1 3/4" x 2 1/2")

Weight: 197g (7oz)

Unobstructed Effective Range: 100m\*

### Package Contents

2.4GHz Night Hawk Color Camera

1 x Power Adapter

1 x 9V battery

Quickstart Manual

\*Actual transmission range may vary according to location, interference & building construction.



www.swannsecurity.com

Please note that the information contained within this document is subject to change without notification.

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>