



Passport 37 Convertible Headset



- Noise canceling microphone greatly reduces background noise for a professional sounding call
- Durable construction to endure the stress of the 24/7 call center
- Flexible gooseneck boom maintains position for consistent voice input quality
- Sturdy quick disconnect allows fast and easy detachment from lower cord for greater mobility
- Optional, adjustable headband secures positional adjustment, won't slide out of position
- Easy conversion between styles- no tools needed

Compatibility:

- Passport 37V compatible with Passport V-series amplifiers and direct connect cords
- Passport 37P compatible with VXI Passport P-series and Plantronics amplifiers and direct connect cords
- Passport 37G compatible with VXI Passport G-series and GN Netcom amplifiers and direct connect cords



w/ headband



Passport 37

2 YEAR *Unconditional* WARRANTY

TRANSMIT SPECIFICATIONS

Microphone type: Noise canceling electret
 Impedance: Low (~300Ohm)
 Sensitivity: -36dB / Pa. (=16mV)
 DC current: 0.5mA. (@ 3V./2.2k Ohm)
 Attenuation of room noise: 12dB or more

RECEIVE SPECIFICATIONS

Impedance: 300 Ohms
 Sound pressure: 96 dB at 1 kHz / 1mW
 Frequency response: 300Hz to 3400Hz
 Sound pressure peak max: 112 dB (limited by built in circuit)

MECHANICAL SPECIFICATIONS

Cables: High strength 4 conductor cable, PVC insulation, polyurethane jacket
 Connectors: 4 pin quick disconnect
 Microphone boom: Flexible with positioning memory
 Headband: ABS plastic, stainless steel band

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>