

ULTRA

X-Finity™ Series Power Supplies 2nd Generation

X-Finity™ PSU - Featuring FlexForce Cables

Featuring phenomenal power distribution and an easy to manage cabling system that promotes extraordinary airflow, this sizzling new X-Finity power supply features dual rail technology for better power distribution and stability. You'll get the smooth, trouble-free performance that's perfect for your powerful gaming system. The incomparable FlexForce cables are dressed in a great looking titanium silver finish. Their specially engineered design promotes easy cable management resulting in 30% better airflow than ordinary cables. Cables are easily routed underneath the motherboard, behind drive bays... anywhere that gets typically unsightly power supply cables out of the way of airflow. Accommodates both AMD and Intel CPUs. 24/20-pin motherboard connection. 4-pin Molex connectors. 4-pin floppy power connectors. PCI Express, SATA 4-pin and 8-pin 12V P4 and EPS connectors. Versatile. Dependable. Affordable. The X-Finity FlexForce ATX power supply.

Features

- 120mm Fan (Dual 80mm for 600W Models)
- Thermostatically controlled fans for low acoustic noise.
- Dual Rail Technology
- FlexForce Cabling Technology
- 20/24 Pin Motherboard Connector
- 4 - SATA Connectors (2 - XF350BK)
- 2 - PCI Express Connectors (1 - XF350BK)
- 1 - 8-Pin EPS Connector (N/A on XF350BK)
- Meets ATX v2.2, v1.3 and ATX 12V v2.03 Specifications
- Power Protections:
Short Circuit, In-rush Current,
Thermal Overload, Over-Temperature,
Over-Voltage, Over-Current, Under-Voltage

Featuring
FLEXFORCE Slim Cable



120mm
Cooling Fan



OUTPUT

350 Watt

Max Output Current	+3.3VDC	+5VDC	+12VDC1	+12VDC2	-12VDC	+5VSB
	22A	21A	10A	15A	0.5A	2.0A
Max Combined Wattage	130 W		240W		7.2 W	10 W
	333 W			17.2 W		
	350 W					

OUTPUT

500 Watt

Max Output Current	+3.3VDC	+5VDC	+12VDC1	+12VDC2	-12VDC	+5VSB
	30A	30A	16A	18A	0.6A	2.5A
Max Combined Wattage	160 W		384W		7.2 W	12.5W
	481 W			19.7 W		
	500 W					

OUTPUT

600 Watt

Max Output Current	+3.3VDC	+5VDC	+12VDC1	+12VDC2	-12VDC	+5VSB
	25A	30A	18A	20A	0.6A	2.5A
Max Combined Wattage	160 W		420 W		7.2 W	12.5W
	581 W			19.7 W		
	600 W					

500 Watt ATX Power Supply - Black

Model: X2F500BK Part #: ULT31845
UPC#: 022769318455
Weight: 5 lbs. Dimensions: 9x4x7"



500 Watt ATX Power Supply - Blue

Model: X2F500BL Part #: ULT31846
UPC#: 022769318462
Weight: 5 lbs. Dimensions: 9x4x7"



500 Watt ATX Power Supply - Titanium

Model: X2F500TI Part #: ULT31844
UPC#: 022769318448
Weight: 5 lbs. Dimensions: 9x4x7"



600 Watt ATX Power Supply - Black

Model: X2F600BK Part #: ULT31848
UPC#: 022769318486
Weight: 6 lbs. Dimensions: 9x4x7"



600 Watt ATX Power Supply - Blue

Model: X2F600BL Part #: ULT31849
UPC#: 022769318493
Weight: 6 lbs. Dimensions: 9x4x7"



600 Watt ATX Power Supply - Titanium

Model: X2F600TI Part #: ULT31847
UPC#: 022769318479
Weight: 6 lbs. Dimensions: 9x4x7"



350 Watt ATX Power Supply - Black

Model: X2F350BK Part #: ULT31842
UPC#: 022769318424
Weight: 5 lbs. Dimensions: 9x4x7"

**NOT SLI™ READY



ULTRA
1-800-830-0051

www.ultraproducts.com

ULTRA

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>