

Avenview



KVM-C5 Series

Part #: KVM-C5-R

Part #: KVM-C5-S

Description

KVM-C5 Series extender solution can extend the KVM control (Keyboard / Video / Mouse) up to 300m (1000 ft) over a single Cat5e cable. Built-in matured KVM technology and video signal processing can extend KVM signal correctly and provide a premium video resolution of up to 2048x1536@200m (675 ft).

KVM-C5 solution is perfect for centralized computer management. By adapting KVM switch or KVM Drawer, you can control multiple computers on a rack locally or in a remote location. This unit is also suitable for office to secure all PCs in a computer room and extend KVM console to every desktop to ease the maintenance, save desktop space and prevent PC to be accessed through USB or other network.

Built-in smart keyboard and mouse simulation, it can support advanced function of Logitech or Microsoft mouse and work on any PS/2 PC or by using a USB to PS/2 converter to extend a USB interface computer (Ex: SUN / Mac).

The KVM-C5 extender solution is designed not only to provide accurate KVM signal, but also easy to install. It is equipped with a magnetic pad and a attachable metal plate, so you can place the KVM Extender very easily on the surface of PC or any preferred place like wood or concrete.

Features

- Extend the Keyboard / Video / Mouse of PC or KVM Switch by Cat 5 / 5e / 6 cable
- Supported VGA Resolution and Distance (distance is based on UTP cable skew 30ns/100m):
 - a. 1024x768 @ 300m (1000ft)
 - b. 1280x1024 @ 300m (1000ft)
 - c. 1600x1200 @ 300m (1000ft)
 - d. 1920x1440 @ 200m (650ft)
 - e. 2048x1536 @ 200m (650ft)
- Supports VGA, SVGA, XGA, TFT-LCD with DDC2B
- Supports PS/2 type PC or KVM switch application
- Plug & Play
- Supports MD-DOS, Windows, FreeBSD, Linux, Unix, Novell
- Auto KVM model detection for optimum setup
- Supports advanced function of Logitech and Microsoft Mice
- Manual signal control (Gain & Focus) for different extended distance and achieving the best quality
- Integrated 3-in-1 KVM cable for PC or KVM switch connection
- Transmitter (KVM-C5-S) and Receiver (KVM-C5-R) built with FOUR color LEDs to indicate system status
- Transmitter is equipped with magnetic pad and metal plate for easy installation


System Devices and Functions

Transmitter KVM-C5-S

- Built-in one set of Keyboard, Mouse and Video
- Built-in one RJ45 port for system output which can be connect by Cat 5/5e/6 cable and send KVM signal to System Receiver.

Receiver KVM-C5-R

- Receive KVM signal through RJ45 port
- Built-in video control (Gain & Focus)



Connection Diagram of KVM-C5-Series

Cable and Accessories




3-in-1 KVM Cable –CBK1512T (Included)

Package Content

KVM-C5 (Transmitter & Receiver Set)	<ul style="list-style-type: none">• KVM 1 Port Transmitter• KVM 1 Port Receiver• KVM Cable 1m• AC 5V 1A Adapter• User Manual
KVM-C5-S Receiver	<ul style="list-style-type: none">• KVM 1 Port Receiver• KVM Cable 1m• AC 5V 1A Adapter• User Manual

Specifications

	KVM-C5-S	KVM-C5-R
Description	PS/2 KVM Transmitter	PS/2 KVM Receiver
Keyboard	PS/2 Female	
Mouse	PS/2 Female	
Video	D-Sub 15 Female	
System Link	RJ45	
LED	4 Color LEDs	
Supported Resolution and Distance	1024 x 768 @ 300m (1000ft) 1280 x 1024 @ 300m (1000ft) 1600 x 1200 @ 300m (1000ft) 1920x1440 @ 200m (650ft) 2048 x 1536 @ 200m (650ft)	
Power Consumption	PS/2 AC 7.5V 250mA	AC 7.5 250mA
Dimensions	62 x 113 x 29 mm	
Operating Temperature	0 - 50°C	
Storage Temperature	-20 - 60°C	
Humidity	10 – 90%	



Copyright 2007, Avenview® Inc. All rights reserved.
Features, availability and specifications are subject to change without notice.

The logo for Avenview Inc. features the word "Avenview" in a bold, dark blue, sans-serif font. A small red square icon with a white crosshair is positioned above the letter 'v'. The entire logo is contained within a white rectangular box with a slight drop shadow and a red underline at the bottom.

Avenview

Avenview Inc.
info@avenview.com
www.avenview.com

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>