

# DAB Lite radio

Dualit's Lite radio offers you the build and acoustic quality you would expect from a Dualit DAB radio. Advanced technology delivers maximum performance without distortion via the 6 Watt, 3 inch speaker and bass reflex port. Choose from interference free DAB or FM with RDS where digital reception is not available. An impressive 20 presets (10 for each mode) allows you to quickly and easily access your favourite radio stations at the touch of a button. The Lite radio can be either mains powered or battery operated with a built-in battery charger and an energy efficient switch mode mains adaptor with interchangeable plugs for both UK and Europe. Designed to meet Dualit's high standards, the Dualit Lite radio is perfectly compact and portable, ideal for in or outdoor listening.

## Features:

- DAB & FM reception with RDS
- 20 presets (10 for each mode)
- High performance 6 Watt, 3 inch speaker
- Bass port for rich sound
- Powered via mains or NiMH rechargeable batteries (not included)
- Kitchen egg timer
- Alarm with snooze and sleep options
- Battery charger and energy efficient UK and European plugs



## DAB kitchen radio

Dimensions (cm)	22.5 x 15.5 x 9
Weight (Kg)	1.15
Colours	Chrome, Black & Cream

### Technical specification:

#### Frequency range

DAB: band III

FM: 87.5 ~ 108 MHz / step 0.1 MHz

#### Tuning

Auto station search in FM and DAB mode

DAB - Quick & full range scan options

Manual tuning option

10 station presets for each mode

FM with RDS

#### Acoustics

3 inch 8 OHM full range mono speaker

6 WRMS @ 0.15%THD

Frequency response: 40 Hz - 14 kHz

Dynamic range control

Bass port

#### Display

LCD white on blue display

Display automatically dims to save power

Battery status indicator:

Charging (flashing green)

Fully charged (solid green)

Low battery (flashing red)

Batteries ok (solid red)

#### Clock, alarm and timer settings

24hr clock display

99 minute kitchen/egg timer

Alarm sounds: DAB/FM or buzzer

Alarm settings: once, everyday, weekdays

and weekends

Sleep function (1 - 120 minutes)

Snooze function (5 minutes)

#### Inputs/Outputs

DAB / FM RDS telescope rotating antenna

Headphone 3.5mm output jack

#### Power

Mains or battery operated

(6 x AA batteries not included)

Built-in charger for rechargeable batteries

Battery life: DAB & FM: 9 hrs life

Charge time: 3 hours

230-240V a.c. 12V d.c. switch mode adaptor  
with UK & European plugs



# Dualit®

**Dualit Limited**

County Oak Way Crawley West Sussex RH11 7ST

t: +44(0)1293 652 500 f: +44(0)1293 652 555 info@dualit.com www.dualit.com

## Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>