

Electronic Timers

Four Program (Model #9400) Eight Program (Model #9408)

Quick Start	3
Detachable Electronics	4
Detailed Set Up	5
Time and Day	6
Watering Time	12
Watering Days	20
Skip Days	27
Changing a Program	34
Program Review	35



Gilmour GARDENIAG INAGVATION

12:00A Sunday

To Set Press OK

CA HRS OR AM/PM: PHESS of & # 2 SEC

The 4 Program Electronic Timer (Model #9400) offers you up to four different programs and the 8 Program Electronic Timer (Model #9408) offers you up to 8 different program options.

You can water every day, more than once a day, every other day or every third day.

Models #9400 & #9408

Download from Www.Somanuals.com. All Manuals Search And Download.

Quick Start

Programming the timer is quick and easy. Just answer the questions flashing on the screen. Press "OK" to start programming. Use "Arrow" keys to review functions to set and "OK" to select that function. Then as they flash, use the "Arrow" keys to set hours, minutes, am/pm, or day and "OK" to accept that setting.

Gilmour

12:00A Sunday

To Set Press OK

CA HES OR AMPM: PHESS S. & \$ 2 SEC.



Models #9400 & #9408

Detachable Electronics Easy to Program

The electronics portion of the timer can be removed from the valve section for easier programming. Press the gray buttons on each side of the timer body to release the electronics.

After programming, slide the electronics back over the valve until the gray buttons snap back into place.



Just squeeze the side grips and pull to remove.



Models #9400 & #9408

Gilmour GARDING INNOVATION

To Set Press OK

24 HRS OR AM/PM: PHESS or & 1 2 SEC.

Press any key (including On/Off) to activate the screen.

On/Off is used to manually open or close the valve.

The display will power down if no keys are pressed within 2 minutes.



Detailed Set Up
Time and Day
Models #9400 & #9408


12:00A Sunday

To Set Press OK

The screen will be flashing "To Set Press OK."

•••••

Press "OK" to begin.




Set Time & Day > OK

Set Program 1 AV

"Set Time & Day" will be flashing.

Press "OK" to set.



Models #9400 & #9408


Set Hour Now

12:00 A ^ V Then OK

"Hours" will flash.

Use up and down arrows to set the hour.

Press "OK" to set.




Set Minutes Now

12:00 A ^ V Then OK

"Minutes" will flash next.

Use up and down arrows to set the minutes.

Press "OK" to set.




Set AM OR PM Now

12:00 A ^ V Then OK

"A" for a.m. or "P" for p.m. will be flashing.

Choose either "A" for a.m. or "P" for p.m. with arrow keys.




Set Day Av & OK

12:00 A Sunday

"Day of Week" will be flashing.

Choose day of week with arrow keys.




Models #9400 & #9408

Set Program 1 > OK

Set Program 2 ^ V

"Set Program 1" will be flashing.



Models #9400 & #9408


Program 1

Set Start Time 1

12:00 A **^ V** Then OK

"Hours" will flash.

Use up and down arrows to set the hour.



Models #9400 & #9408


Program 1

Set Start Time 1

12:00 A **^V** Then OK

"Minutes" will flash.

Use up and down arrows to set the minutes.



Models #9400 & #9408


Program 1

Set Start Time 1

12:00 A **^ V** Then OK

"A" for a.m. or "P" p.m. will be flashing.

Choose either "A" for a.m. or "P" for p.m. with arrow keys.




Models #9400 & #9408

Program 1

Set End Time 1 > OK

Days to Water ^v



Models #9400 & #9408


Program 1

Set End Time 1

12:00 A **^ V** Then OK

"Hours" will flash.

Use up and down arrows to set the hour.



Models #9400 & #9408


Program 1

Set End Time 1

12:00 A ^ V Then OK

"Minutes" will flash.

Use up and down arrows to set the minutes.



Models #9400 & #9408


Program 1

Set End Time 1

12:00 A **^ V** Then OK

"A" for a.m. or "P" p.m. will be flashing.

Choose either "A" for a.m. or "P" for p.m. with arrow keys.



Models #9400 & #9408


Program 1

Days to Water

Set Skip Days AV

"Days to Water" will be flashing.

Choose either "DAYS TO WATER" by pressing "OK" or arrow down to select "SET SKIP DAYS."



Models #9400 & #9408


<u>Program 1</u>

Water on Sun Yes

Set Av Then OK

If "Days to Water" is selected, Water on Sunday" with "Yes" flashing is shown.

Use up and down arrows to choose "Yes or No."



Models #9400 & #9408


Program 1

Water on Mon

Set Av Then OK

Water on Mon with "Yes" flashing is shown.

Use up and down arrows to choose "Yes or No."



Models #9400 & #9408

Program 1

Water on Tue > Yes

Set Av Then OK

Repeat for remaining days of the week, using arrow keys to set "Yes" or

"No" and "OK."



Gilmour CAPDINING INNOVATION

Water on Tue Set & OK

Models #9400 & #9408

Gilmour GARDENING HANGVATION

Set Skip Days >O Finished PGM 1

Program 1

Water on Sat > Yes

Set Av Then OK

After Saturday is complete, "Set Skip Days" will be flashing.

Press down arrow to choose "FINISHED PGM 1" and



Set Additional Programs Models #9400 & #9408 Program 2 **Set Program 2** OK **Set Program 3** Gilmour GARDENING INNOVATION "Set Program 2" will be flashing. Press "OK" to begin programming Program 2. Follow the steps used for Program 1.

Set Additional Programs

Models #9400 & #9408


Program 2

Set Program 2 OK

Set Program 3

If not setting Programs 2, 3, 4, 5, 6, 7 or 8, use arrow keys to move to "Review Programs" or

"Finished."




Models #9400 & #9408

Program 1

Set Skip Days > OK

Finished PGM 1

If Set Skip Days was chosen, "Set Skip Days" will be flashing.



Models #9400 & #9408


Program 1

Water Ea 2nd Day

Set ^v & OK

If using "SET SKIP DAY," Timer will begin watering on the day program is set.

For example, if you program your timer on Sunday, and you choose "every 2nd day" then your watering schedule will be:



Models #9400 & #9408

Program 1

Water Ea 2nd Day

No Set Av & OK

You can water every 2nd day or every 3rd day.

Use up and down arrows to choose "Yes or No" to "water every 2nd day" *OR* "water every 3rd day."

Models #9400 & #9408


Program 1

Finished PGM 1

Set Start Time 1

"Finished PGM 1" will be flashing.

Press OK.



Set Additional Programs Models #9400 & #9408 Program 2 **Set Program 2** OK **Set Program 3** Gilmour GAPDING INNOVATION "Set Program 2" will be flashing. Press "OK" to begin programming Program 2. Follow the steps used for Program 1.

Set Additional Programs


Models #9400 & #9408

Program 2

Set Program 2 OK

Set Program 3

If not setting Programs 2, 3, 4, 5, 6, 7 or 8, use arrow keys to move to "Review Programs" or "Finished."



Models #9400 & #9408

Gilmour

Nater Ea 3rd Day No Set & OK

NOTE: If Set Skip Days is set to yes, you cannot choose Watering Days in the same program.

To change a program back to *Watering Days*, go to Set Skip Days and choose "No" to water each 2nd and 3rd days.



Changing a Program

Models #9400 & #9408

Gilmour CAPDINING INNOVATION

To make changes to a program, press any key (including On/Off) to activate the screen.

Press "OK."

Use the down arrow to choose PGM Set/RePgm and Press "OK."
Use arrow keys to scroll through programs.
Press "OK" to choose program to reset.

Repeat programming steps.

GIMOUT, GARDENING INNOVATION

Program Review

Models #9400 & #9408

With "Review Program" flashing, Press "OK."


To review Program 1, press down arrow key. Screen will show letters for each day of the week and "Y" for yes or "N" for no for each day. To the right it will show start time on top and stop time on bottom.

Press arrow key to review Programs 1 through 8.

After Program 8, "Review Done" flashes. Press "OK" to exit this section.

"Finished" will flash.

Press "OK" if finished.



Free Manuals Download Website

http://myh66.com

http://usermanuals.us

<u>http://www.somanuals.com</u>

http://www.4manuals.cc

http://www.manual-lib.com

http://www.404manual.com

http://www.luxmanual.com

Golf course search by state

http://aubethermostatmanual.com

http://golfingnear.com

Email search by domain

<u>http://emailbydomain.com</u> Auto manuals search

http://auto.somanuals.com

TV manuals search

<u>http://tv.somanuals.com</u>