

AMILO Pa 2510-25P

With AMD Turion™64 X2 Mobile Technology

CUZ:N-NOR-MLVAR001

Issue September 2007

Pages 2



Features

- AMD Turion™ X2 Mobile Technology TL-50
- 2048MB DDR II 667Mhz (2 x 1024MB), max 2GB
- 250GB Serial ATA HDD
- Dual Layer DVD±R±RW drive (8.5GB)
- 15.4" TFT LCD WXGA display
 - BrilliantView
 - High brightness
 - Resolution of 1280 x 800
- ATI Mobility Radeon® Xpress 1200 graphics with up to 256MB shared memory
- 4-in-1 card reader supports SD/MS/MMC/MSPRO multimedia storage cards.
- 3 x USB 2.0, SPDIF, 2 x Audio, VGA
- WLAN 802.11b/g (54 Mb/s) & 10/100 LAN
- Silent Mode functionality
- Windows® Vista Home Premium FI / SWE / NOR / DK / ENG
- Software included:
 - Microsoft Works 9.0
 - Microsoft Office Home & Student 60 Day Trial Version
 - Vista DVD Playback Pack
 - Nero 7 Essentials
 - Norman Virus Control 3 years



Operating system

Microsoft® Windows® Vista Home Premium
FI / SWE / NOR / DK / ENG

Fujitsu Siemens Computers recommends Microsoft® Windows® Vista Home Premium

Application Software

Microsoft® Works 9.0
Microsoft® Office Home & Student 60 Day Trial Version
Vista DVD Playback Pack
Nero 7 Essentials
Adobe Acrobat Reader
Norman Virus Control with 3 years free updates

Quick Start Guide, Manual (on DUDVD), Safety Guide and Warranty Guide

Drivers and Utility

Drivers and Utility DVD included.
Updates downloadable at:
<http://www.fujitsu-siemens.com>

System, processors, architecture

Chipset: AMD M690V + SB600
CPU: AMD Turion™64 X2 Mobile
Technology TL-50, 1600Mhz
35W, 512KB L2 Cache, Socket S1

Memory

2048MB DDR II, 2 x 1024MB. Max supported memory 2GB
2 SO-DIMM memory slots (no memory on board)

Storage devices/drives

HDD:
250GB SATA hard disk
ODD:
8x Multi-format DVD Burner DL (Double Layer)
Read speed: CD-ROM 24x, DVD-ROM 8x
Write speed: CD-R 24x, CD-RW20x, DVD+R6x,
DVD-R 6x, DVD+RW 4x, DVD-RW 4x,
DVD+R DL (Double Layer 8.5GB) 2,4x

Display

15.4" TFT WXGA, BrilliantView
Resolution 1280 x 800
Brightness (typ.) 180cd/m
Contrast (typ.) 300:1
ISO 13406-2 class II

Graphics

ATI Mobility Radeon® Xpress 1200
up to 256MB shared VGA memory

Pointing device, keyboard & control buttons

Touchpad with a left and right mouse button
Full size keyboard with Nordic layout
Power button / lid switch

Status indicators

The notebook has 7 status icons:
Caps lock
Num lock
Media activity (ODD/HDD)
Silent mode
Power status
Battery status
WLAN communication on/off

ACPI functions

S1 standby (LCD off)
S3 save to RAM
S4 save to disk
S5 complete off
Silent Mode

I/O Interfaces

3x USB 2.0 ports
1x VGA, 1x modem, 1x LAN, 1x WLAN
1x ExpressCard slot (34/54mm)
1x line in shared with microphone in
1x headphone out shared with SPDIF
1x power supply
1x 4-in-1 card reader SD/MS/MMC/MSPRO

Communications

Built-in 56K, V.92 fax modem
10/100Mbps LAN
Integrated Wireless LAN (WLAN) solution 802.11b/g:
- speeds up to 54Mbps

Audio

Integrated in chipset (7.1 SPDIF), 2 built-in speakers,
microphone in shared with stereo in,
headphone combined with SPDIF support

Launch Keys

2 Launch Keys located on top of the keyboard enabling the user to launch the following applications:
- Media Player
- Silent mode (reduce noise level / fan speed by reducing the CPU & VGA performance)

Hot Keys

The following hotkeys or key combinations are available:
Fn-F1 Suspend
Fn-F3 Mute
Fn-F4 Display toggle, switches display output between display screen and external monitor or dual view
Fn-F5 Volume up
Fn-F6 Volume down
Fn-F7 Increase display brightness
Fn-F8 Decrease display brightness
Fn-F9 Disable touch pad

Power system

Li-Ion battery, 6 cell: 10.8 / 11.1V / 4000mAh
battery runtime: Approximately 3h
depending on usage¹
External AC adapter: 110 - 240V AC, 50 - 60Hz
Output: 65 W with 20V DC, 6A
Dynamic charge supported
ACPI 2.0 supported

Dimensions and weight

Dimension (H x W x D): ~28 - ~36 x 358 x 255mm
Weight: 2.8 kg with 6 cell battery²

Operating conditions

Operational: 5°C to 35°C (ambient temperature)
10% to 90% relative humidity, non-condensing

Warranty & Support

Warranty and support according to country terms

- 1) Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Recharge time varies depending on usage.
- 2) Weight may vary depending on actual configuration

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>